



**ODISHA POWER TRANSMISSION CORPORATION
LIMITED**

**OFFICE OF THE SR. GENERAL MANAGER,
CENTRAL PROCUREMENT CELL,
JANPATH, BHUBANESWAR - 751022**

**TENDER SPECIFICATION NO. SR.G.M -CPC-POWER TRANS-57/2022-23
TOWARDS PROCUREMENT OF**

40 MVA, 220/33 KV POWER TRANSFORMER –4 NOS.



ODISHA POWER TRANSMISSION CORPORATION LIMITED
Janpath, Bhubaneswar-751022,Orissa.

NOTICE INVITING TENDER NO. – 57/2022-23

For & on behalf of Odisha Power Transmission Corporation Limited (OPTCL), Senior General Manager, CPC (**Central Procurement Cell**) invites tenders from reputed manufacturers under two-part bidding system for Supply of the Transformers as per the following details.

Tender Specification No.	Description	Quantity	Last Date & Time of Submission of Bid.	Date & Time of Opening of Techno-commercial Bid
Sr. G.M-CPC-POWER TRANS-57 /2022-23	40 MVA, 220/33 KV Power Transformer	04 (Four) Nos	Dt. 26.07.2023 up to 15:00 Hrs (IST)	On Dt. 27.07.2023 on/after 11.00 Hrs (IST)

The interested bidders would be required to enroll themselves on the tender portal www.tenderwizard.com/OPTCL. Complete set of bidding documents are available at www.tenderwizard.com/OPTCL from Dt.**27.06.2023**, 11 Hrs. to Dt. **26.07.2023**, 11.00 Hrs. Interested manufacturers may visit OPTCL's official web site <http://www.optcl.co.in> and www.tenderwizard.com/OPTCL for detail specification.

N.B: -All subsequent addendums / corrigendum to the tender shall be hosted in the www.tenderwizard.com/OPTCL only.

SENIOR GENERAL MANAGER [C.P.C.]



ODISHA POWER TRANSMISSION CORPORATION LTD.,
REGD. OFFICE: JANPATH, BHUBANESWAR – 751 022,
ODISHA, INDIA.

e-NOTICE INVITING TENDER NO. – CPC-57/2022-23

For & on behalf of Odisha Power Transmission Corporation Limited (OPTCL), Senior General Manager, CPC (Central Procurement Cell) invites tenders from reputed manufacturers under two-part bidding system for Supply of the Transformers as per the following details.

SL. No.	Tender Specification No.	Description of materials.	Quantity In Nos.	Earnest Money Deposit (In Lacs.)	Cost of Tender Spec. document	Tender Processing fee.	Last date of submission of tender	Date of opening of tender	Pre-bid Query Meeting
1	S.G.M-CPC-P.T-57/2022-23	40 MVA, 220/33 KV Power Transformer	4 (Four) Nos.	Rs.23,11,361/-	Rs. 25,000+ 18% GST = Rs 29,500/- (Rupees Twenty Nine Thousand five hundred only)	Rs 5,000/ + GST@ 18% (=Rs 5,900/-)	Up to Dt.26.07.2023 up to 15:00 Hrs (IST)	On Dt.27.07.2023 on/after 11.00 Hrs (IST)	On Date: 07.07.2023 at 11.30 Hrs. at CPC conference Hall, 1 st floor

1. The bidders who want to submit bid(s), shall have to pay the tender paper cost (non-refundable) for amount Rs 29,500/- (including GST @ 18%) online through e-payment gateway link provided in e-tender portal (by using Net Banking, Debit Card or Credit Card). The online payment can be made prior to last date & time of submission of online tender.
2. The bidders shall also have to pay a non-refundable amount of Rs.5900/- (Rupees Five thousand Nine Hundred only inclusive of GST @ 18%) towards tender processing fee for each lot, to “K.S.E.D.C.Ltd, Bangalore”, in e-payment mode. The e-payment of above amount is to be made to enable the bidder to download the tender documents in electronics mode.
3. The bidders are required to submit the EMD (as applicable), tender processing fee, tender cost etc. on or before the scheduled date & time of submission of online tender.
4. The bidders shall scan the “Tender Cost” & “Tender processing fee” and upload the same in the prescribed form in .gif or .jpg format in addition to sending the original as stated above.
5. Local micro & small enterprisers (MSEs) (In the state of Odisha) based in Odisha and registered with respective DICs, Khadi, Village, Cottage & Handicrafts Industries, OSIC and NSIC can participate without payment of the cost of tender specification. They have to submit notarized hard copy of valid registration as local MSE (In the state of Odisha) as above on or before the date & time of opening of techno-commercial bid.

The bidders shall scan the notarized hard copy of valid registration as local MSE (**In the state of Odisha**) (if any) and upload the same in the prescribed form in .gif or .jpg format in addition to sending the original as stated above.

6. The prospective bidders are advised to register their user ID, Password, company ID from website www.tenderwizard.com/OPTCL by clicking on hyper link “Register Me”.
7. Any clarifications regarding the scope of work and technical features can be had from the undersigned during office hours.
8. Pre-bid query meeting held on dated.07.07.2023 at 11:30 Hrs. at CPC conference hall, 1st floor.

Minimum qualification criteria of bidders: AS STIPULATED IN SECTION-II, PART-I (G.T.C.C) OF THE TENDER SPECIFICATION.

SENIOR GENERAL MANAGER [C.P.C.]



**ORISSA POWER TRANSMISSION CORPORATION LIMITED
JANAPATH, BHUBANESWAR - 751022.
OFFICE OF THE SR. GENERAL MANAGER,
CENTRAL PROCUREMENT CELL,**

FAX: 0674 - 2542964

TELEPHONE: 0674 - 2541801

**TENDER SPECIFICATION NO.
SR. G.M- CPC-POWER TRANS – 57/2022-23-14**

CONTAINING

PART-I

SECTION - I: INSTRUCTIONS TO TENDERERS.

SECTION - II: GENERAL TERMS AND CONDITIONS OF CONTRACT.

SECTION - III: LIST OF ANNEXURES. (SCHEDULES & PROFORMA)

SECTION - IV: TECHNICAL SPECIFICATION.

PART - II. : PRICE BID.

TABLE OF CONTENTS

PART – I SECTION – I (Instruction to Bidder).

<u>Clause.</u>	<u>Title.</u>	<u>Page.</u>
1.	Submission of Bids.	9
2.	Division of Specification	10
3.	Tenders shall be in two parts	10
4.	Opening of Bids	10
5.	Purchaser's right regarding alteration Quantities, tendered.	11
6.	Procedure and opening time of tenders.	11
7.	Bidder's liberty to deviate from specification	11
8.	Eligibility for submission of bids	11
9.	Purchaser's right to accept/reject bids	11
10.	Mode of submission of tenders	11
11.	Earnest money deposit	12
12.	Validity of the bids	12
13.	Bid Price.	13
14.	Revision of Tender Price by Bidders.	13
15.	Tenderers to be fully conversant with the Specification.	15
16.	Documents to accompany Bids.	15
17.	Conditional Offer	15
18.	Affidavit to be furnished by the bidders	16
19.	Expenses in respect of OPTCL's representative for witnessing the inspection & testing of the offered equipment/materials at the inspection and testing site.	16
20.	General	18
21.	Litigation / Arbitration	18
22.	Undertaking for Input tax credit	18
23.	Challenge test	18

SECTION - II.

GENERAL TERMS AND CONDITIONS OF CONTRACT [G.T.C.C.]

Clause.	Title.	Page.
1.	Scope of the contract.	22
2.	Definition of terms	22
3.	Manner of execution	23
4.	Inspection and testing.	
5.	Training facilities	23
6.	Rejection of materials.	24
7.	Experience of bidders	24
8.	Language and measures	25
9.	Deviation from Specification	25
10.	Right to reject/accept any tender.	25
11.	Supplier to inform himself fully	25
12.	Patent rights etc	25
13.	Delivery	26
	Despatch Instructions.	26
15.	Supplier's Default Liability	26
16.	Force Majeure.	26
17.	Extension of Time	27
18.	Guarantee Period.	27
19.	Bank Guarantee towards Security Deposit, Payment and Performance.	27
20.	Import License	28
21.	Terms of Payment	28
22.	Penalty for Delay in Completion of Contract.	28
23.	Insurance	29
24.	Payment Due from the Supplier	29
25.	Documents to be attached	
26.	GST & Other Taxes	29
27.	Supplier's Responsibility.	30
28.	Validity.	30
29.	Evaluation	30
30.	Qualifying Requirement of Bidder	35
31.	Jurisdiction of High Court of Orissa	36
32.	Correspondences	37
33.	Official Address of the Parties to the Contract	37
34.	Outright rejection of Tenders.	37
35.	Documents to be treated as confidential.	37
36.	Contacting the purchaser.	38
37.	Scheme/Projects	38
38.	Empanelment of Bidders	38
39.	Limitation of Liabilities	

SECTION - III.

LIST OF ANNEXURES

[I TO XV]

[P-29 to P-52]

PART - II [PRICE BID]

1.	PRICE	53
2.	Insurance	53
3.	Certificate for exemption from GST	53
4.	Proper filling up of the Price Schedule.	53
5.	Nature of Price	53

SECTION - IV.

TECHNICAL SPECIFICATION.

COMMERCIAL SPECIFICATION
PART-I
SECTION-I
INSTRUCTION TO TENDERER

1. Submission of Bids: -

The bidder shall submit the bid in Electronic Mode only i.e www.tenderwizard.com/OPTCL. The bidder must ensure that the bids are received in the specified website of the OPTCL by the date and time indicated in the Tender notice. Bids submitted by telex/telegram will not be accepted. No request to collect the Bids in physical form will be entertained by the OPTCL.

The OPTCL reserves the right to reject any bid, which is not submitted according to the instruction, stipulated above. The participants to the tender should be registered under **GST Laws**.

1. For all the users it is mandatory to procure the Digital Signatures.
2. Contractors / Vendors / Bidders / Bidders are requested to follow the below steps for Registration:
 - a. Click "Register", fill the online registration form.
 - b. Pay the amount of Rs. 2360/- through e-payment in Favour of KSEDC Ltd. Payable at Bangalore. This registration is valid for one year.
 - c. Send the acknowledgment copy for verification.
 - d. As soon as the verification is being done the e-tender user id will be enabled.
3. After viewing Tender Notification, if bidder intends to participate in tender, he has to use his e-tendering User Id and Password which has been received after registration and acquisition of DSCs.
4. If any Bidder wants to participate in the tender he will have to follow the instructions given below:
 - a. Insert the PKI (which consist of your Digital Signature Certificate) in your System. (Note: Make sure that necessary software of PKI be installed in your system).
 - b. Click / Double Click to open the Microsoft Internet Explorer (This icon will be located on the Desktop of the computer).
 - c. Go to Start > Programs > Internet Explorer.
 - d. Type www.tenderwizard.com/OPTCL in the address bar, to access the Login Screen.
 - e. Enter e-tender User Id and Password, click on "Go".
 - f. Click on "Click here to login" for selecting the Digital Signature Certificate.
 - g. Select the Certificate and enter DSC Password.
 - h. Re-enter the e-Procurement User Id Password
5. To make a request for Tender Document, Bidders will have to follow below mentioned steps.
 - Click "Un Applied" to view / apply for new tenders.
 - Click on Request icon for online request.
 - Enter the required fields including details of D.D for tender Processing fee.
6. After making the request Bidders will receive the Bid Documents which can be checked and downloaded by following the steps mentioned below:
 - Click to view the tender documents which are received by the user.
 - Tender document screen appears.
 - Click "Click here to download" to download the documents.
7. After completing all the formalities Bidders will have to submit the tender and they must take care of following instructions.
 - Prior to submission, verify whether all the required documents have been attached and

- uploaded to the particular tender or not.
- Note down / take a print of bid control number once it displayed on the screen
- 8. Tender Opening event can be viewed online.
- 9. Competitors bid sheets are available in the website for all.
- 10. For any e-tendering assistant contact help desk number mentioned below.
 - Bangalore – 080- 40482000.
 - Bhubaneswar - 09937040591
- 2. Division of Specification.

The specification is mainly divided into two parts viz. Part-I & Part-II.

Part-I Consists of

- | | | |
|-------|-------------|---|
| [i] | Section-I | Instruction to Tenderers. |
| [ii] | Section-II | General terms and conditions of contract. |
| [iii] | Section-III | Schedules and forms etc. |
| [iv] | Section-IV | Technical Specification. |

Part-II Consists of

- [i] Abstract of price components as per Annexure-V
- [ii] Schedule of prices as per Annexure-VI

3. Tenders shall be in Two Parts

The Tenderers are required to submit the tenders in two parts. Part-I shall be techno-commercial & and Part-II shall be “Price Bid”.

4. Opening of Bids.

[a] The part-I shall be opened on the date and time fixed by the OPTCL. Bids will be opened in Electronic mode in presence of the Tenderers or their authorized representatives [limited to one person only] on the due date of opening of tender. After scrutiny of the technical particulars and other commercial terms, clarifications, if required, shall be sought for from the bidders. The Tenderers shall be allowed 15 days time for such activity.

[b] On receipt of technical clarification, the bids shall be reviewed, evaluated and those not in conformity with the technical Specification / qualifying experience, shall be rejected. If any of the technical proposals requires modification to make them comparable, discussion will be held with the participating bidders.

All the responsive bidders shall be given opportunity to submit the revised technical and revised price proposals as a follow up to the clarification (modification if any) on the technical proposals. The qualified bidders shall be given opportunity to submit revised price proposals within 15 days from the date of such discussion or within time frame mutually agreed, whichever is earlier.

[c] When the revised price proposals are received, only the revised technical and price proposals will be considered for bid evaluation. The price bids [Part-II] of such of the Tenderers, whose tenders have been found to be technically and commercially acceptable, including those supplementary revised price bids, submitted subsequently, shall be opened in the presence of the bidder’s representative on a date and time which will be intimated to all technically and commercially acceptable Tenderers.

[d] The bidders are required to furnish sufficient information to the Purchaser to establish

their qualification, capacity to manufacture and/or supply the materials/perform the work. Such information shall include details of bidder's experience, its financial, managerial and technical capabilities.

[e] The bidders are also required to furnish details of availability of appropriate technical staff and capability to perform after sales services. The above information shall be considered during scrutiny and evaluation of bids and any bid which does not satisfactorily meet these requirements, shall not be considered for price bid evaluation.

[f] The price bids of the technically and otherwise acceptable bids shall only be evaluated as per the norms applicable in terms of this Specification.

[g] Tenderers are requested to go through our Technical requirements thoroughly and carefully and it may be noted that furnishing of all information, as required in the enclosed Annexure is mandatory. In case, any of the annexure, duly filled in, is not found furnished, as required in the enclosed annexure, the Tender will be treated as incomplete and will be liable for rejection without any correspondence by the purchaser.

5 Purchaser's Right Regarding Alteration of Quantities Tendered:

The Purchaser may alter the quantities of materials/equipment at the time of placing orders. Initially the purchaser may place orders for lesser quantity with full freedom to place extension orders for further quantity under similar terms and conditions of the original orders. The Purchaser may, at its discretion increase or decrease the quantity of Transformer as per above tender. In case of increase in quantity, the successful bidder(s) shall be asked to furnish their willingness.

Clause 5.2-The Orders may be split among techno-commercially responsive Bidders, basing on the lowest evaluated cost (maximum three nos of Techno-commercially responsive Bidders if found expedient by the purchaser in order to get the benefit of timely delivery. In case of splitting between two bidders, the ratio shall be 70% (L1): 30% (L2) of the quantity as a whole or lot(s), as the case may be, considering the nearest whole number . Similarly in case of splitting among 3 bidders, the ratio shall be 50% (L1): 30% (L2): 20% (L3) of the quantity as a whole or lot(s), as the case may be, considering the nearest whole number. In case L2 or L3 bidders does not agree to match the L1 prices, negotiation can be held with other techno-commercially responsive L4, L5 bidders in sequence to match L1 price basing on total evaluated cost.

6 Procedure and opening time of tenders.

Tenders will be opened in the office of the Senior General Manager [C.P.C.] on the specified date and time in presence of the Tenderers or their authorized representatives [limited to one person only] in case of each bidder who may desire to be present, at the time of opening the bids.

7. Bidder's Liberty to deviate from Specification.

No technical/commercial deviations shall be allowed and in case of any deviation furnished by any bidder, their bid shall be liable for rejection.

8. Eligibility for submission of bids.

Only those manufacturers who have deposited the cost of tender specification, tender processing fee & EMD (As applicable) are eligible to participate in the tender. They should deposit the above prior to **scheduled date & time of opening of Tender** & submit the money receipt as a proof of such payment.

9. Purchaser's right to accept/reject bids:

The purchaser reserves the right to reject any or all the tenders without assigning any reasons

what so ever, if it is in the interest of OPTCL under the existing circumstances. [Read with clause-10, Section-II of the specification].

10. **Mode of submission of Tenders.**

[A] Tenders shall be submitted in electronic mode only. (www.tenderwizard.com/OPTCL)

[B] Tenders submitted through **Telegraphic, FAX or any other mode except above**, shall not be accepted under any circumstances.

11. **Earnest money deposit:**

The tender shall be accompanied by Earnest Money deposit of value specified in the notice inviting tenders against each lot / bid. Tenders without the required EMD as indicated at Annexure-X will be rejected out rightly.

The local Micro and small Enterprises(MSEs) (In the state of Odisha)registered with respective DICs, Khadi, Village, Cottage & Handicrafts Industries, OSIC and NSIC can participate by submitting Earnest Money Deposit @ fifty percent of the amount indicated in the Notice Inviting Tender.

The earnest money deposit shall be furnished in one of the following forms subject to the conditions mentioned below:

(a) Bank Draft: -To be drawn in favour of Drawing & Disbursing Officer, OPTCL [H.Qrs.Office], Bhubaneswar-751 022.

(b) **Bank Guarantee from any Nationalized/Scheduled Bank strictly as per enclosed proforma vide Annexure-VII to be executed on non-judicial stamp paper worth Rs.29.00 or as applicable, as per prevailing laws in force and also to be accompanied by the confirmation letter of the issuing Bank Branch.**

NOTE:

(i). The **validity of the EMD in the form of Bank Guarantee shall be at least for 300** (Three Hundred) days from the date of opening of tender failing which the tender will be liable for rejection.

(ii) No interest shall be paid on the Earnest Money Deposit.

~~(iii) E.M.D. in shape of cash may be submitted up to Rs. 25,000/- (Rupees Twenty five) Thousand) only. Above Rs. 25,000/- (Rupees Twenty five thousand) the Earnest Money Deposit shall be furnished in any one of the forms indicated above (i.e. Through Bank Draft, Bank Guarantee/ National Savings Certificate).~~

(iv) No adjustment towards EMD shall be permitted against any outstanding amount with the **ODISHA POWER TRANSMISSION CORPORATION LTD.**

(v) The chart showing particulars of EMD to be furnished by Tenderers of different categories is placed at **Annexure-X**.

In the case of un- successful tenderer, the EMD will be refunded after the tender is decided. In the case of successful Tenderer, this will be refunded only after furnishing of security money referred to at clause-19 of Section-II.

(vi) Suits, if any, arising out of this clause shall be filed in a Court of law to which the jurisdiction of High Court of ODISHA extends.

(vii) EMD will be forfeited if the tenderer fails to accept the letter of intent and/or purchase order issued in his favour or to execute the order, placed on them.

(viii) Tenders not accompanied by Earnest Money shall be disqualified.

The non judicial stamp papers in which the EMD BG is executed, should be purchased in the name of issuing bank only & not in the name of the bidder.

12. **Validity of the Bids: -**

The tenders should be kept valid for a period of **240** Two Hundred Forty) days from the date of opening of the tender, failing which the tender will be rejected.

13. **BID PRICE: -**

- A) i) Prices quoted shall be variable Unit Price(Taxable Value at Destination) for Transformers including oil and all other accessories as per Specification and the quotations should be based on price, inclusive of packing, forwarding, freight, GST & other local taxes, handling charges (including unloading and part-wise stacking) at the Destination stores/site and insurance to cover the transport by road from the bidder's works to site/stores.
- ii) It is the responsibility of the bidder to inform himself of the correct rates of duties and taxes, leviable on the material at the time of bidding.
- iii) If the rates of statutory levies, assumed by the Bidder are less than the correct rates, prevailing at the time of tendering, the OPTCL shall not be responsible for such errors. If the rates of statutory levies, assumed by the Bidder are later proved to be higher than the actual/correct rates, prevailing at the time of tendering, the difference shall be passed on to the credit of the OPTCL. If the rates of statutory levies, assumed by the bidder increase due to increase in turnover, the increase shall be borne by the Bidder.
- iv) In case, the bidder is exempted from paying GST, such bidder shall invariably enclose a copy of certificate of exemption from Goods & Services Tax. Offers with exemption from Goods and Services Tax shall be accompanied with authenticated proof of such exemption. Authenticated proof for this clause shall mean attested Photostat copy of exemption certificate. Any claim towards Goods and Services Tax shall be paid on actual basis subject to production of authenticated documentary evidence.
- v) **The benefit of Input Tax credit**, available to the bidder on the purchase of inputs (raw materials) including oil, consequent to the introduction of GST **shall** be taken in to account, while quoting the prices.
- B) The prices, indicated in the price schedule shall be entered in the following manner: -
- i) The Basic price(taxable value) of the Transformer shall be quoted as 'VARIABLE' as per ~~Wholesale Price Index(WPI)~~ **IEEMA** of Transformers, in accordance with enclosed **ANNEXURE-XV** & sub-clause-C below.
- ii) The charges for conducting various type tests **special tests** (test wise) shall be quoted on 'FIRM PRICE' basis.
- iii) The charges for mandatory spares (item wise) shall be quoted on 'FIRM PRICE' basis.
- iv) The price for Digital RTCC panel, Nitrogen Injection Type Fire Prevention & Extinguishing System, Online insulating oil drying system, Online dissolved gas(Multi gas) & moisture analyzer and Oil storage Tank shall be quoted on 'FIRM PRICE' basis.
This clause is applicable for the tenders, where above items are specifically mentioned in the price bid sheet.
- v) The bid price shall be in Indian rupees.
- vi) GST and other local taxes, which will be payable for goods and services, specified under **this contract shall be included in the Bid price and they shall be indicated separately both in lump sum and percentage.**
- vii) Charges towards supervision of erection, testing and commissioning, shall be quoted on 'FIRM PRICE' basis along with GST, if any.

The above break-up of price will be solely for the purpose of facilitating the comparison of bids by the purchaser and will not in any way limit the purchaser's right to contract on any of the terms, offered.

The Bid price shall be written both in words and figures. In case of conflict between the figures and words, the latter shall prevail.

C) IEEMA CLAUSE: -

For the procurement Contracts, the price variation shall be allowed for below items

1. Power Transformers & Reactors,
2. ~~Substation & Transmission Line Tower Structure materials including Nuts & Bolts,~~
3. Conductors,
4. Power, control and EHV cables

The quoted price shall be variable as per IEEMA PVC

The IEEMA formula as on date of opening of tender shall be applicable. Whenever IEEMA formula is amended subsequently, the same shall be applicable from the effective date mentioned therein with two stage computation for the period prior to amendment and subsequent to amendment.

Computational procedure

- IEEMA PV formula shall be made applicable on 95% of taxable value (Discovered in OPTCL tenders/negotiated including freight and insurance) considering 5% towards freight and loading & unloading cost
- There would be ceiling of 20% on positive side and no ceiling on negative side for price variation. However increase beyond 15% can be given in exceptional cases only.
- ~~The GIS S/s will also be added in the list of items, whenever the same is covered by IEEMA, OPTCL may also include PV formula for GIS S/s.~~
- ~~For Conductor, only Monthly average Aluminium LME seller settlement price will be considered as per IEEMA for calculating PV.~~
- When the actual delivery date is within the contract delivery date, the PV will be calculated considering the actual delivery date (the date on which the item is notified as being ready for inspection/dispatch or in the absence of such notification, the date of manufacturers dispatch note is to be considered as the date of delivery).

When the actual delivery date is after the contract delivery date, the PV will be calculated considering the scheduled delivery date or the date of offer for inspection or the actual delivery date, whichever is advantageous to the purchaser.

- Price variation bills/ debit or credit notes are to be submitted by the firm for the item that are subject to variable price for a quarter
- In case of upward revision of price due to price variation, the BG for 10% of differential amount shall be submitted within 15 days of approval of Price Variation

14. **Revision of tender price by Bidders: -**

[a] After opening of tenders and within the validity of period, no reduction or enhancement in price will be entertained. If there is any change in price, the tender shall stand rejected **and the EMD deposited shall be forfeited.**

[b] After opening of price bid if the validity period is not sufficient to place purchase order, the tenderer may be asked by the purchaser to extend the validity period of the bid under the same terms and condition as per the original tender.

However, the tender are free to change any or all conditions including price except delivery period of their bids at their own risk, if they are asked by the purchaser to extend the validity period of the bid prior to opening of price bid.

15. **Tenderers to be fully conversant with the Specification: -**

The bidder is deemed to have carefully examined all instructions, formats, terms and meaning of all the clauses of the specification. Failure to furnish all informations, required by the Bidding documents or submission of a bid, not substantially responsive to the Bidding Documents in every respect will be at the Bidder's risk and may result in the rejection of his bid. In case of doubt regarding the meaning of any clause, instruction, format and terms, the bidder may seek clarification in writing from the Senior General Manager (CPC) OPTCL and must ensure that the same is received by CPC, not later than 10(ten) days prior to the deadline for submission of bids.

16. **Documents to Accompany Bids.**

Tenderers are required to submit tenders in the following manner:

Part-I of the Tender shall contain the following documents.

[i] Declaration Form. [As per Annexure-I]

[ii] Earnest Money [As per Annexure-VII]

[iii] Technical specification and Guaranteed Technical Particulars, conforming to the Purchaser's Specification along with drawings, literatures and all other required Annexures, duly filled in.

[iv] Photostat copies of type test certificates, as stipulated in the Technical Specification.

[v] Abstract of Terms & conditions in prescribed proforma as per **Annexure-II.**

[vi] General Terms & Conditions of supply offer as per Section-II of the Specification.

[vii] List of orders executed for the tendered transformer rating or higher (both MVA & Voltage rating), indicating the customer's name, Purchase Order No. & Date, date of supply and

date of commissioning etc.

- [viii] Data on past experience as per **Clause-7 of Section-II** of the Specification.
 - [ix] Rating under Goods & Services Tax, GST Registration Certificate. The permanent account number [PAN] and IT Return for last three years of the firm is required under Income tax Act.
 - [x] ~~Notarized copies~~ of Audited Balance sheet & profit loss accounts of the bidder for past 5 (Five) years with **UDIN number**.
 - [xi] Schedule of quantity and delivery in the prescribed Proforma vide **Annexure-IV.**
 - [xii] List of Orders in hand to be executed.
 - [xiii] Check list for qualifying requirements as per **Annexure-III.**
 - [xiv] Other Annexures as per Section-III of this specification.
 - [xv] Abstract of Price components as per **Annexure-V.**
- [xvi] Bidders are advised to number all pages of their Tender documents along with the Annexures and submit (upload) the tender as well as they will mention "List of contents "in a separate document and clearly indicating description of the documents and page numbers, failing which their Tender(s) is/are liable for outright rejection. The documents such as copies of purchase orders, User certificates, performance certificates, audit reports, balance sheets, Tax clearance certificates, type test reports, which are issued by external agencies in the favour of the tenderer, will be submitted, failing which these documents may not be considered for evaluation.

Part-II Bid shall accompany with the following documents

- [i] Schedule of prices in the prescribed proforma as per **Annexure-VI.**

17. Conditional Offer

Conditional offer shall not be accepted and shall be liable for rejection at the discretion of the purchaser.

18. Affidavit towards correctness of documents & information furnished by the bidders:-

The bidders are required to furnish an affidavit (Format enclosed as Annexure-XVI of Section-III), towards correctness of documents & information furnished in their bids.

19.0 Expenses in respect of OPTCL's representative for witnessing the inspection & testing of the offered equipment/materials at the inspection and testing site.

The testing and inspection of the equipment/ materials at manufacturer works are in the scope of work of the Contractor/Supplier.

OPTCL inspecting officer, on receipt of offer for inspection from the contractor/supplier, proceeds to the manufacturer works to witness the Type/Acceptance/Routine test.

Important:

It is hereby informed to all the bidders that the relevant clauses of the contract specification, pertaining to inspection and testing of equipment/materials, are hereby supplemented with following additional terms and conditions.

The expenses under the following heads, in respect of OPTCL's representative for witnessing the inspection & testing of the offered equipment/materials at the inspection and testing site, shall be borne by the contractor / supplier.

a) Hotel Accommodation:

I. Single room accommodation in 4 star hotel for the OPTCL inspecting officer of the rank of Assistant General Manager (Grade E-6) and above.

II. Single room accommodation in 3 star hotel for the OPTCL inspecting officer of the rank below Assistant General Manager (Grade E-6).

N.B.: *It is the responsibility of the contractor to arrange the hotel accommodation matching with their inspection and testing schedule, so that the inspecting officer can check-in the hotel one day prior to the date of inspection and check out after the completion of the inspection, subject to availability of the return travel ticket. In case of extended duration of inspection or non-availability of the return travel ticket, Contractor/supplier/manufacturer shall arrange for the extended stay of the inspecting officer in the Hotel accordingly. In case there is no hotel with prescribed standard in and around the place of inspection, the contractor/supplier/manufacturer shall suggest alternative suitable arrangement at the time of offer for inspection, which is subjected to acceptability of OPTCL inspecting officer.*

b) Journey of the inspecting officer:

(i) To and fro travel expenditure from the Head Quarters of the inspecting officer to the place of inspection/testing shall be borne by the contractor/supplier/manufacturer. Journey from the Head Quarters of the inspecting officer to the nearest Air Port by train (1st/1Ind A.C) & A/C Taxi then by Air to the place of inspection/testing or to the nearest place of inspection/testing and then by train (1st/1Ind A.C) & A/C taxi to the place of inspection/testing shall be arranged by the contractor/supplier/manufacturer.

(ii) For train journey, inspecting officer of the rank Assistant General Manager and above shall be provided with 1st class AC ticket and inspecting officer below the rank of Assistant General Manager shall be provided with 2nd class AC ticket.

(iii) The Air-ticket / train-ticket booking/cancellation is the responsibility of the contractor / supplier.

(iv) Moreover, if during the journey there is an unavoidable necessity for intermediate travel by road/ waterway/sea-route, the contractor/supplier shall provide suitable conveyance to the inspecting officer for travel this stretch of journey or bear the cost towards this. Any such possibilities shall be duly intimated to OPTCL at the time of their offer for inspection.

c) Local Conveyance:

At the place of the inspection/testing, for local journey of the inspecting officer between Hotel and inspection/testing site and or any other places, Air-conditioned four wheeler vehicle in good condition shall be provided by the contractor/supplier/manufacturer.

d) Following points are also to be considered:

(i) All the above expenses shall be deemed to be included in the bidder's quoted price for that supply item. Bidder shall not be eligible to raise any extra claim in this regard.

(ii) Contractor/supplier/manufacturer may assume that only in 40% of the inspection and testing offer cases, OPTCL inspecting officer, not below the rank of Assistant General Manager will witness the inspection and testing.

(iii) In case of inspection and testing of some critical equipment/materials like Power transformers, OPTCL may depute more than one inspecting officer.

(iv) Contractor/supplier/manufacturer shall judiciously plan the inspection/testing schedule and place of inspection/testing, so that optimum number of inspection/testing and minimum time shall be required to cover all the equipment/materials of the relevant contract package.

(v) It shall be the responsibility of the Contractor/Supplier to organize the above tour related matters of OPTCL inspecting officer including the matters related to overseas inspection/testing, if any.

20. General: -

- (i) In the event of discrepancy or arithmetical error in the schedule of price, the decision of the purchaser shall be final and binding on the Tenderer.
- (ii) For evaluation, the price mentioned in words shall be taken if there is any difference in figures and words in the price bid.
- (iii) Notice inviting tender shall form part of this specification.
- (iv) The price bids of the techno-commercially and otherwise acceptable bids shall only be evaluated. The price bids of the others along with the EMD, if any, shall be returned to the bidders.
- (v) Tenderer can offer any lot or all the lots of the tender, if there are more than one lot. But the tender (bid) must be furnished separately for each lot. For each lot, the tenderer has to submit PART-I & PART-II of the bids separately.
- (vi) It should be distinctly understood that the part-II of the bid shall contain only details/documents relating to price, as outlined in clause-16 mentioned herein above. Inclusion of any of the documents/information etc. shall render the bid liable for rejection.
- (vii) The tenderer must submit the EMD amount, cost of tender document and documents towards e-payment of Tender processing fee, copy of GST registration number in a sealed cover envelope super scribing the tender specification number, Tender Notice No & Date opening of tender clearly on the cover envelope. The said envelope is to be submitted in the office of the purchaser on or before the scheduled date and time of opening of techno-commercial bid.

21. Litigation/Arbitration

- (i)- Bidder has to furnish detailed information on any litigation or arbitration arising out of contracts completed or under execution by it over the last five years. A consistent history of litigation by or against the bidder may result in rejection of bid.
- (ii) The bidder should not have any pending litigation or arbitration with OPTCL with regard to any project or related activity. The bidder should certify/declare the same in unequivocal terms by way of an affidavit duly sworn before a magistrate or a notary. Bid furnished by the bidder shall not be eligible for consideration if it is not accompanied by the affidavit. Further, the bid/LOA/LOI shall be liable for outright rejection/cancellation at any stage if any information contrary to the affidavit/declaration is detected.

22. The bidders are required to give an undertaking(In Annexure-V) that, entire implication of lower tax and input tax credit benefit have been fully passed on to the purchaser as per anti-profiteering and other provisions under GST law while quoting tender price.

23. CHALLENGE TEST :

- 23 (a) Any participating bidder can challenge whether the supplier has supplied the transformer as per the purchase order / tender technical specification or not. Challenge testing can be done on any one transformer of a supplier, out of the ordered quantity, during guarantee period from the date of dispatch instruction but before commissioning at site.
- 23 (b) The challenger shall have to make written request to the Senior General Manager(CPC) for challenge testing giving details of manufacturer, purchase order and rating of transformer supplied by the party challenged along with the following :

- i) Demand draft / Banker's cheque in favour of DDO, Head Quarter, OPTCL, Bhubaneswar amounting to Rs. 5,00,000/- (Rs. Five lacs only) thereon towards challenge testing (non refundable).
- ii) Demand draft / Banker's cheque in favour of the party challenged amounting to rs. 1,00,000/- (Rs. One lac only) to meet their contingencies which shall be handed over to the party challenged at the time of sealing of the selected transformer for testing.
- iii) Confirmation of test date from the test lab (CPRI / ERDA). The test date shall not be later than 6 months from the date of submission of application for challenge testing. The test date at CPRI / ERDA is to be obtained by the challenger by deposit the required test charges.

23 (c) All the expenses mentioned below during challenge testing shall be incurred by the challenger:

- i) Dismantling (if the transformer is already installed) and loading at site.
 - ii) To & Fro transportation (including insurance) charges from site to testing platform and back to site (anywhere in ODISHA). The transformer lifted from site shall be fully insured against all the risk for the period starting from lifting of the transformer from the site till return back to site (anywhere in ODISHA) after testing.
 - iii) Unloading and assembly at testing platform.
 - iv) Dismantling after testing & loading from testing platform.
 - v) Unloading at site.
 - vi) Taxes, duties, levies, etc., during transportation of transformer from site to test lab & back to site, if any.
 - vii) Re-installation charges of transformer at site, in case the selected transformer had already been installed.
 - viii) Testing fee / charges demanded by CPRI / ERDA.
- All the arrangements in regards to above activities shall be exclusively made by the challenger.

23 (d) The challenger shall intimate the proposed date of lifting of selected transformer to the Senior General Manager(CPC), OPTCL, Bhubaneswar, ODISHA at least, 15 days in advance, along with the following:

- i) Bank guarantee, in acceptable form of an amount equivalent to F.O.R. Destination cost of the selected transformer including entry tax as per purchase order, in lieu of security of selected transformer for challenge testing. The Bank Guarantee shall be valid initially for one year.
- ii) Insurance cover for full value of transformer against all the risk for the period starting from proposed date for lifting of the transformer from site till return back to site (anywhere in ODISHA) after testing.

Thereafter, permission for lifting of the transformer shall be granted to the challenger. The challenger shall also intimate the proposed date of lifting of

selected transformer simultaneously to the party challenged.

- 23 (e) The selected sample shall be lifted after sealing the same in the presence of authorized representative (s) of the challenger, the party challenged and OPTCL within 45 days prior to the date of proposed testing. If the party challenged fails to depute its representative to seal / witness the lifting of the proposed transformer on the intimated date, the transformer shall be lifted for testing without waiting for their representative for sealing / witness and the absence of their representative will be treated as their consent about sealing as well as challenge testing. The sealed transformer shall be transported to CPRI / ERDA for testing in order to proceed as per reserved testing schedule. Both party i.e. challenger, the party challenged may accompany the truck during transportation of selected sample from site to CPRI / ERDA and back.
- 23 (f) The challenger, the party challenged and OPTCL shall witness the test. If any party i.e. challenger and / or the party challenged and / or OPTCL fails to attend / witness the testing, the sample shall be tested in their absence and all the parties have to accept the test results whatsoever.
- 23 (g) The challenge testing would cover the following tests:-
- a) Measurement of No load losses (including confirmation on requirement of minimum knee-point voltage as per OPTCL's Technical Specification).
 - b) Measurement of load losses at rated full (100%) load at principal tap duly converted to 75 deg.C winding temperature.
 - c) Temperature rise test.
- All the tests shall be conducted in above mentioned sequence.
- 23 (h) If all the test results conform to the specification, action shall be taken as detailed below:
- a) The challenger will not be reimbursed the expenses incurred by him for challenge testing of the transformer.
 - b) Since the challenge testing may take about 8 month's period for which the transformer may not be in operation. In such case, the actual performance guarantee of the transformer will be available for lesser period than prescribed performance period i.e. 36 months from the date of receipt or 30 months from the date of commissioning whichever is earlier, as per contract. Therefore, after expiry of contractual performance guarantee period of the transformer, the party challenged (Transformer manufacturer) shall have to further guarantee the transformer equivalent to the period starting from the date of application for challenge testing till return back to site after testing. For this, the party challenged shall have to furnish bank guarantee equivalent to 10% of the cost of transformer towards performance for the period as stated above.
 - c) The Bank Guarantee, equivalent to the cost of transformer furnished in lieu to security, will be released on receipt of certificate by the consignee / site in-charge regarding receipt of the transformer complete with all fittings and accessories anywhere in Rajasthan to the challenger after recovery of re-installation charges etc, if any.
- 23 (i) If any of the test results does not conform to the specification, action shall be taken as

detailed below:

- a) The party challenged shall be declared as unsuccessful manufacturer and would be debarred from participating in all future tenders of power transformers for the period of 5 years. Further, the order for balance quantity under that particular order shall be cancelled.
- b) The party challenged shall have to reimburse all the expenses as detailed at Clause No. 6.4.3(c) incurred by the challenger on challenge testing directly to the challenger on furnishing requisite documents towards the expenses incurred. The party challenged shall also have to reimburse Rs. 5,00,000/- (Rs. One lac only) to the challenger which had been incurred by the challenger as detailed at Clause No. 3.40.2 above.
- c) If the losses are found beyond guaranteed value then the penalty towards excess losses shall be recovered at twice the rate prescribed at Clause No. 5.2.2 of Specification for each supplied transformers in this order.
- d) If the transformer does not conform to the specification in temperature rise test, penalty @ 5% of F.O.R. Destination cost (including entry tax) of all the transformers supplied in that particular order till date shall be recovered.
- e) Any type of recoveries arising out due to challenge testing shall be recovered from the financial hold of the party challenged available with the OPTCL in any form in any order placed by the OPTCL.
- f) The Bank Guarantee(s) of the party challenged available with the Nigam against the purchase order shall be released after successful completion of performance guarantee period (including extended period as at Clause No. 3.40.8(b)) and recovery of all dues including the charges due to be reimbursed to the challenger.

PART-I
SECTION-II
GENERAL TERMS AND CONDITIONS OF CONTRACT [G.T.C.C.]

1. Scope of the contract:

The scope of the contract shall be to design, manufacture, supply of equipments as per the specification at the consignee's site, and rendering services in accordance with the enclosed technical specification.

2.0 Definition of terms:

For the purpose of this specification and General Terms and Conditions of contract [GTCC], the following words shall have the meanings hereby indicated, except where otherwise described or defined.

- 2.1 "The Purchaser" shall mean the Senior General Manager [Central Procurement Cell] for and on behalf of ODISHA POWER TRANSMISSION CORPORATION LIMITED, Bhubaneswar.
- 2.2 "The Engineer" shall mean the Engineer appointed by the Purchaser for the purpose of this contract.
- 2.3 "Purchaser's Representative" shall mean any person or persons or consulting firm appointed and remunerated by the Purchaser to supervise, inspect, test and examine workmanship and materials of the equipment to be supplied.
- 2.4 "The supplier" shall mean the bidder whose bid has been accepted by the purchaser and shall include the bidder's executives, administrators, successors and permitted assignees.
- 2.5 "Equipment" shall mean and include all machinery, apparatus, materials, and articles to be provided under the contract by the suppliers.
- 2.6 "Contract Price" shall mean the sum named in or calculated in accordance with the provisions of the contract as the "Contract Price" which shall include packing, forwarding, freight, insurance Goods and Services Tax and other taxes and duties as applicable at the time of opening of bids.
- 2.7 "General Condition" shall mean these General Terms and Conditions of Contract.
- 2.8 "The Specification" shall mean both the technical as well as commercial parts of the specification, annexed to or issued with GTCC and shall include the schedules and drawings, attached thereto as well as all samples and pattern, if any.
- 2.9 "Month" shall mean "Calendar month".
- 2.10 "Writing" shall include any manuscript, type written, printed or other statement reproduction in any visible form and whether under seal or under hand.
- 2.11 "Basic Price (Taxable Value for Goods) at the point of destination" shall mean the price quoted by the bidder for equipment and material at the consignee's store/site. The

cost is inclusive of packing, forwarding, freight, insurance and all expenses and taxes & duties at the end of the supplier excluding Goods & Service Tax. The Goods & Service Tax shall be shown in a separate column item wise alongside the Basic Price quoted at the applicable rate in the Tax Invoice. The applicable rate of GST shall refer to the HSN code of the material supplied. The Basic Price and GST thereon shall be the "FOR Destination Price" as quoted by the bidder.

- 2.12 The term "Contract document" shall mean and include GTCC, specifications, schedules, drawings, form of tender, Notice Inviting Tender, covering letter, schedule of prices or the final General Conditions, any special conditions, applicable to the particular contract.
- 2.13 Terms and conditions not herein defined shall have the same meaning as are assigned to them in the Indian Contract Act, failing that in the Orissa General Clauses Act.

3. Manner of execution:

All equipment supplied under the contract shall be manufactured in the manner, set out in the Specification or where not set out, to the reasonable satisfaction of the Purchaser's representative.

4. Inspection and Testing:

- [i] The purchaser's representative shall be entitled at all reasonable times during manufacture to inspect, examine and test at the supplier's premises, the materials and workmanship of all equipment to be supplied under this contract and if part of the said equipment is being manufactured in other premises, the supplier shall obtain for the purchaser's representative permission to inspect, examine and test as if the equipment were being manufactured in the supplier's premises. Such inspection, examination and testing shall not relieve the supplier from his obligations under the contract.
- [ii] The supplier shall give to the purchaser adequate time/notice [at least two weeks] in writing for inspection of materials indicating the place at which the equipment is ready for testing and inspection and shall also furnish the Routine Test Certificate, calibration certificates of Testing instruments, calibrated in Govt. approved laboratory with authenticity letter of that laboratory, along with offer for inspection to the Purchaser. A packing list along with the offer indicating the quantity which can be delivered through suitable road transport only to facilitate issue of despatch instruction shall also be furnished.
- [iii] Where the contract provides for test at the premises of the supplier or any of his sub-vendors, the supplier shall provide such assistance, labour, materials, electricity, fuel and instruments, as may be required or as may be reasonably demanded by the Purchaser's representative to carry out such tests efficiently. The supplier is required to produce routine test Certificate, calibration certificates of Testing Instruments before offering their equipment for inspection and testing. The test house/laboratory where tests are to be carried out should be approved by the Govt. A letter pertaining to Govt. approved laboratory should be furnished to the purchaser along with the offer for inspection.
- [iv] After completion of the tests, the Purchaser's representative shall forward the test results to the Purchaser. If the test results conform to the specific standard and specification, the

Purchaser shall approve the test results and communicate the same to the supplier in writing. The supplier shall provide at least two copies of the test certificates to the Purchaser.

- [v] The Purchaser has the right to have the tests carried out at his own cost by an independent agency whenever there is dispute regarding the quality of supply.
- [vi] All the tour expenses of OPTCL inspecting officers towards inspection & testing shall be borne by the bidder as per Cl. No – 19, Section-I (Instruction To Tenderer), Part-I of the T.S. In case, the transformer is not presented for inspection (stage or final) on the date of inspection, offered by the firm due to any reason(s) or in case of repetition of tests and inspection, the firm shall be required to bear all the expenses, incurred in the visit of the Inspector(s).

5. Training facilities.

The supplier shall provide all possible facilities for training of Purchaser's Technical personnel, when deputed by the Purchaser for acquiring first-hand knowledge in assembly of the equipment, its erection, commissioning and for its proper operation and maintenance in service, wherein it is thought necessary by the purchaser.

6. Rejection of Materials.

In the event, any of the equipment/material, supplied by the manufacturer is found defective due to faulty design, bad workmanship, bad materials used or otherwise not in conformity with the requirements of the Specification, the Purchaser shall either reject the equipment/material or ask the supplier in writing to rectify or replace the defective equipment free of cost to the purchaser. The supplier on receipt of such notification shall either rectify or replace the defective equipment/material free of cost to the purchaser within 30days of the date of such notification by the purchaser. If the supplier fails to do so, the purchaser may: -

- [a] At its option replace or rectify such defective equipments/materials and recover the extra costs so involved from the supplier plus fifteen percent and/or.
- [b] Terminate the contract for balance work/supplies, with enforcement of **price reduction** Clause as per contract for the un-delivered goods and with forfeiture of Performance Guarantee/Composite Bank guarantee.
- [c] Acquire the defective equipment/materials at reduced price, considered equitable under the circumstances.

7. Experience of Bidders:

The bidders should furnish information regarding experience particularly on the following points: -

- [i] Name of the manufacturer:
- [ii] Standing of the firm and rating of Transformer, quoted:
- [iii] Description of the transformers, quoted, supplied and installed with the names of the Organizations to whom supplies were made along with Purchase Order No. & Date, wherein, at least 3 (Three) certificate shall be from a State/Central P.S.U.
- [iv] Details as to where installed and commissioned, as per the above Qualifying Requirement.
- [v] Testing facilities at manufacturer's works.
- [vi] A list of purchase orders of the same rated Transformer, as offered as per technical specification or higher rating (both MVA & Voltage rating) along with user's certificate, as applicable in accordance with the above Qualifying Requirement of this Specification. User's certificate shall be legible and must indicate, user's name(name of the organisation), address, name and designation of the issuing officer's, contact

telephones/mobile no. and e-mail ID FAX No, place of use and satisfactory performance of the Transformers for a period, as stipulated in the above Qualifying Requirement, from the date of commissioning. Further, the certificates must indicate P.O. reference, transformer Sl.No. and rating (MVA, Voltage) and date of commissioning. Incomplete user certificate(s) in the above respect may not be considered for evaluation.

Bids will not be considered, if the past manufacturing experience is found to be unsatisfactory or is of less than the period, as stipulated in the above Qualifying Requirement of this Specification, on the date of opening of the bid and bids, not accompanying user's certificates will be rejected.

8. Language and measures:

All documents pertaining to the contract including specifications, schedule, notices, correspondence, operating and maintenance instructions. Drawings or any other writing shall be written in English language. The metric system of measurement shall be used exclusively in this contract.

9. Deviation from specification:

No technical/commercial deviations shall be allowed and in case of any deviation furnished by any bidder, their bid shall be liable for rejection.

10. Right to reject/accept any tender:

The purchaser reserves the right either to reject or to accept any or all tenders if the situation so warrants in the interest of the purchaser. Orders may also be split up between different Tenderers on individual merits of the Tenderer. The purchaser has exclusive right to alter the quantities of materials/ equipment at the time of placing final purchase order. After placing of the order, the purchaser may defer the delivery of the materials. The quantity of transformers as per above tender may be increased or decreased at the discretion of the purchaser. It may be clearly understood by the Tenderer that the purchaser needs not assign any reason for any of the above action [s].

11. Supplier to inform himself fully:

The supplier shall examine the instructions to tenderers, general conditions of contract, specification and the schedules of quantity and delivery to satisfy himself as to all terms and conditions and circumstances affecting the contract price. He shall quote price [s] according to his own views on these matters and understand that no additional allowances except as otherwise provided there in will be admissible. The purchaser shall not be responsible for any misunderstanding or incorrect information, obtained by the supplier other than the information given to the supplier in writing by the purchaser.

12. Patent rights etc.

The supplier shall indemnify the Purchaser against all claims, actions, suits and proceedings for the infringement or alleged infringement of any patent design or copy right protected either in the country of origin or in India by the use of any equipment supplied by the manufacturer, but such indemnity shall not cover any use of the equipment, other than for the purpose indicated by or reasonably to be inferred from the specification.

13. Delivery:-

- [a] Time, being the essence of the contract; the equipment shall be supplied within the delivery date, specified in the contract. The Purchaser, however, reserves the right to reschedule the delivery and change the destination if required. The delivery period shall be reckoned from the date of placing the Letter of Intent/Purchase order, as may be specified in LOI/Purchase order.
- [b] The bidder shall be required to state the period of time within which they will complete the delivery of the equipment along with all accessories and spares. **The period, as quoted by the Bidder 14 weeks or more in excess of the specified delivery period will make the bid non-responsive and will be rejected.**

14. Dispatch Instructions

- I] The materials should be securely packed and dispatched directly to the specified site at the supplier's risk by Road Transport only.
- II] Loading & unloading of Ordered Materials.
It will be the sole responsibility of the supplier for loading and unloading of materials both at the factory site and at the destination site/store. The Purchaser shall have no responsibility on this account.

15. Supplier's Default Liability.

- [i] The Purchaser may, upon written notice of default to the supplier, terminate the contract in circumstances detailed hereunder: -
 - [a] If in the judgment of the Purchaser, the supplier fails to make delivery of equipment within the time specified in the contract or within the period for which extension has been granted by the Purchaser in writing in response to written request of the supplier.
 - [b] If in the judgment of the Purchaser, the supplier fails to comply with any of the provisions of this contract.
- [ii] In the event, Purchaser terminates the contract in whole or in part as provided in Clause-15 (i) of this section, the Purchaser reserves the right to purchase upon such terms and in such a manner as he may deem appropriate in relation to the equipment similar to that terminated and the supplier will be liable to the Purchaser for any additional costs for such similar equipment and/or for penalty for delay as defined in clause-22 of this section until such reasonable time as may be required for the final supply of equipment.
- [iii] In the event, the Purchaser does not terminate the contract as provided in clause 15(i) of this Section, supplier shall be liable to the Purchaser for penalty for delay as set out in Clause-22 of this section until the equipment is accepted. This shall be based only on written request of the supplier and written willingness of Purchaser.

16. Force Majeure:

The supplier shall not be liable for any penalty for delay or for failure to perform the contract for reasons of force majeure such as acts of god, acts of the public enemy, acts of Govt., Fires, floods, epidemics, Quarantine restrictions, strikes, Freight Embargo and provided that the supplier shall within Ten (10) days from the beginning of such delay notify the purchaser in writing of the cause of delay along with documentary evidence. The purchaser shall verify the facts and grant such extension, if facts justify.

17. Extension of time:-

If the delivery of equipment/material is delayed due to reasons beyond the control of the supplier, the supplier shall without delay give notice to the purchaser in writing of his claim for an extension of time. The purchaser on receipt of such notice may agree to extend the contract delivery date as may be reasonable but without prejudice to other terms and conditions of the contract.

18. Guarantee period: -

[i] The equipment along with all its accessories and spares covered by this specification should be guaranteed for satisfactory operation and against defects in design, materials and workmanship for a period of 66 [Sixty Six] months from the last date of delivery or 60 [Sixty] months from the date of commissioning, whichever is earlier. The date of commissioning shall be the date from which the equipment is in satisfactory operation. The last date of delivery shall be the date on which the transformer along with all its accessories and spares are received at OPTCL's stores/sub-station site in complete shape and good condition, substantiated with verification certificate by OPTCL which are released for Dispatch by the purchaser after due inspection.

The above guarantee certificate shall be furnished in triplicate to the purchaser for his approval. Any defect noticed during this period should be rectified by the supplier free of cost to the purchaser provided such defects are due to faulty design, bad workmanship or bad materials used, within one month upon written notice from the purchaser, failing which provision of Clause-22 (ii) shall apply.

[ii] Equipment/material along with all its accessories and spares failed or found defective during guarantee period shall have to be guaranteed after repair/replacement for a further period of 60 months from the date of commissioning or 66 months from the date of delivery at OPTCL's stores/sub-station site in complete shape and good condition, after such repair/replacement whichever is earlier. Date of receipt as used in this clause shall mean the date on which the transformer along with all its accessories and spares are received at OPTCL's stores/sub-station site in complete shape and good condition.

19. B.G. towards security deposit, 100% payment and performance guarantee:

(i) A Composite Bank Guarantee as per the proforma enclosed at **Annexure-VIII** of the specification for 10% [ten percent] of the total FORD cost of the purchase order shall be furnished from any nationalized/scheduled bank having a place of business at Bhubaneswar to the office of **Senior General Manager** [Central Procurement Cell], OPTCL within 15 days of issue of the purchase order. The BG shall be executed on non judicial stamp paper worth of Rs.100.00 [Rupees one hundred] only or as per the prevalent rules, valid for a period of **68 months** from the last date of stipulated delivery period, for scrutiny and acceptance, failing which the supply order will be liable for cancellation without any further written notices. The BG should be accompanied by a confirmation letter from the concerned bank, and should have provision for encashment at Bhubaneswar, before the Bank Guarantee is accepted and all concerned intimated. The BG should be revalidated as and when intimated to cover the entire Guarantee Period.

[ii] No interest is payable on any kind of Bank Guarantee.

[iii] In case of non-fulfillment of contractual obligation, as required in the detailed purchase

order/Specification, the composite Bank guarantee shall be forfeited.

20. Import License

In case, imported materials are offered, no assistance will be given for release of Foreign Exchange. The firm should arrange to import materials from their own quota. Equipment of indigenous origin will be preferred.

21. (A) Terms of Payment.

- "i) 100% taxable value of each consignment with 100% Goods and Services Tax in full as applicable will be paid on receipt of materials including 10% of extra oil **as per dispatch instruction** in good condition at stores/desired site and verification thereof, subject to furnishing and approval of
 - a. Contract cum Performance Bank Guarantee at the rate of **10% (Ten percent)** of Taxable Value plus GST thereon
[In case successful bidder is a local Micro and small Enterprise (MSEs), based in Odisha & registered with respective DICs, Khadi, Village, Cottage & Handicrafts Industries, OSIC and NSIC, 5% (five percent) in place of **10% (ten percent)** will be applicable].
 - b. Guarantee certificate,
 - c. Test certificate by the Purchaser.
- ii) TDS under GST Laws for shall be deducted, **as** applicable and requisite TDS certificate will be issued.
- iii) Any statutory variation due to imposition of new tax or revision in rate of existing tax shall be paid/reimbursed based on scheduled delivery or actual delivery whichever is earlier (i.e. If delivery is within schedule period, statutory variation as applicable shall be paid, and if delivery is made beyond schedule date, any additional financial implication due to statutory variation shall be to the bidder's account)

[B] The supplier shall furnish Contract cum Performance Bank Guarantee of appropriate amount 10% (Ten Percent) to OPTCL as indicated in (i) above within 30 days from the date of issue of the purchase order.

22. Price Reduction Schedule for Delay in Completion of Supply under Purchase Order/Contract:-

- (i) If the Supplier fails to deliver the materials/equipment within the delivery schedule, specified in the Purchase Order/Contract including delivery time extension, if any, granted with waiver of Price Reduction Schedule, the Purchaser shall recover from the Supplier, Price Reduction Schedule for a sum of half per cent (0.5 per cent) of the Taxable Value of the un-delivered equipment /materials for each calendar week of delay or part thereof. For this purpose, the date of receipted challan shall be reckoned as the date of delivery. The total amount of Price Reduction Schedule shall not exceed five per cent (5%) of the Taxable Value of the un-delivered equipment/materials. Equipment will be deemed to have been delivered only when all its components, accessories and spares as per technical Specification are also delivered. If certain components, accessories and spares are not delivered in time, the equipment/materials will be considered delayed until such time as the missing components, accessories and spares are delivered.
- (ii) During the guarantee period, if the Supplier fails to rectify/replace the equipment/material within 30 days from the date of intimation of defect by the purchaser, then the Price Reduction Schedule at the rate of half percent (0.5%) of the Total Taxable Value for each calendar week of delay or part thereof shall be recovered

by the purchaser. For this purpose, Price Reduction Schedule shall be reckoned from the 30th day from the date of issue of letter on defectiveness of equipment/material. The total amount of Price Reduction Schedule in this case shall not exceed 10% (TEN PERCENT) of the Purchase Order/Contract amount except GST (i.e. Total Taxable Value). If the defects, so intimated are not rectified or equipment/materials not replaced by the supplier within the guarantee period, then whole of the C.P.B.G. will be forfeited by the purchaser, without any intimation to the supplier.

- (iii) In case of failure of the transformer, the supplier shall take back the faulty transformer from its plinth for repair at their own cost (or replace the transformer with a new transformer) and deliver, at their own cost, unload at the destination sub-station transformer plinth within three months period from the date of intimation of defects to the satisfaction of the owner, at free of cost. If the delivery after repair/replacement will not be completed within three months, then the supplier shall pay price reduction @ 0.5% of the Total Taxable Value for each calendar week of delay from the end of three months period from the date of intimation of defects. Also, the Purchaser reserves the right for forfeiture of the total Composite Bank Guarantee and all the Securities, available with OPTCL, in case the Supplier fails to pay the price reduction amount by one month before the expiry of the guarantee period. Also, this will be taken as adverse in all future tenders.

The purchase order amount shall mean Taxable Value + GST and other local taxes.

23. Insurance

The Supplier shall undertake insurance of equipment covered by this Specification unless otherwise stated. The responsibility of delivery of the equipment at destination in good condition rests with the Supplier. Any claim with the Insurance Company or transport agency arising due to loss or damage in transit has to be settled by the supplier. The Supplier shall undertake free replacement of materials damaged or lost, which will be reported by the consignee within 30 days of receipt of the materials at destination, without awaiting for the settlement of their claims with the carriers and under writers.

24. Payment Due from the Supplier.

All costs and damages, for which the supplier is liable to the purchaser, will be deducted by the purchaser from any money, due to the supplier under any of the contract (s), executed with OPTCL.

25. The following documents are to be submitted at the time of Tender Submission:-

- i) Compliance rating under Goods and Services Tax for immediate preceding financial year.
- ii) Audited Balance Sheet and Profit & Loss Account of the bidder for the previous five years to assess the financial soundness of the bidder(s).
- iii) GST registration certificate and PAN Card Copy.
- iv) Tax holiday/exemption certificate under GST or any other Act.
- v) TDS exemption certificate under the Income Tax Act or any other act.

26. GST AND OTHER LOCAL TAXES: -

- a) A Bidder will be entirely responsible for quoting the correct taxes and duties, other local taxes or levies, if any etc. which has to be incurred until completion of the contract. For the purpose of evaluation, the Bidder should clearly indicate, the GST & Other local taxes, payable, in the price schedule. Failure to furnish the same will be loaded as

indicated below: -

- i) It is the responsibility of the Bidder to quote all taxes and duties correctly without leaving any row/ column unfilled. Where taxes and duties are not applicable, the bidder should enter "NA". If no duty/tax is leviable, the same may be entered as 'NIL'. If any column/row is left blank or filled vaguely like "as applicable", the same will be loaded with the maximum of the other eligible bids.
 - ii) Any additional implication because of imposition of or variation in statutory levies on goods, contracted to be supplied, occurring after the expiry of the original contractual delivery date shall not be reimbursable.
- b) GST & Other local taxes on finished products i.e. Transformer including oil and other accessories as per Specification for supply, payable by the purchaser shall be indicated separately both in lump sum and rates of duty, applicable shall be quoted and shall be included in the bid price. The items for which these duties are not quoted by the bidders, shall not be payable by the purchaser and shall be borne by the Bidder/Supplier.
 - c) All GST & Other local taxes payable by the bidders in respect of transaction between the bidders and their vendors/sub-suppliers while procuring any component, sub-assemblies, raw materials and equipment shall be included in the bid price considering input tax credit and no claim on this behalf will be entertained by the purchaser.
 - d) Offers with exemption from Goods and Services Tax shall be accompanied with authenticated attested Photostat copy of exemption certificate. Any claim towards Goods and Services Tax shall be paid on actual basis subject to payment of GST by the supplier. In case Outward supply details of the supplier of Goods in GSTR-1 do not match with GSTR -2 of OPTCL on GSTN portal, the same will be adjusted through debit/credit advice issued by OPTCL under intimation to the supplier after allowing cooling period of 3 months after the date of supply.

27. Supplier's Responsibility.

Notwithstanding anything mentioned in the Specification or subsequent approval or acceptance by the Purchaser, the ultimate responsibility for design, manufacturing, materials used and satisfactory performance shall rest with the Tenderers. The supplier(s) shall be responsible for any discrepancy noticed in the documents, submitted by them along with the bid(s).

28. Validity

Prices and conditions contained in the offer should be kept valid for a minimum period of **240(Two-hundred forty) days** from the date of opening of the tender, failing which the tender shall be rejected.

29. EVALUATION:

- i) **TECHNO-COMMERCIAL BID:-** All the bids, which are opened, read out and considered for evaluation will be checked for qualification requirements as per clause No.30 and stipulations in outright rejection clause No.34 of this section of the specification. Such of the bid(s), which do not meet the qualification requirements and stipulations as per outright rejection clauses, will not be evaluated further.
However, if in the opinion of the purchaser, the bidder has offered equipment/material better than that, specified in the technical specification; the same may be taken into consideration.

Further, the purchaser may enquire from the bidder in writing for any clarification on the bid. The response of the bidder will also be in writing. However, no change in the prices or substance of the bid will be sought, offered or permitted.

II) **PRICE BID:-**Evaluation of price bids will be on the basis of the FOR DESTINATION PRICE including Goods & Services tax and other levies, as may be applicable. The FORD PRICE shall consist of the following components.

- a) Taxable value of the Transformer including oil and other accessories as per specification.
- b) Taxable value of Nitrogen Injection Type Fire Prevention & Extinguishing System
- c) Goods & Services tax
- d) Other levies
- e) Mandatory spares
- f) Type test charges
- g) **Dynamic Short Circuit test charges. However the decision on conducting the Dynamic Short Circuit test shall be taken by OPTCL purchase subcommittee during execution stage of order.**
- h) Supervision of erection, testing and commissioning charges including GST, if applicable
- i) Any other items, as deemed proper for evaluation by the purchaser
- j) For delivery period, quoted beyond the period specified in this specification will attract a loading @ 0.5% of the Taxable value for each week or part thereof delay beyond the base and this will be added to the Bid price for evaluation. Bids, offering completion of delivery longer than 14 weeks after the stipulated delivery period, specified in the specification will be rejected.
- k) Loading will be made for items not quoted by the bidder at the highest rate quoted by other bidders unless particular item is included in other items.
- l) Any imposition of new tax or revision of tax shall be considered between due date of submission of bids and the date of price bid opening.
- m) **E- Reverse Auction process shall be resorted to as detailed below:-**

STRATEGY FOR E-REVERSE AUCTION	
1	Bidders are required to go through the guidelines given below and submit their acceptance to the same.
2	e-Reverse Auction (RA) will be conducted in e-tender portal of OPTCL on specified date and time, while bidders shall quote from their own offices/places of their choice. Internet connectivity shall be ensured by the respective agencies/bidders themselves.
3	Demonstration/ training (if not trained earlier) of bidder's nominated person(s), shall be done to explain all the rules related to e-Reverse Auction/ Business Rule document to be adopted.
4	The strategy to be used for reverse auction shall be "DYNAMIC TEMPLATE BIDDING"
Procedure for electronic Reverse Auctioning (e-RA):	
5	<p>a. The e-RA shall be conducted on www.tenderwizard/OPTCL.com only.</p> <p>b. Bidder has to submit letter towards agreement to the Process related Terms & Conditions for e-Reverse Auction, as per (Reverse Auction Process Compliance Form at Annexure-IB). In non-receipt of the same, vendors will not be allowed to participate in e-RA.</p> <p>c. e-RA shall be carried out after opening of Price bids and completion of Price bid evaluation, which will be intimated only to the techno-commercially qualified bidders by OPTCL as per procedure given below.</p> <p>d. OPTCL reserves the right to conduct e-RA and it is obligatory on part of bidder(s) invited to participate in e-RA process once they have responded to the techno-commercial bid.</p>

6	<p>Prior intimation/ Notice for RA invitation will be given to techno-commercially qualified bidders regarding the date & time of opening of the e-RA.</p> <p>The start bid price (SBP) for e-Reverse Auction of each bidder under a particular package shall be the L1 evaluated price for the subject package including Taxes & Duties for the total scope for subject Package. Taking the above discovered L1 price as the upper limit e-RA will be conducted to determine the lowest possible price.</p> <p>Reverse Auction will be conducted amongst first 50% of the technically qualified bidders arranged in order of prices from lowest to highest, as L1, L2,L3-----Ln, and L1 price will be discovered. Minimum of 3 bidders shall be eligible for e RA. (eg. If 4 bidders are financially evaluated then the L1, L2 and L3 bidders shall be eligible for e-RA). Number of bidders eligible for participating in RA would be rounded off to next higher integer value if number of technically qualified bidders is odd (e.g. if 7 bids are technically qualified, then RA will be conducted amongst L1 to L4).</p> <p>However, in case only two bidders are found to be responsive, e-RA would be carried out with both the parties without any elimination. However, OPTCL reserves the right to invite the evaluated L1 bidder for negotiation without conducting the e-RA.</p> <p>In case of price submitted by any bidder is found to be abnormal, OPTCL reserves the right to reject the bid of the bidder(s).</p> <p>Rank of bidders would be displayed as per the total cost to OPTCL, i.e including Taxes and Duties payable by OPTCL as per the provisions of the bidding document & after e-RA process is over.</p>
7	<p>Names of bidders/ vendors shall not be disclosed during the e-RA process. Names of bidders/ vendors shall be anonymously masked in the e-RA process.</p> <p>(i) In case of RA, start/ reference price and step value of decrement shall be indicated to the bidders at the start of the auction. Any participating bidder can bid one or multiple step decrement lower than the prevailing lowest bid at that time. The Bidder shall be able to view Bid Start Price, Bid Decrement Value, Prevailing Lowest Bid value, last Bid Placed by him and time left for bidding.</p> <p>(ii) The step value of decrement in a package to be offered by bidder (the minimum amount of reduction in the total bid price including all taxes & duties during auction) , shall be kept at 0.15% of L1 bidder's final evaluated price (or) at approved amount as decided by OPTCL.</p> <p>(iii) Bidders can only quote any value lower than their previous quoted price. However, at no stage, increase in Price will be permissible.</p> <p>(iv) At any point during Reverse Auction, bidding Price field (Total price) shall remain enabled for the bidders. The total reverse auction period shall be unlimited and the initial auction period (1st slot) will be of thirty (30) minutes with provision of auto extension by (10) ten minutes from the schedule/ extended closing time. If any fresh lower bid is received in last ten minutes of auction period or extended auction period, the reverse auction process shall get extended automatically for another 10(ten) minutes. In case, there is no Bid received during schedule/extended slot, the Auction shall get closed automatically without further extension.</p> <p>(v) However, bidders are advised not to wait till the last minute or last few seconds to enter their bid during the period of e-reverse auction to avoid complication related with internet connectivity, network problem, system crash down, power failure etc.</p>
8	<p>After conclusion of e-Reverse Auction i.e (Closing Price in Reverse Auction will be taken as offered price by the L1 bidder), decrease in price of individual head of the template shall be considered proportionately on all individual line items of the respective head of the price schedule of the successful L1 bidder .</p>

	<p>Any bid received at the tender wizard server end subsequent to closure of the e-RA shall be summarily rejected and shall not be considered as a valid bid under whatsoever circumstances. For this purpose, tender wizard server log shall prevail.</p> <p>The bidder shall not involve himself or any of his representatives in price manipulation of any kind directly or indirectly by communicating with other bidders.</p> <p>During Reverse Auction, If no bid is received within the specified time, OPTCL, at its discretion, may decide to close the reverse auction process/ proceed with conventional mode of tendering [Evaluation of Part-II (price bid) submitted by bidders earlier].</p>
9	<p>Consequent upon completion of e-Reverse Auction, OPTCL's decision on award of contract shall be final and binding on the bidders.</p> <p>OPTCL shall be at liberty to call the L1 bidder for further process/ negotiation and also at liberty to cancel the e-reverse auction process/ re-tender at any time, without assigning any reason thereof. OPTCL can decide to reschedule or cancel any reverse auction: the bidders shall be informed accordingly.</p> <p>OPTCL/ Service Provider shall not have any liability to bidders for any interruption or delay in access to the e-Tender site/ Reverse Auction link irrespective of the cause.</p>
10	The bidders have to furnish Reverse Auction Process Compliance Form as per Annexure-IA

- N.B:** - a) The purchaser's evaluation of a bid will exclude and not take into account any allowance for price adjustment during the period of execution of the contract, if provided in the Bid.
- b) Arithmetical errors will be rectified on the following basis. If there is a discrepancy between the unit price and the total price that is obtained by multiplying the unit price and quantity, the unit price shall prevail and the total price will be corrected. If there is a discrepancy between the Total Bid Amount and the sum of the total prices, the sum of the total prices shall prevail and the total bid amount will be corrected.

- III) **Weightage shall be given to the following factors in the Evaluation and comparison of Bids:** -
- In comparing bids and in making awards, the purchaser will consider other factors such as compliance with the specification, qualification criteria, outright rejection of tenders, relative quality, adaptability of suppliers or services, experiences, financial soundness, record of integrity in dealings, performance of materials/equipment earlier supplied, ability to furnish repairs and maintenance services, the time of delivery, capability to perform including available facilities such as adequate shops, plants, equipment and technical organization.

30. **QUALIFYING REQUIREMENT OF BIDDER (QR):** -

- a) The bidder should have manufacture and supply experience of the rating as tendered or higher capacity Transformers (both MVA & Voltage rating) for a minimum period of 5(Five) years as on the date of opening of the Techno-Commercial bid.
NB: Period of five years shall be reckoned from the date on which such transformers had been received as per material receipt certificate (MRC) of the transformers issued by the power utility. In case of non-availability of MRC ,Commissioning certificate/performance certificate should be furnished. In such case, date of commissioning of transformer shall be treated as actual date of supply.
- b) Minimum 100% of the total tendered quantity or Five nos whichever is higher (both MVA & voltage rating as per tender or higher capacity) should have been supplied by

the Bidder successfully, within 5(Five) years as on the date of opening of the Techno-Commercial bid.

The material receipt certificate (MRC) / Commissioning certificate / performance certificate shall have to be furnished by the bidders, in support of above.

- c) At least 3(Three) Nos of Transformers of the same rating, as tendered or higher capacity (both MVA and Voltage rating), supplied by the Bidder to Public Sector Electricity Undertaking(s) should have minimum of 3 (Three) years of performance each from the date of commissioning of such Transformers up to the date of the opening of the Techno-Commercial Bids against this Tender.

NB-The bidder in his offer should clearly mention the complete official addresses and contacts Nos of the authorities.(Not below the rank of Executive Engineer/equivalent of the concerned PSU),who have issued the performance certificates.

- d) The tenderer should have adequate infrastructural facility for “after sales service”.

e) Type test reports & NABL accreditation:-

- 1) The bidders shall furnish type test reports with his bid. All type tests conducted on the rating (Both MVA & Voltage Class) or higher capacity(Both MVA & Voltage rating) shall be as per relevant IS / IEC in recognised laboratory. The date of type test shall not be earlier than five years as on the date of bid opening. The bids, received without type test reports may be treated as non-responsive.

- 2.i) The bidder should have NABL accredited testing laboratory and should furnish the copy of NABL accreditation certificate of his laboratory along with their offer.

- 2.ii) If the testing laboratory of the bidder is not NABL accredited, the bidder should get the NABL accreditation before the date of final inspection & testing, in an event the order is placed on them. If the bidder fails to get the NABL accreditations before the time of final testing, then the bidder is required to conduct all the tests on the transformers as stipulated in the Tender specification at any other NABL accredited lab in presence of OPTCL inspector free of cost to OPTCL and without affecting the contractual delivery schedule. **All such bidder(s) are required to furnish a written undertaking in this regard along with their offer.**

- f) Copies of documents, defining the constitution or legal status, place of registration and principal place of business of the company shall be furnished along with the bid. **The Minimum Average Annual Turnover (MAAT) of the Bidder should not be less than 100% of the estimated cost of the tender quantity for best three years out of last five financial years-Audited of profit and loss statement and balance sheet** of the respective year should be furnished.

- g) Even though the bidders meet the above qualifying criteria, they are subject to be disqualified if they have

- i) Made misleading or false representations in the forms, statements and attachments, submitted in proof of qualification requirements and/ or
ii) Record of poor performance such as not properly completing the contract, inordinate delays in completion of supply, litigation history or financial failure etc.

- h) Notwithstanding anything stated above, the purchaser reserves the right to assess the Bidder’s capability and capacity to perform the contract within the scheduled time, should circumstances warrant such assessment in the overall interest of the Purchaser.

NB:- 1)In support of supply of the transformers, as enumerated above, the Bidders should submit the notarized copies of receipted challans of the concerned stores organization(s) along with copies of Excise gate pass(s) ,purchase order(s) of the Transformers, duly notarized, in absence of which the bid may not be considered for evaluation.

2) The scanned copies of all the required documents are to be uploaded by the bidders.

Registration certificate of DPIIT:

A. To be incorporated as qualifying requirement of bidder /certificates in case of tenders for procurement of goods/services(including consultancy and non-consultancy)

I. Any bidder from a country which shares a land border with India will be eligible to bid in this tender only if the bidder is registered with the Competent Authority as per requirement of Govt. of India

II. "Bidder" (including the term 'tenderer', 'consultant' or 'service provider' in certain contexts) means any person or firm or company, including any member of a consortium or joint venture (that is an association of several persons, or firms or companies), every artificial juridical person not falling in any of the descriptions of bidders stated herein before, including any agency branch or office controlled by such person, participating in a procurement process.

III. "Bidder from a country which shares a land border with India" for the purpose of this Order means :-

- a. An entity incorporated, established or registered in such a country ; or
- b. A subsidiary of an entity incorporated, established or registered in such a country ' or
- c. An entity substantially controlled through entities incorporated , established or registered in such a country ; or
- d. An entity whose beneficial owner is situated in such a country ; or
- e. An Indian (or other) agent of such an entity ; or
- f. A natural person - who is a citizen of such a country ; or
- g. A consortium or joint venture where any member of the consortium or joint venture falls under any of the above.

IV. The beneficial owner for the purpose of (iii)(d) above will be as under :

1. In case of a company or Limited Liability Partnership, the beneficial owner is the natural person(s), who, whether acting along or together, or through one or more juridical person, has a controlling ownership interest or who exercises control through other means.

Explanation-

- a. "Controlling ownership interest" means ownership of or entitlement to

more than twenty-five per cent of shares or capital or profits or the company.

b. "Control" shall include the right to appoint majority of the directors or to control the management or policy decisions including by virtue of their shareholding or management rights or shareholders agreements or voting agreement;

2. In case of a partnership firm, the beneficial owner is the natural person(s) who, whether acting along or together, or through one or more juridical person, has ownership or entitlement to more than fifteen per cent of capital or profits of the partnership ;

3. In case of an unincorporated association or body of individuals, the beneficial owner is the natural person(s), who, whether acting along or together, or through one or more juridical person, his ownership or entitlement to more than fifteen per cent of the property or capital or profits of such association or body of individuals ;

4. Where no natural person is identified under (1) or (2) or (3) above, the beneficial owner is the relevant natural person who hold the position of senior managing official ;

5. In case of a trust, the identification of beneficial owner(s) shall include identification of the author of the trust, the trustee, the beneficiaries with fifteen per cent or more interest in the trust and any other natural person exercising ultimate effective control over the trust through a chain of control or ownership.

V. An Agent is a person employed to do any act for another, or to represent another in dealings with third person.

Certificate (to be furnished in bidder's letter head)

I have read the clause regarding restrictions on procurement from a bidder of a country which shares a land border with India; I certify that this bidder is not from such a country or, if from such a country, has been registered with the Competent Authority. I hereby certify that this bidder fulfils all requirements in this regard and is eligible to be considered. [Where applicable, evident of valid registration by the Competent Authority shall be attached.]

31. Jurisdiction of the High Court of Odisha.

Suits, if any, arising out of this contract shall be filed by either Party in a court of Law to which

the jurisdiction of High court of Odisha extends.

32. Correspondences.

- i) Any notice to the supplier under the terms of the contract shall be served by Registered Post or by hand at the Supplier's Principal Place of Business.
- ii) Any notice to the Purchaser shall be served at the Purchaser's Principal Office in the same manner.

33. Official Address of the Parties to the Contract

The address of the parties to the contract shall be specified:-

- [i] **Purchaser:** Senior General Manager (CPC), OPTCL,
Bhubaneswar-751022 (Odisha)

Telephone No. 0674 - 2541801

FAX No. 0674 - 2542964

- [ii] **Supplier:** Address

Telephone No.

Fax No.

34. Outright Rejection of Tenders.

Tenders shall be out rightly rejected if the followings are not complied with –

- i. The tenderer shall submit the bid in electronic mode only and shall submit the cost of tender document and Tender processing fee on or before the last date and time of submission of bid.
- ii. The Tender shall not be submitted telegraphically or by Fax.
- iii. The Tender shall be accompanied by the prescribed Earnest Money deposit unless otherwise qualified for exemption from furnishing of E.M.D. Wherever, EMD is furnished in the form of BG, the said BG should be kept valid for a period of 300(Three Hundred) days from the date of opening of Techno-Commercial Bids. The EMD shall be submitted on or before the last date and time of submission of bid.
- iv. The tender shall be kept valid for a minimum period of 240(Two Hundred Forty) days from the date of opening of tender.
- v. The Tender shall be submitted in two parts, as specified.
- vi. The schedule of price should be filled up fully to indicate the break-up of the prices including taxes and duties. Incomplete submission of this schedule will make the tender liable for rejection; vide Clause No. 4 (ii) of Part-II.
- vii. The Tenderer should quote "VARIABLE PRICE" as per **IEEMA** of Transformers and the price should be kept valid for a minimum period of 240(Two Hundred Forty) days from the date of opening of the Tender.
- viii. Guaranteed Technical Particulars and Abstract of Terms and Conditions should be filled in properly.
- x) Bids, offering completion of delivery, longer than 14 weeks after the delivery period, specified in this Specification, will be rejected.
- xi) The Tenderer should fulfill the "Qualifying Requirement" as per Clause No. 30 of Part-I, Section-II of this Specification.
- xii) The bidder should not have any pending litigation with OPTCL with regard to any project or related activity. The bidder should certify/declare the same in unequivocal terms by way of an affidavit duly sworn before a magistrate or a Notary. Bid furnished by the bidder shall not be eligible for consideration if it is not accompanied by the affidavit. Further the bid / LOA/ LOI shall be liable for outright rejection/ cancellation at any stage if any information contrary to the affidavit / declaration is detected.

35. Documents to be treated as confidential.

The supplier shall treat the details of the specification and other tender documents as private

and confidential and these shall not be reproduced without written authorization from the Purchaser.

36. CONTACTING THE PURCHASER: -

- (a) Subject to Clause No.4 (opening of bids) of part-I, Section-I (Instruction to Tenderer), no bidder shall contact the purchaser on any manner, relating to its bid, from the time of bid opening to the time, the contract is awarded.
- (b) Any effort by a Bidder to influence the purchaser in the purchaser's bid evaluation, bid comparison or contract award decisions may result in the rejection of the Bidder's bid.

37. Scheme/Projects

The materials/equipment covered in this specification shall come under "Construction & O&M Works".

38. EMPANELMENT OF BIDDERS:-

OPTCL may consider for empanelment of such Bidders and for such rating(s) of transformer(s) for which the Bidders will be found to be techno-commercially responsive against this Tender Specification. Such empanelment should be valid for a period of 3(three) years from the date of opening of techno-commercial bids against this Tender. During the above period, OPTCL may ask for price bids and the price will be variable as per **IEEMA PVC**. The bidders are required to give their consent in their offers against the above tender for such empanelment. However, the Bidders are to note that such empanelment is not binding on the purchaser and the purchaser is free to take any other decision under the prevailing circumstances in the interest of OPTCL.

39. LIMITATION OF LIABILITIES:-

The final payment by OPTCL in pursuance of the Contract shall mean the release of the Contractor from all his liabilities under the Contract except for liabilities under Guarantee period. Such contractual liabilities and responsibilities of the Contractor shall prevail till expiry of the guarantee period even after the final payment is released.

Notwithstanding anything to the contrary mentioned herein and to the extent permitted by law, the aggregate liability of Contractor to OPTCL, whether in contract, tort or otherwise, will be limited to 100% of the contract value.

SECTION - III
[LIST OF ANNEXURES]

The following schedules and proforma are annexed to this specification and contained in Section-III as referred to in the relevant clauses: -

1	Declaration form	ANNEXURE-I
2.	Reverse Auction Process Compliance Form	ANNEXURE-IA
3.	Abstract of General Terms & Conditions of contract.	ANNEXURE-II
4.	Check list for qualifying requirements.	ANNEXURE-III
5.	Schedule of Quantity and Delivery.	ANNEXURE-IV
6.	Abstract of price component [to accompany Part-II of this specification]	ANNEXURE-V
7.	Schedule of prices to accompany Part-II	ANNEXURE-VI
8.	Bank Guarantee form for Earnest Money Deposit.	ANNEXURE-VII
9.	Composite Bank Guarantee form for security deposit, payment and performance.	ANNEXURE-VIII
10.	Form of Extension of Bank Guarantee	ANNEXURE-IX
11.	Chart showing particulars of E.M.D.	ANNEXURE-X
12.	Data on Experience.	ANNEXURE-XI
13.	Proforma for performance statement.	ANNEXURE-XII
14.	Schedule of Deviation.	ANNEXURE-XIII
15.	Schedule of spare parts for five years of normal operation and maintenance.	ANNEXURE-XIV
16	Affidavit towards correctness of documents & information furnished by the bidders	ANNEXURE-XV
17	Litigation History	ANNEXURE – XVI
18	Format for Manufacturer's Authorization for Optic Fiber Temperature System (OFTS) being offered	Annexure-XVII
19	Format for Manufacturer's Authorization for Nitrogen Injection Type Fire Prevention & Extinguishing System (NIFPES) being offered	Annexure-XVIII
20	DPIIT Certificate	Annexure-XIX

LIST of Documents

The following documents are to be attached in the below name

- 1.PAN
- 2.GSTIN
- 3.Income tax return
- 4.Audited B/s & Profit loss account

5. Certificate of incorporation
6. E payment proof of tender cost

**ANNEXURE - I
DECLARATION FORM**

[Tender Specification No. S.G.M-CPC-P.T-57/2022-23]

To,
Senior General Manager,
CPC, OPTCL,
Bhubaneswar – 22.

Sir,

1. Having examined the above specification together with terms & conditions referred to therein, *I/We the undersigned hereby offer to supply the materials/equipments, covered therein, complete in all respects as per the specification and General conditions, at the rates, entered in the attached contract schedule of prices in the Tender.
2. * I/We hereby undertake to have the materials/equipments delivered within the time specified in the Tender.
3. * I/We hereby guarantee the technical particulars given in the Tender supported with necessary reports from concerned authorities.
4. * I/We certify to have purchased/ downloaded a copy of the specification by remitting cash/money order/D.D./ remitting the cost of tender, herewith and this has been acknowledged by your letter/ money receipt No. _____
Dated _____
5. In the event of tender, being decided in *my/our favour, *I/We agree to furnish the Composite B.G. in the manner, acceptable to ODISHA POWER TRANSMISSION CORPORATION LIMITED, and for the sum as applicable to *me/us as per clause-19 of section-II of this specification within 15 days of issue of letter of intent/purchase order failing which *I/We clearly understand that the said letter of Intent/Purchase order will be liable to be withdrawn by the purchaser and the EMD, deposited by us shall be forfeited by OPTCL.

Signed this _____ day of _____ 20____

Yours faithfully

Signature of the Tenderer with seal of the company

[This form should be dully filled up by the tenderer and uploaded at the time of submission of tender]

* (Strikeout whichever is not applicable)

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE - IA
(Reverse Auction Process Compliance Form)

(To be submitted on letter head of the bidding company with sign and stamp and along with Technical bid)

To,
Sr. G.M (CPC), OPTCL
Bhubaneswar-751022,
Odisha

Sub: Agreement to the Process related Terms & Conditions for e-Reverse Auction.
Dear Sir,

This letter is to confirm that:

- The undersigned is authorized representative of the company.
- We have studied the Commercial Terms and the Business rules governing the Reverse Auction as mentioned in your tender and confirm our agreement to that.
- We also confirm that we have gone through the auction manual and have understood the functionality of the same thoroughly.
- We, hereby, confirm that we will honour the Bids placed by us during the tendering/ e- Reverse auction process as called as e-RA.
- We also confirm that we will accept our Rank / Position that will be displayed when the Bidding Time for the Online Reverse Auction is over.

With regards,

Signature with Designation with
company seal Name & Address

Person having power of attorney for the subject package.

ANNEXURE-II
ABSTRACT OF GENERAL TERMS AND CONDITIONS OF CONTRACT
[COMMERCIAL] TO ACCOMPANY PART-I

1.	State whether the quotation is in Single part/Two part	Single part /Two part
2.	Whether the material/equipment offered conforms to the OPTCL'S specification (If not, specify the deviations in Annexure).	Yes/No
3(a)	Cost of Tender Document: OPTCL Money Receipt No. & Date / D.D No & Date.	
3(b)	Earnest money furnished. Bank Guarantee No. & Date / D.D No. & Date.	
3(c)	Tender Processing Fee: D.D No. & Date.	
4.	Manufacturer's supply experience including user's certificate furnished or not. [As per clause No.7 of Section-II.]	Yes/No
5(a).	Deviations to the specification if any[list enclosed or not] Commercial [As per clause-9 of the Section-II]	Yes/No
5(b)	Deviations to the specification if any[list enclosed or not] Technical. [As per clause-9 of the Section-II]	Yes/No
6.	Delivery [a] Commencement (No. of months from the date of purchase order)	
	[b]Rate of delivery per month	
	[c]Completion	
7.	Guarantee : - Whether agreeable to OPTCL's terms. [As per clause-18 of Section-II]	Yes/No
8.	Whether agreeable to furnish Composite B.G. in case his tender be successful [As per clause-19 of Section-II]	Yes/No
9.	Terms of payment :- Whether agreeable to OPTCL's terms or not [As per clause-21 of Section-II]	Yes/No
10.	Nature of price :- Variable as per Tender Specification	Yes/No
11.	Price Reduction : - Whether agreeable to OPTCL's terms or not (As per clause-22 of Section-II)	Yes/No
12.	Whether STCC/ P&L A/C, Balance Sheet for the required period are furnished as per clause-25 of Section-II	Yes/No
13.	Validity : - Whether agreeable to OPTCL's terms or not [As per clause-28 of Section-II]	Yes/No
14.	Whether GST is shown separately. % of GST (on Taxable Value) as well as L.S indicated. If Nil/Exempted, Please specify.	
15.	Whether recent type test certificates from any Government approved laboratory is furnished or not. [As per clause-30[e] of section-II]	Yes/No
16.	Whether guaranteed technical particulars are furnished or not	Yes/No
17.	Whether dimensional design/drawings furnished or not	Yes/No
18.	Whether materials are ISI/ISO marked.	Yes/No
19.	Manufacturer's name and it's trademark	Yes/No
20.	Whether registered under GST Laws	Yes/No
21.	Whether declaration form, duly filled in, furnished or not	Yes/No
22.	Whether the bidder is agreed to be empanelled in the list of vendors as per cl.No.38 of Part-I, Section-II of this specification, in the event of its bid, found to be techno-commercially responsive.	Yes/No
23.	Whether furnished the Affidavit as per Annexure-XVI	Yes/No

Place:

Date:

Signature of the Tenderer
with seal of the company.

ANNEXURE-III
CHECK LIST FOR QUALIFYING REQUIREMENTS.

1.	The bidder has manufacturing and supply experience of the rating, as tendered or higher capacity Transformer (both MVA & voltage rating) for a minimum period of 5(Five) years as on the date of opening of Techno-Commercial bid(As per Cl.No -30-a, Section –II of TS). If Yes, necessary supporting documents/informations, furnished or not.	YES/NO YES/NO
2.	Nos. of transformers, as tendered or higher capacity (both MVA and voltage rating), supplied during the above period (Whether separate sheet is enclosed, indicating the MVA, voltage rating of HV/ LV, purchase order No. & Date, Name of the customer, Date of supply etc.) (As per Cl.No -30-b, Section –II of TS). If Yes, necessary supporting documents/informations, furnished or not.	YES/NO YES/NO
3.	The rating, as tendered or higher capacity (both MVA and Voltage rating) transformers have at least 3(Three) years successful performance from the date of commissioning. (As per Cl.No -30-c, Section –II of TS). The user’s certificates enclosed.	YES/NO YES/NO
4.	Whether the bidder has adequate infrastructural facility for “after sales service”. (As per Cl.No -30-d, Section –II of TS).	YES/NO
5.	Type test reports of the bidder for the transformer, offered, or higher capacity (both MVA & voltage rating), tests being conducted in recognized laboratory and not earlier than five years as on the date of opening of bid, furnished. (As per Cl.No -30-e, Section –II of TS). If Yes, necessary supporting documents/informations, furnished or not.	YES/NO
6	Whether the Testing Laboratory of the Bidder is ‘NABL Accredited’ as on the date of opening of the Techno-Commercial bids against this Tender. (As per Cl.No -30-e, Section –II of TS). If Yes, necessary supporting documents/informations, furnished or not. If no whether the required undertaking as per Cl. No -30.e.2.ii, furnished or not	YES/NO YES/NO
7	The Minimum Average Annual Turnover (MAAT) of the Bidder should not be less than 100% of the estimated cost of the tender quantity for best three years out of last five financial years (As per Cl.No -30-e, Section –II of TS). . If Yes, necessary supporting documents/informations, furnished or not.	YES/NO

PLACE:

DATE:

SIGNATURE OF THE BIDDER
WITH SEAL

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE-IV
SCHEDULE OF QUANTITY AND DELIVERY

Sl. No	Description of materials	Quantity required	Desired Delivery	Destination	Remarks.
1	2	3	4	5	6
1.	40MVA, 220/33 KV Power Transformer.	04(Four) Nos.	<u>Delivery Schedule</u> Within 6(Six) Month from the issue of purchase Order.	Any Grid S/S of OPTCL (Existing or New) inside the state of Odisha.	

N.B: -The delivery schedule, destination Sub-station will be intimated at the time of placement of purchase order/release order.

Place:

Date:

Signature of Tenderer
with seal of Company.

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE-V

ABSTRACT OF PRICE COMPONENT

1	Price basis	F.O.R. Purchaser's destination Stores/site.(Taxable value includes packing forwarding, Freight, Insurance, unloading)
2	HSN Code of the Item	
3	GST Identification Number (GSTIN) of the firm	
4	Whether Intra-state supply(i.e. from inside Odisha) or Inter-state supply(i.e from outside Odisha). select from dropdown list	
5	Rate of CGST	
6	Rate of OGST.	
7	Rate of IGST.	
8	Rate of Goods and Services Tax on supervision of erection testing and commissioning	
9.	Nature of price.	
10.	We hereby undertake and declare that implication of lower Tax and Input Tax Credit benefit as per anti-profiteering (under Section 171 of CGST Act) and other provisions under GST Laws have been fully passed on to the purchaser while quoting the price.	Agreed
11.	Any imposition of new tax or revision of tax shall be paid/reimbursed at the time of dispatch, scheduled or actual whichever is lower (i.e. If delivery is within schedule period, tax variation as applicable shall be paid, and if delivery is made beyond schedule date, any additional financial implication due to statutory variation in tax shall be to bidder's account). (Indicated- Yes/No)	

Place:

Date:

Signature of Tenderer.
With seal of Company.

ANNEXURE-VI
SCHEDULE OF PRICES

A	Description of the equipment		
B.	LOT NO. & Quantity (Nos.)		
C. Sl.No	PARTICULARS.		Price in Rupees
1.	a) Taxable value of transformer including oil and other accessories as per Specification along with packing, forwarding, Freight, Insurance, unloading(at site) charges		
	b) Taxable value of Nitrogen Injection Type Fire Prevention & Extinguishing System (As per Technical Specification)		
2.	Unit GST		
	Other Local Taxes		
3.	Unit FORD sub-station/site price with taxes and duties		
4.	Supervision of erection, testing & commissioning charges at site per unit.		
5.	GST, if any, on supervision of erection, testing and commissioning charges per unit.		
6.	Total FORD sub-station site/ store price with taxes and duties Including supervision of erection, testing, commissioning charges & service Tax		
7.	TEST CHARGES [for type tests as specified at clause No. 6.4.1 of Technical specification] [a] Temperature rise test with DGA test before and after Temperature rise test. [b] Measurement of zero sequence impedance [c] Measurement of auxiliary power consumption [d] Vacuum test [e] Pressure test [f] IP-55 Test on cooler control cabinet and OLTC cabinet. [g] Dynamic SC test charges and transportation charges [h] Taxes and duties, if any, on the type test charges		
10.	[i] SPARES FOR THE WHOLE LOT[As per clause No. 5.4.24 of Technical Specification]		
Sl.No.	* Description	Quantity	Price
1	145kV RIP HV Bushing with metal parts & gaskets	2 No	
2	36kV LV Bushing with metal parts & gaskets	1 No	
3	52kV RIP HV Neutral Bushing with metal parts & gaskets	1 No	
4	36kV LV Neutral Bushing with metal parts & gaskets	1 No	
5	Winding Temperature indicators with contacts	1 set	
6	Oil Temperature indicators with contacts	1 set	
7	Pressure Relief Device	2 No	

8	Magnetic oil level gauge with low oil level alarm contacts	1 No	
9	Cooler fan with motor	2 No	
10	Buchholz relay	2 No	
11	Tap position Indicator	1 No	

TOTAL PRICE-

9 GST on Spares, if any.

10 Any other LOCAL taxes on spares.

Signature of Tenderer
Name, Designation and Seal

NB: -

- 1) The tenderer should fill up the price schedule properly in Excel file in e-tender mode. The tender will be rejected, if the price bid is not submitted in accordance with the price schedule. No post tender correspondence will be entertained on break-up of prices. Also, the supplier should agree for delivery at the desired site.
- 2) The Tenderer shall give an undertaking in part-I of the bid that, entire implication of lower Tax and Input Tax Credit benefit have been fully passed on to the purchaser as per anti-profiteering and other provisions under GST Laws while quoting the tender price.
- 3) Conditional offers will not be acceptable.
- 4) The price for Nitrogen Injection system for protection against fire & explosion shall be quoted on 'FIRM PRICE' basis.
- 5) Type Test charge & special test charges (FIRM price) should be quoted for each individual type test and the bid, having lump sum price, quoted for all type test charges together is liable for rejection.
- 6) Rate of each spare (FIRM price) should be quoted and the bid, having lump sum price, quoted for all mandatory spares together is liable for rejection.
- 7) Price for Supervision of erection, testing & commissioning charges shall be quoted on 'FIRM PRICE' basis.

ANNEXURE-VII

PROFORMA FOR BANK GUARANTEE FORM FOR EARNEST MONEY DEPOSIT

(To be Stamped in accordance with Stamp Act and the Non-Judicial Stamp Paper of appropriate value should be in the name of Issuing Bank)

Ref No:
Bank Guarantee No.
Date:.....
BG Amount:.....
Validity Period:.....

This Guarantee Bond is executed this..... day of by us the..... Bank at , P.O..... , Dist....., State..... and Code No.....

Whereas the ODISHA POWER TRANSMISSION CORPORATION Limited, Janpath, Bhubaneswar, a company constituted under the Companies Act-1956 (hereinafter called OPTCL) has invited Tender vide e-NIT No..... Dated..... for the purpose of work under Package(s) No...../ purchase of ----- .

1. Now, therefore, in accordance with Notice Inviting Tender (e-NIT) No..... Dated of OPTCL, Ms/Shri.....Address..... Wish / wishes to participate in the said tender and as a Bank Guarantee for the sum of Rs..... [Rupees in **words**-----] valid for a period ofdays is required to be submitted by the bidder, as per Tender Specification, we the _____) [indicate the name, Address & Code of the bank] [hereinafter referred to as "Bank"] at the request of Ms/Shri..... [hereinafter referred to as "Bidder"] do hereby unequivocally and unconditionally guarantee and undertake to pay during the above said period on written request by the <Tender Issuing Authority, Central Procurement Cell (CPC) ODISHA POWER TRANSMISSION CORPORATION Ltd. , Bhubaneswar an amount not exceeding Rs..... to OPTCL, without any reservation. The guarantee would remain valid up to [Date] and if any further extension to this is required, the same will be extended on receiving instruction from ----- on whose behalf this Bank Guarantee has been issued.

2. We, the _____ [indicate the name of the Bank, Address, Code] do hereby further undertake to pay the amounts due and payable under this guarantee without any demur, merely on a demand from OPTCL. Any such demand made on the Bank shall be conclusive as regards the amount due and payable by the Bank under this guarantee. However, our liability under this guarantee shall be restricted to an amount not exceeding Rs..... (Rupees in words.....)

3. We undertake to pay to OPTCL any money so demanded not withstanding any dispute or disputes so raised by the bidder in any suit or proceeding instituted/pending before any court or tribunal relating thereto, our liability under this present being absolute and unequivocal. The payment so made by us under this bond shall be a valid discharge of our liability for payment thereunder and the bidder shall have no claim against us for making such payment.
4. We, the _____ Bank further agree that the guarantee herein contained shall remain in full force and effect during the aforesaid period of _____ days [in words]..... (as per Tender Specification) and it shall continue to be so enforceable till all the dues of OPTCL under or by virtue of the said Bid have been fully paid and its claims satisfied or discharged or till OPTCL certifies that the terms and conditions of the said Bid have been fully and properly carried out by the said bidder and accordingly discharges this guarantee. Unless a demand or claim under this guarantee is made on us or our Branch Office at Bhubaneswar <Mention Name, Address & Code of the Branch Office at Bhubaneswar of Issuing Bank> in writing on or before _____ we shall be discharged from all liability under this guarantee thereafter.
5. We the _____ Bank further agree with OPTCL that OPTCL shall have the fullest liberty without our consent and without affecting in any manner our obligations hereunder to vary any of the terms and conditions of the said Bid or to extend time of performance by the said Bidder from time to time or to postpone for any time or from time to time any of the powers exercisable by OPTCL against the said Bidder and to forbear or enforce any of the terms and conditions relating to the said Bid and we shall not be relieved from our liability by reason of any such variation, postponement or extension granted to the Bidder or for any forbearance, act or omission on the part of OPTCL or any indulgence by OPTCL to the said Bidder or by any such matter or thing whatsoever which under the law relating to sureties would, but for this provision, have the effect of so relieving us.
- 6 This guarantee will not be discharged due to the change in the name, style and constitution of the Bank and/or of the Bidder.
- 7 We _____ [indicate the name of Bank, Address & Code] lastly undertake not to revoke this guarantee during its currency except with the previous consent of OPTCL in writing .
8. We, the _____ Bank (Name, Address & Code) further agree that this guarantee shall also be invocable at our place of business at ----- Branch of **Bhubaneswar** (indicate Name, Address & Code of the Branch at Bhubaneswar) in the State of Odisha.”

“ Notwithstanding anything contained herein”

- a) Our liability under the bank guarantee shall not exceed Rs.----- (Rupees in words-----) only.
- b) This Bank guarantee shall be valid up to -----.
- c) We or our Branch at Bhubaneswar <Mention Name, Address & Code.....> shall be liable to pay guaranteed amount or any part thereof under this guarantee only if you serve upon us at----- Branch of Bhubaneswar a written claim or demand on or before,

The Bank Guarantee is issued in paper form and Advice transmitted through SFMS with required details to the beneficiary's advising bank (ICICI Bank Bhubaneswar, IFSC Code ICIC0000061).

Dated, the _____ Day of _____

For _____ [Indicate name of Bank]

Signature
 Full name
 Designation
 Power of Attorney No.
 Date.....
 Seal of the Bank.....

WITNESS: (SIGNATURE WITH NAME AND ADDRESS)

(1)
 Signature
 Full name
 (2)
 Signature
 Full name

N.B.:

1. Name of the Bidder.:
2. BG No & Date :.....
3. Amount (In Rs.):.....
4. Validity up to :.....
5. E-NIT No.....
6. Package/Works No.....
7. Name, Address & Code of Issuing Bank:.....
8. Name, Address & Code Bhubaneswar Branch of the Issuing Bank:.....
9. The Bank Guarantee shall be accepted after getting SFMS advice as per details below.

**Format for SFMS details
 (The Unique Identifier for field 7037 is "OPTCL541405793")**

Sl. No	PARTICULARS	TYPE	DETAILS
1	Type of Bank Guarantee	Mandatory	EMD
2	Currency & Amount	Mandatory	
3	Validity Period(from—to --)	Mandatory	
4	Effective Date	Mandatory	
5	End date of lodgment of Claim	Mandatory	
6	Place of lodgment of claim	Mandatory	Bhubaneswar, Branch Name----- of Bhubaneswar Branch code----- of Bhubaneswar Branch Address ----- at Bhubaneswar

7	Issuing Branch IFSC Code	Mandatory	
8	Issuing Branch name & address	Mandatory	
9	Name of applicant and its details	Mandatory	
10	Name of Beneficiary and its details	Mandatory	
11	Beneficiary's Bank/Branch and IFSC Code	Mandatory	ICICI Bank Ltd IFSC Code-ICIC0000061
12	Beneficiary's Bank/Branch name and address	Mandatory	ICICI Bank Ltd Bhubaneswar Main Branch, Bhubaneswar
13	Sender to receiver information	Mandatory	
14	Purpose of Guarantee	Mandatory	EMD
15	Reference/Description of the underlined tender/contract	Mandatory	NIT No

ANNEXURE-VIII

PROFORMA FOR COMPOSITE BANK GUARANTEE FOR SECURITY DEPOSIT, PAYMENT AND PERFORMANCE

(To be stamped in accordance with Stamp Act and the Non-Judicial stamp paper of appropriate value should be in the name of the Issuing Bank.)

Ref No:-

Bank Guarantee No.

Date:

BG Amount:.....

Validity Period:.....

This Guarantee Bond is executed this..... day of by us the..... Bank at , P.O..... , Dist....., State..... and Code No.....

Whereas the ODISHA POWER TRANSMISSION CORPORATION Limited, Janpath, Bhubaneswar, a company constituted under the Companies Act-1956 (hereinafter called OPTCL) has issued Letter of Award (LOA) No..... Dated..... for the purpose of work under Package No..... (herein after called "the Agreement") to M/s/Shri , Address..... (herein after called the "Contractor") for supply, erection, installation & commissioning and associated civil works under the above LOA and whereas OPTCL has agreed (1) to exempt demand of security deposit under the terms and conditions of the LOA (2) to release payment of the cost of the Contract Price to the Contractor on furnishing by the Contractor to OPTCL a Contract Performance Bank Guarantee (CPBG) of the value of 10% of the Contract Price of the said Agreement.

1. Now therefore, in accordance with the terms and conditions of LOA No. _____ dated _____ for the due fulfillment by the said Contractor of the terms and conditions contained in the said agreement, on production of a Bank Guarantee for Rs. _____ (Rupees _____) only, we the bank _____ [Indicate bank Name , Address & Code] (hereinafter referred to as "the Bank") at the request of M/s/Shri _____ contractor do hereby undertake to pay to OPTCL, an amount not exceeding Rs. _____ (Rupees _____) only .

2. We, the _____ Bank [indicate the name of the Bank, Address & Code] do hereby undertake to pay the amounts due and payable under this guarantee without any demur, merely on a demand from OPTCL. Any such demand made on the bank shall be conclusive as regards the amount due and payable by the bank under this guarantee. However, our liability under this guarantee shall be restricted to an amount not exceeding Rs. _____ (Rupees----- In Words).

3. We, the Bank also undertake to pay to OPTCL any money so demanded not withstanding any dispute or disputes raised by the Contractor in any suit or proceeding instituted / pending before any court or tribunal relating thereto, our liability under this present being absolute and irrevocable. The payment so made by us under this bond shall be a valid discharge of our liability for payment thereunder and the Contractor shall have no claim against us for making such payment.

4. We, the _____ Bank further agree that the guarantee herein contained shall remain in full force and effect during the aforesaid period of _____ days and it shall continue to be so enforceable till all the dues of OPTCL under or by virtue of the said Agreement have been fully paid and its claims satisfied or discharged or till OPTCL certifies that the terms and conditions of the said Agreement have been fully and properly carried out by the said contractor and accordingly discharges this guarantee.

Unless a demand or claim under this guarantee is made on us or our Branch Office at Bhubaneswar <Mention Name, Address & Code of the Branch Office at Bhubaneswar of issuing Bank> in writing on or before (Date), we shall be discharged from all liability under this guarantee thereafter.

5. We, the _____ Bank [indicate the name of the Bank, Address & Code] further agree with the Board that OPTCL shall have the fullest liberty without our consent and without affecting in any manner our obligations hereunder to vary any of the terms and conditions of the said Bid or to extend time or performance by the said contractor(s) from time to time or to postpone for any time or from time to time any of the powers exercisable by OPTCL against the said contractor(s) and to forbear or enforce any of the terms and conditions relating to the said Bid and we shall not be relieved from our liability by reason of any such variation postponement or extension being granted to the said contractor(s) or for any forbearance, act or omission on the part of OPTCL or any indulgence by OPTCL to the said contractor(s) or by any such matter or thing whatsoever which under the law relating to sureties would, but for this provision, have the effect of so relieving us.

6. This guarantee will not be discharged due to the change in the name, style or constitution of the Bank and/or of the contractor(s).

7. We, the _____ Bank [indicate the name of the bank, Address & Code] lastly undertake not to revoke this guarantee during its currency except with the previous consent of OPTCL in writing.

8. We, the _____ Bank (Name, Address & Code) further agree that this guarantee shall also be invocable at our place of business at -----Branch of **Bhubaneswar** (indicate Name, Address & Code of the Branch at Bhubaneswar) in the State of Odisha.

“ Notwithstanding anything contained herein”

a) Our liability under the bank guarantee shall not exceed Rs.----- (Rupees in words-----) only.

b) This Bank guarantee shall be valid up to -----.

c) We or our Branch at **Bhubaneswar** <Mention Name, Address & Code.....> shall be liable to pay guaranteed amount or any part thereof under this guarantee only if you serve upon us at----- Branch of Bhubaneswar a written claim or demand on or before,

The Bank Guarantee is issued in paper form and Advice transmitted through SFMS with required details to the beneficiary’s advising bank (**ICICI Bank Bhubaneswar**, IFSC Code ICIC0000061).

Dated, the _____ Day of _____
For _____ [Indicate name of Bank]

Signature.....
Full Name.....

Designation.....
Power Of Attorney.....
Dated.....
Seal of the Bank.....

WITNESS: (SIGNATURE WITH NAME AND ADDRESS)

1. Signature.....
Full Name.....

2. Signature.....
Full Name.....

N.B.:

1. Name of the Contractor.:
2. BG No & Date :.....
3. Amount (In Rs.):.....
4. Validity up to :.....
5. LOA No.....
6. Package No.....
7. Name, Address & Code of Issuing Bank:.....
8. Name, Address & Code of Bhubaneswar Branch of the Issuing Bank:.....
1. The Bank Guarantee shall be accepted after getting SFMS advice as per details below.

Format for SFMS details
(The Unique Identifier for field 7037 is “OPTCL541405793”)

Sl. No	PARTICULARS	TYPE	DETAILS
1	Type of Bank Guarantee	Mandatory	Contract Performance
2	Currency & Amount	Mandatory	
3	Validity Period(from—to --)	Mandatory	
4	Effective Date	Mandatory	
5	End date of lodgment of Claim	Mandatory	
6	Place of lodgment of claim	Mandatory	Bhubaneswar, Branch Name----- of Bhubaneswar Branch code----- of Bhubaneswar Branch Address ----- at Bhubaneswar
7	Issuing Branch IFSC Code	Mandatory	
8	Issuing Branch name & address	Mandatory	
9	Name of applicant and its details	Mandatory	
10	Name of Beneficiary and its details	Mandatory	
11	Beneficiary's Bank/Branch and IFSC Code	Mandatory	ICICI Bank Ltd IFSC Code-ICIC0000061
12	Beneficiary's Bank/Branch name and address	Mandatory	ICICI Bank Ltd Bhubaneswar Main Branch, Bhubaneswar
13	Sender to receiver information	Mandatory	
14	Purpose of Guarantee	Mandatory	Contract Performance
15	Reference/Description of the underlined tender/contract	Mandatory	LOA No----

ANNEXURE-IX

**FORM OF EXTENSION OF BANK GUARANTEE
(ON NON-JUDICIAL STAMP PAPER OF Rs.100/-)**

Ref. No. _____

Dated: _____

Sr. General Manager,
(Central Procurement Cell)
OPTCL, Bhubaneswar-751022.

Dear Sirs,

Sub: Extension of Bank Guarantee No. _____ for Rs. _____ favouring yourselves
expiring _____ on account of M/s. _____ in respect of contract
No. _____ dated _____ (hereinafter called original bank guarantee).

At the request of M/s. _____ we _____ bank Branch office at
_____ having its head office at _____ do hereby extend our liability under
the above mentioned guarantee No. _____ Dated _____ for a further
period of _____ Years/months from _____ to expire on _____ except as
provided above, all other terms and conditions of the original bank guarantee
No. _____ dated _____ shall remain unaltered and binding.

Please treat this as an integral part of the original guarantee to which it would be
attached.

Yours faithfully,

For _____
Manager/Agent/Accountant

POA No. _____

Date: _____

SEAL OF BANK

Note: The non-judicial stamp paper of worth Rs.100/- shall be purchased in the
name of the bank, which has issued the bank guarantee.

ANNEXURE-X

CHART SHOWING PARTICULARS OF EARNEST MONEY DEPOSIT FURNISHABLE BY TENDERERS OF DIFFERENT CATEGORIES

1.	Central and state Government undertakings	The amount of EMD as specified in the Specification /Tender Notice in shape of bank guarantee /DD.
2.	All other inside and outside State Units.	

NB: - REFUND OF E.M.D.

- [a] In case of Unsuccessful Bidders, the EMD BG will be returned in two phases i.e. after disqualification of a bidder in Techno-Commercial Evaluation and after award of contract. In case of Successful bidder, the EMD BG shall be returned only after submission & approval of Composite Bank Guarantee referred to in clause No.19 of Section-II of this specification. Suits, if any, arising out of EMD shall be filed in a court of law to which the jurisdiction of High Court of Odisha extends.
- [b] The successful bidder shall have to keep the EMD BG valid till the approval of Composite Bank Guarantee.
- [c] Earnest Money will be forfeited if the tenderer fails to accept the letter of intent/purchase order, issued in his favour or revises the bid price[s] within the validity period of Bid.

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE-XI

DATA ON EXPERIENCE

- [i] Name of the manufacturer:
- [ii] Standing of the firm and rating of Transformer, quoted:
- [iii] Description of Transformer, quoted, supplied and installed with the name(s) of the Organisations to whom supplies were made along with Purchase Order No. & Date, wherein, at least 3 (Three) certificate shall be from a State/Central P.S.U or in accordance with Qualifying Requirement, as stipulated at Cl.No.30 of Part-II, Section-II of this Tender Specification
- [iv] Details as to where installed and commissioned, as per the above Qualifying Requirement.
- [v] Testing facilities at manufacturer's works.
- [vi] A list of purchase orders of the same rated Transformer, as offered as per technical specification or higher rating (both MVA & Voltage rating) along with user's certificate, as applicable in accordance with the above Qualifying Requirement of this Specification. User's certificate shall be legible and must indicate, user's name, address, designation, Telephone & FAX No., place of use and satisfactory performance of the Transformers for a period, as stipulated in the above Qualifying Requirement, from the date of commissioning.

Place:

Date:

Signature of tenderer
Name, Designation, Seal

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE-XII

PROFORMA FOR PERFORMANCE STATEMENT.

Bid No. _____

Date of Opening. _____

Name of the Firm _____

Order placed by {full name & address of purchaser}	Order No. and Date.	Description and quantity of ordered Equipment.	Date of completion of Delivery.	
			As per Contract	Actual

Remarks indicating reasons for late delivery, if any.	Has the equipment been satisfactorily functioning? (Attach a Certificate from the purchaser)

Signature of the Bidder _____

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE-XIII

SCHEDULE OF DEVIATION.

A. TECHNICAL.

Sl.No.	Requirements/ Equipment.	Specification Clause No.	Deviations.	Remarks
No deviations				

It is hereby conformed that except for deviation mentioned above, the offer conforms to all the other features specified in Technical Specification Section _____ of this Bid document.

Place:

Signature of the Bidder.

Date:

Name:

Business address:

B. COMMERCIAL.

Sl.No.	Requirements/ Equipment.	Specification Clause No.	Deviations.	Remarks
No deviations				

It is hereby conformed that except for deviation mentioned above, the offer conforms to all the other features specified in Commercial Specification Section _____ of this Bid documents.

Place:

Signature of the Bidder.

Date:

Name:

Business address:

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

Annexure-XV

AFFIDAVIT OF BIDDER

BEFORE Sri / _____ Notary
at. _____

AFFIDAVIT

WHEREAS the Odisha Power Transmission Corporation Ltd., Bhubaneswar (OPTCL) has floated its Tender No _____ inviting bids from eligible bidder to execute the work of _____.

And WHEREAS M/s. _____ (briefly "Bidder") has offered its bid on _____ in response to the said Tender No. _____ of the OPTCL expressing its interest to execute the work as specified therein.

AND WHEREAS the said Tender No. _____ of OPTCL requires the Bidder to solemnly affirm the correctness of the document and information furnished in its bid, so offered to OPTCL.

NOW TEREFORE, in response to the requirement, the Tender No. _____ of OPTCL and having been duly authorized by the Bidder, I Sri/ Mrs. _____ aged about _____ years. Son / Daughter / Wife of Sri / Mrs. _____. At present working as _____ of M/s. _____ (the Bidder) do hereby solemnly affirm and state as follows.

1. That I am competent and have been duly authorized by the Bidder M/s. _____ to swear this affidavit on its behalf.
2. That the documents and information furnished by the Bidder in its bid offered in respect to the said Tender No. _____ of OPTCL are true and correct.
3. That in the event any document and information as furnished by the bidder in response to the said Tender No. _____ of OPTCL at any time as to be not correct / wrong, the OPTCL shall be competent and at liberty without any show cause to the Bidder to terminate its contact/ agreement with the bidder if any.
4. The OPTCL shall also be competent, without any reference to the Bidder, to black list the Bidder and debar the Bidder from participating in any other Tender of OPTCL pursuant to its consideration / finding that the Bidder has furnished any incorrect / wrong document and information tendered / made pursuant to Tender No. _____ of OPTCL.
5. That the affirmation made herein above is / are correct and true and nothing stated herein is false.

Identified by

DEPONENT

ADVOCATE

ANNEXURE – XVI
LITIGATION HISTORY

Name of the Bidder:

Bidder should provide information on any history of litigation or arbitration resulting from contracts executed in the last five years or currently under execution.

Year.	Award for or against bidder	Name of client, cause of litigation and matter in dispute	Disputed amount (current value in Rs.)

Place: -

Date

Signature of Bidder:

Annexure-XVII

[Manufacturer's Authorization for Optic Fiber Temperature System (OFTS) being offered]

Ref: _____

Date: _____

To,

The SG.M, CPC, OPTCL,1ST FLOOR, MULTI STORIED BUILDING, ODISHA POWER TRANSMISSION CORPORATION LIMITED,BHUBANESWAR.

We, _____ who are established and reputed manufacturer, meeting the Qualifying requirement of Supply of **Optic Fiber Temperature System (OFTS)** equipment as per your tender specification, having factories in _____ do hereby authorize M/s _____ to offer our equipment for tender against NIT No. _____ & Tender Specification -----

We hereby undertake that **Optic Fiber Temperature System (OFTS)** equipment being offered will meet the relevant technical specification of _____. The supervision of erection, testing and commissioning of the offered equipment at site which will be carried out by our Service Engineer. We hereby confirm that the necessary spares for the above item(s) shall be available for the period for 10 years from the date of commissioning of transformer.

(Signature of Authorized Representative)

Name:

Designation:

Common Seal of the Company:

WITNESS SIGNATURE WITH ADDRESS

1.

2.

Notes:-

- 1) The manufacturer authorization shall be submitted from the Optic Fiber Temperature System (OFTS) equipment manufacturer(s), which should be filled in non-judicial stamp paper of worth Rs.100/- and duly Notarized.
- 2) The bidder shall furnish the copy of the Power of Attorney of the Optic Fiber Temperature System (OFTS) equipment manufacturer(s) in the name of their above authorized signatory, along with the bid.
- 3) The bidder shall submit the manufacturer authorization from such manufacturer(s) who meets the requirements as stated for the equipment.

ANNEXURE-XVIII

[Manufacturer's Authorization for Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES) being offered]

Ref: _____

Date: _____

To,
The SG.M, CPC, OPTCL, 1ST FLOOR, MULTI STORIED BUILDING, ODISHA POWER TRANSMISSION CORPORATION LIMITED, BHUBANESWAR.

We, _____ who are established and reputed manufacturer, meeting the Qualifying requirement of Supply of **Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES)** equipment as per your tender specification, having factories in _____ do hereby authorize M/s _____ to offer our equipment for tender against NIT No. _____ & Tender Specification -----

We hereby undertake that **Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES)** equipment being offered will meet the relevant technical specification of _____. The supervision of erection, testing and commissioning of the offered equipment at site which will be carried out by our Service Engineer. We hereby confirm that the necessary spares for the above item(s) shall be available for the period for 10 years from the date of commissioning of transformer.

(Signature of Authorized Representative)

Name:

Designation:

Common Seal of the Company:

WITNESS SIGNATURE WITH ADDRESS

- 1.
- 2.

Notes:-

1. The manufacturer authorization shall be submitted from the Nitrogen Injection Type Fire Prevention & Extinguishing System (NIFPES) equipment manufacturer(s), which should be filled in non-judicial stamp paper of worth Rs.100/- and duly Notarized.
2. The bidder have furnish the copy of the Power of Attorney of the Nitrogen Injection Type Fire Prevention & Extinguishing System (NIFPES) equipment manufacturer(s) in the name of their above authorized signatory, along with the bid.
3. The bidder shall submit the manufacturer authorization from such manufacturer(s) who meets the requirements as stated for the equipment.

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE-XIX

Certificate (to be furnished in bidder company's letter head)

I have read the clause regarding restrictions on procurement from a bidder of a country which shares a land border with India and on sub-contracting to contractors from such countries; I certify that this bidder is not from such a country or, if from such a country, has been registered with the Competent Authority and will not sub-contract any work to a contractor from such countries unless such contractor is registered with the Competent Authority. I hereby certify that this bidder fulfils all requirements in this regard and is eligible to be considered. [Where applicable evidence of valid registration by the Competent Authority shall be attached.]

Authorized signatory

Company seal

PART - II PRICE BID

1. PRICE:

(i) Bidders are required to quote their price(s) for goods offered indicating they are **Variable Price (as per IEEMA) of Transformers (ANNEXURE-XV).**

(ii) The prices (inclusive of oil and other accessories) quoted shall be FOR Destination only at the consignee's site/store inclusive of packing, forwarding, Freight & Insurance. In addition, the break-up of FOR Destination price shall be given as per schedule of Prices in Annexure-VI of Section - III. The Tenderer has to certify in the price bid that Input tax Credit benefit if any, has been fully passed on to the Purchaser, while quoting the tender prices.

2. INSURANCE:

Insurance of materials/equipments covered by the Specification should normally be done by the Suppliers with their own Insurance Company unless otherwise stated. The responsibility of delivery of the materials/equipments at destination stores/site in good condition rests with the Supplier. Any claim with the Insurance Company or Transport agency arising due to loss or damage in transit has to be settled by the Supplier. The Supplier shall undertake free replacement of equipments/materials damaged or lost which will be reported by the Consignee within 30 days of receipt of the equipments/materials at Destination without awaiting for the settlement of their claims with the carriers and underwriters.

3. CERTIFICATE FOR EXEMPTION FROM GST:

Offers with exemption from GST shall be accompanied with authenticated proof of such exemption. Authenticated proof for this clause shall mean attested Photostat copy of exemption certificates. Any claim towards Goods & Services Tax shall be paid on actual basis subject to production of Authenticated documentary evidence.

4. PROPER FILLING UP OF THE PRICE SCHEDULE:

The tenderer should fill up the price schedule (Annexure-VI of Section-III) properly and in full. The tender may be rejected if the schedule of price is submitted in incomplete form as per clause-34(vii) of Section-II of the Specification.

5. NATURE OF PRICE INDICATED IN SPECIFICATION SHALL BE FINAL.

The nature of price indicated in the Clause-13, Section - I of PART -I of the Specification shall be final and binding.



SECTION-IV
TECHNICAL SPECIFICATION

FOR

PROCUREMENT OF

**TENDER SPECIFICATION NO. SR.G.M -CPC-POWER TRANS-57/2022-23
TOWARDS PROCUREMENT OF**

40 MVA, 220/33 KV POWER TRANSFORMER –4 NOS.

TECHNICAL SPECIFICATION

<u>Sl. No.</u>	<u>TITLE.</u>
1.0	SCOPE.
2.0	Standards
3.0	Auxiliary Power Supply.
4.0	Principal Parameters.
5.0	General Technical Requirements.
5.1	Duty requirements.
5.2	Transformer Losses
5.3	Clearance.
5.4	Constructional Details.
5.4.1	Tank and Tank Accessories.
5.4.2	Valves and Location.
5.4.3	Joints and Gaskets.
5.4.4	Pressure relief device.
5.4.5	Earthing terminals.
5.4.6	Corrosion Protection.
5.4.7	Rating, diagram and valve plates.
5.4.8	Core.
5.4.9	Windings.
5.4.10	Gas and Oil actuated relays.
5.4.11	Temperature indicating devices and alarms.
5.4.12	Cooling equipment and its control.
5.4.13	Voltage selection and control.
5.4.14	Supervisory control.
5.4.15	Terminal and connection arrangements.
5.4.16	Specification for control cabinets.
5.4.17	Insulating Oil.
5.4.18	Cleaning, painting and tropicalisation.
5.4.19	Bolts and Nuts.
5.4.20	Wiring and cabling.
5.4.21	Fittings.
5.4.22	Limits of Temperature rise.
5.4.23	Motors & MCBs.
5.4.24	Spanners & Special tools.
5.4.25	List of Mandatory Spares.
6.0	INSPECTION AND TESTING.
6.1	Testing facilities
6.2	General
6.3	Stage Inspection.
6.4	Final Inspection
6.4.1	Type Tests & Special Tests
6.4.2	Routine Tests
6.4.3	Challenge Test
6.4.4	Tests on site
7.0	TEST REPORTS.
8.0	LIST OF TRANSFORMER ACCESSORIES AND TEST CERTIFICATES REQUIRED FOR THEM.
9.0	INSPECTION.
9.1	General.

9.2	Inspection Programme.
9.3	Pre-shipment check at supplier's works.
9.4	Recommended commissioning checks.
10.0	QUALITY ASSURANCE PLAN.
11.0	DOCUMENTATION.
12.0	PACKING AND FORWARDING.
13.0	SUPERVISION OF ERECTION, TESTING AND COMMISSIONING.
14.0	QUANTITY AND DELIVERY REQUIREMENTS.
15.0	VALUES QUOTED IN G.T.P. AND LOSS CALCULATION.
16.0	METHOD OF TECHNICAL EVALUATION.

ANNEXURES

No. Title.

- I. Quantity and Delivery Schedule.
- II. Maximum Flux Density and Core
Weight calculation.
- III. Details of Loss Calculations.
- IV. Guaranteed Technical Particulars.
- V. Additional Schedule of Informations.
- VI. Check list towards Type Test Reports.
- VII. Calibration Status of Testing
Instruments/Meters.
- VIII. Check list for Delivery Schedule.
- IX. Abstract of Terms & Conditions
(Technical).
- X. Manufacturer's Authorization for Optic Fiber Temperature System (OFTS) being offered.
- XI. Manufacturer's Authorization for Nitrogen Injection Type Fire Prevention &
Extinguishing System(NIFPES) being offered.

N. B. : 1. Annexure-II to IX are to be filled up in complete shape by the bidders, failing which their tenders are liable for rejection.

- 2. No approximate value is allowed in respect of any of the parameters, as asked in the above Annexures. The bidders may quote the firm values with tolerances, if asked in respective parameters.***

SECTION - IV.

TECHNICAL SPECIFICATION

1.0 **SCOPE:**

1.1 This Specification provides for design, engineering, manufacture, assembly, stage inspection, final inspection and testing before dispatch, packing and delivery at destination Sub-station by road transport, unloading at site and supervision of erection, testing and commissioning of 40 MVA, 220/33kV Power Transformers complete with all fittings, accessories, associated equipments and spares, required for its satisfactory operation in any of the sub-stations of the State of Odisha.

1.2 The scope of supply includes the provision of training for Purchaser's personnel.

1.3 The transformers shall conform in all respects to high standards of engineering, design, workmanship and the latest revisions of relevant standards at the time of offer and Purchaser shall have the power to reject any work or material which, in his judgment, is not in full accordance therewith. The transformer(s), offered shall be complete with all components, necessary for their effective and trouble free operation. Such components shall be deemed to be within the scope of supply, irrespective of whether those are specifically brought out in this Specification and/or the commercial order or not.

1.4 The transformer(s), to be supplied against this specification shall be suitable for satisfactory continuous operation under the following Topographical and Meteorological conditions:-

a) Maximum ambient air temperature (°C) -	50
b) Minimum ambient air temperature (°C)-	0
c) Average daily ambient air temperature (°C)-	32
d) Relative humidity (%) -	100
e) Average rainfall per annum (cm)-	150
f) Maximum altitude above mean Sea level (m)-	1000
g) Isoceraunic level (days/year)-	70
h) Seismic withstand factor(g)	0.3
i) Wind Velocity-(Wind Zone to IS875) (m/sec)	55(Zone-VI)
j) Pollution level to IEC815	Heavy/Very Heavy
k) Air-borne contamination, if any	Highly Polluted
l) special environmental condition	Salinity and exposure to moisture in coastal areas and excessive dust in industrial belts of the State
.	
.	
.	
m) Specific Creepage Distance of insulation in air	31mm/kv

2.0 **STANDARDS:**

- 2.1 All transformers and associated equipments and accessories shall, except where modified by this Specification, be designed, manufactured and tested in accordance with the latest editions of the relevant International (IEC), Indian (IS) and British (BS) standards. In case of conflict, the order of precedence shall be (1) IEC, (2) IS, (3) Other.

Reference to particular standard or recommendation in this Specification does not relieve the Supplier of the necessity of providing goods and services, complying with other relevant standards or recommendations.

The list of standards, provided in this Specification is not to be considered exhaustive and the supplier shall ensure that equipments, supplied under this contract meet the requirements of the relevant standard whether or not it is mentioned here.

IEC	IS	BS/other	Title
60076 P-1-2000 P-2-1993 P-3, 5-2000 P-6-1997	2026	171	Power Transformers
-	-	6056	Methods of measurement of transformer and Reactor sound levels
-	-	4360	Weldable structural steel
-	-	61	Threads for light gauge copper tube and fittings
-	-	3600	Steel pipes and tubes for pressure purpose
-	-	4504	Flanges for pipes, valves and fittings
529	13947	EN60529	Enclosures for electrical apparatus (App.-
214	-	4571	On load tap changers
60137(1995)	2099	223	Bushings for alternating voltages above 1000V
-	3347	-	Dimensions for porcelain transformer bushing for use in lightly polluted atmospheres
223	-	4963	Tests on hollow insulators
60354(1991)	6600	BSCP-0160	Loading guide for transformers
606	-	-	Application guide for power transformers
60296(Amd1-1986)	335	BS-14	Specification for unused mineral insulating oil for Transformers and reactors
34	325	-	Three phase Induction Motors
185	2705	-	Current Transformers
518	-	-	Dimensional standardization of terminals for HV Equipment
616	5578 (11353)	-	Terminal and tapping markings for Power Transformers
-	1886	-	Code of practice for installation and maintenance of Transformers

-	3639	-	Fittings and accessories for power transformers
-	3637	-	Gas operated relays
-	6272	-	Industrial cooling fans
-	4691	-	Degrees of protection provided by enclosures for rotating electrical machines
186	3156	-	Specification for voltage transformers
617	-	-	Graphical Symbols for drawings
-	2629	729	Galvanising
-	2633	-	Methods of testing uniformity for zinc coated articles
-	5	-	Colours for ready mixed paints and enamels
-	2147	-	Degrees of protection provided by enclosures for Low voltage switchgears and control gears
-	3401/1992	-	Silicagel
-	9434	-	Guide for sampling and analysis of dissolved gas in oil filled equipment.
-	12676	-	Oil impregnated paper insulated Bushing Dimension and requirements.
60071, P-1-1993	-	-	Insulation Co-ordination
P-2-1996	-	-	
-	375	-	Markings & Arrangements for switchgear Bus bars, Main connections and Auxiliary wiring
-	3638/1996	-	Application Guide for Gas operated Relays.
60214(1989)	8468	-	On-load Tap-changer.
-	8269	-	Methods for switching Impulse Test on High Voltage Insulators.
-	10028/1981	-	Installation of Transformers.
-	(Part-2)	-	
-	10028/1981	-	Maintenance of Transformers.
-	(Part-3)	-	
-	10561/1983	-	Application Guide of Power Transformers.
60542,	-	-	
Amd 1-1988	8468/1997	-	Application Guide for On-load Tap-changer.
-	8263	-	Method for Radio Interference Tests on High Voltage Insulators.
-	3202	-	Code of practice for climate proofing of Electrical Equipment.
-	6702/1972	-	Method for determination of Electric strength of Insulating Oils.
-	6103/1971	-	Method of Test for specific Resistance of Elect. Insulating Liquids.
-	6262/1971	-	Method of Test for power factor and Dielectric Constant of Electrical Insulating Liquids.
-	6104/1971	-	Method of Test for Interfacial Tension of oil against water by the Ring Method.
60034,	-	-	
P1-22(1972-2000)	-	-	Rotating Electrical Machines.
60044,	-	-	Instrument Transformers.
Amd P1-2000,	-	-	
P-6-1992	-	-	
60060,	-	-	High Voltage Test Techniques.
P-1-1989,	-	-	
Amd P-2-1996	-	-	
60085 (1994)	-	-	Thermal Evaluation and classification of Elect. Insulation.

60270 (1981)	-	-	Partial Discharge Measurements.
60404-8-7 (1998)	-	-	Specification for Individual Materials-Cold Rolled Grain oriented Electrical Steel sheet and strip delivered in fully processed state
60529 (Amd 1-1999)	-	-	Degree of protection, provided by enclosures (IP-Code)
60551(Amd 1-1995)	-	-	Determination of Transformer and Reactor Sound Levels.
60567(1992)	-	-	Guide for sampling Gases and oil from oil-filled Electrical equipment for the analysis of free and Dissolved Gases
60599(1999)	-	-	Mineral Oil-Impregnated Electrical Equipment in service-Guide to the Interpretation of Dissolved and Free Gases Analysis.
IS: 778			Gun metal gate,globe and check valves for general purpose
IS: 3401			Silicagel
60722 (1982)	-	-	Guide to the Lightning and Switching Impulse Testing of Power Transformers and Reactors.
60815 (1986)	-	-	Guide for selection of Insulators in respect of polluted conditions.
60947, P-1-7 (1984-2000)	-	-	Low voltage switchgear & control gear.
	-	IEEE C 57.93	IEEE Guides for Installation of Liquid Immersed 1995 Power Transformers.
-	-	IEEE Std 80	Guide for safety and AC Sub-station Grounding.
-	-	IEEE Std 979	Guide for Sub-station Fire protection.
-	-	IEEE Std 980	Guide for containment and control of oil spills in Sub-stations.
-	-	CBIP Pub.295/ 2006	Manual on Transformers.
-	-	NFPA	National Fire Protection Association.
-	-	NEMA-	-
-	-	Standard No.1.	-
-	-	Indian Electricity Rules-1956.	-

2.2 The standards, mentioned above are available from:

Standard:	Name and Address:
IS	Bureau of Indian Standards, Manak Bhawan, 9-Bahadur Sahah Zafar Marg, New Delhi - 110001, India.
IEC	International Electro Technical Commission, Bureau Central dela Commission, Electro Technique International, 1-Ruede Verembe, Geneva, SWITZERLAND.

2.3 Transformer meeting with requirements of other authoritative International Standards that ensure equal or better performance than the standards, mentioned above shall also be

considered. When the transformer, offered by the supplier conforms to other standards, salient points of difference between standards adopted and the standards, specified in this specification shall be clearly brought out in the offer. Two copies of such standards with authentic translation in English shall be furnished along-with the offer.

3 AUXILIARY POWER SUPPLY:-

Auxiliary electrical equipment shall be suitable for operation on the following supply system.

- | | | |
|-----|--|--|
| (a) | Power devices like drive motors of Rating 1KW and above. | 415V, 3Phase, 4 Wire, 50 Hz, neutral Grounded AC supply. |
| (b) | Lighting, space heaters and KW Motors. | 240V, single phase, 50Hz, neutral Grounded AC supply. |
| (c) | Alarm control and protective Devices. | 220V, DC, 2 Wire. |

Each of the foregoing supplies shall be made available by the purchaser at the terminal point for each transformer for operation of accessories and auxiliary equipment. Supplier's scope includes supply of interconnecting cables, terminal boxes etc. The above supply voltage may vary as below and all devices shall be suitable for continuous operation over entire range of voltages.

- | | | |
|------|--------------|--------------------------------------|
| (i) | AC Supply: - | Voltage \pm 10% Frequency \pm 5% |
| (ii) | DC Supply: - | - 15% to + 10% |

4.0 PRINCIPAL PARAMETERS:-

(A) For 40MVA,220/33KV Power Transformer

The transformer shall conform to the following specific parameters:-

Sl. No.	Item.	Specification.
1	Type of Power Transformer/Installation.	3 Phase Core type, 2 winding transformer, suitable for outdoor installation and suitable for bi-directional flow of power
2	Type of Mounting.	On wheels, mounted on rails.
3	Suitable for rated system frequency.	50 Hz (\pm 5%).
4	(a) Maximum system voltage ratio (HV/LV)	245 KV/36KV.
	(b) Nominal voltage Ratio (HV/LV)	220 KV/33 KV.
5	No. of Phases.	3 (Three)
6	No. of Windings.	Two winding Transformer
7	Type of Cooling.	ONAN/ONAF

NOTE: - ONAN- Oil Natural Air Natural.

ONAF - Oil Natural Air Forced.

8	MVA Rating corresponding to cooling system.	<u>40MVA</u>
	(a) ONAN cooling.	80% - 32 MVA
	(b) ONAF cooling.	100% - 40 MVA
9	Method of connection.	HV - Star LV - Star
10	Connection symbol.	YNyno

11	System Earthing.	Effectively solidly earthed (Neutral of both H.V. & L.V.)												
12	Percentage Impedances on normal tap and MVA base corresponding to HV/LV rating and applicable tolerances:	% Impedance with Tolerance 12.5+10% (Tol.) (No negative tolerance is allowed)												
NOTE:- No reactor either inside or outside the tank shall be used to achieve above % Imp. Value.														
13	Intended regular cyclic overloading of windings.	As per IEC76-1, Clause 4.2												
14	a) Anticipated unbalanced loading. b) Anticipated Continuous loading of windings (H.V and L.V)	< 10% 110% of rated current												
15	Tap changing gear: - (i) Type. (ii) Provided on. (iii) Tap range. (iv) Tap step. (v) Rated current (vi) Rated short circuit current (vii) Automatic control required? (viii) Remote control panel required? (ix) DC supply. (x) Supervisory control provision required? (xi) Marshalling kiosk required? (xii) No. of Transformers in parallel for which auto control to be suitable.	In Tank, Hi-speed Resistor Type On load. H.V. side - 15% to +5%. 1.25% of 220KV 350A(min.) 6KA(min.) Yes. Yes. As per Specification. Yes. Yes. 4 (Maximum).												
16	Over voltage operating capability and duration.	125% rated voltage for 60 seconds. 140% rated voltage for 5 seconds. 110% rated voltage continuous												
17	Minimum Air core reactance of HV windings.	20%												
18	Minimum knee point voltage (This will be determined during no load test method that 10% increase in voltage from 110% rated voltage causes the excitation current to increase not by more than 50%).	At 110% of rated voltage.												
19	Maximum Flux Density in any part of the core and yoke at rated MVA, Maximum System voltage [245 KV/36 KV] and minimum system frequency [48.5 HZ] [In Tesla].	1.6 Tesla												
20	Insulation levels:- For windings:- (a) 1.2/50 microsecond wave Shape Impulse Withstand (KVP). (b) Power frequency voltage withstand (KV-rms). (c) Separate source withstand voltage (KV-rms)	<table border="0"> <tr> <td></td> <td><u>HV</u></td> <td><u>LV</u></td> </tr> <tr> <td></td> <td>950</td> <td>170</td> </tr> <tr> <td></td> <td>395</td> <td>70</td> </tr> <tr> <td></td> <td>38</td> <td>70</td> </tr> </table>		<u>HV</u>	<u>LV</u>		950	170		395	70		38	70
	<u>HV</u>	<u>LV</u>												
	950	170												
	395	70												
	38	70												
21	Type of winding insulation:- (a) HV (b) LV winding.	Graded. Full.												

22	a) Withstand time for three phase short circuit at Terminals.	5 seconds.
	b) System short circuit level to which the transformer will be connected..	50KA(rms)-220KV 31.5KA(rms)-33KV
23	Maximum Partial discharge level	As per relevant up-to-date IEC 24
	Noise level at rated voltage and frequency.	As per latest NEMA Std.
25	Permissible Temperature Rise over ambient Temperature. (Both for ONAN & ONAF Ratings)	
	(i) Of top oil measured by thermometer & Optic Fiber Temperature Sensor	40° C (MAX.)
	(ii) Of winding measured by resistance Method	45° C (MAX.)
	(iii) Of winding hot spot temperature rise measured by Optic Fiber Temperature Sensors	54° C (MAX.)
	(iv) Reference ambient temperature	50° C [MAX.]
26	Minimum clearances in air (mm):-	Phase to phase. Phase to ground
	(a) HV	2350 2150
	(b) LV	400 320
	(c) HV to LV	2200 -
27.	Terminals.	
	(a) HV winding line end.	245 KV RIP/RIS condenser bushing (b)LV
	Winding & Neutrals	52KV RIP/RIS condenser bushing
28	Bushing current rating. (All bushing stud should 60mm and no threaded allowed)	1. 245 KV - 1250 Amp. 2. 52 KV - 1250 Amp. 3. 52KV(N) - 1250Amp.
29	Maximum Radio Interference Voltage level at 1 MHZ & 1.1 times max. Rms phase to ground voltage for HV winding.	500 micro volts
30	Minimum visual corona extinction voltage	As per ISS/IEC
31	(a) Number of cooler banks required per Transformer.	Minimum of two.
	(b) Rating of each bank as % of total loss.	Not greater than 50%
	(d) No. of Fans.	Adequate number of fans of 18"/24" sweep with one No. stand- by fan for Each bank.
32	Insulation level of bushing.	HV LV NEUTRAL
	(a) Lightning Impulse withstand (KVP)	1050 170 170
	(b) 1 Minute Power Frequency withstand Voltage (KV - rms).	460 70 70
	(c) Creepage distance (mm). (min.)	7595 1612 1612
33	Material of HV & LV Conductor.	Copper

34	Accommodation on tank for outdoor Neutral C.Ts.	There shall be provision on the main Tank of the Transformer for installation of Outdoor NCTs for both HV & LV and the required clearances for the same are to be maintained as per this Specification.
35	Neutral C.T.(To be provided by the bidder):	
	(i) Type.	Single phase,outdoor mounted
	(ii) Quantity.	Two(one in H.V side & one in L.V side)
	(iii) Voltage class.	36 KV.
	(iv) No. of cores.	One
	(v) Current ratio (A/A).	HV-200/1, LV-800/1
	(vi) Turn ratio.	Identical to turns ratio, provided on HV and LV side.
	(vii) Knee point voltage.	600 volts(min)
	(viii) Class of Accuracy.	P.S.
	(ix) Maximum secondary winding resistance	5 (Ohms). at 75°C
	(x) Location for mounting.	In neutral lead before connection Station earth
	(xi) Secondary current rating	One Amp.
	(xii) Maximum Excitation current at minimum	25mA

(NOTE: - HV - High Voltage, LV -Low Voltage.)

36.	a)Maximum current density for HV & LV windings for rated current.	2.4A/mm²
	b) Maximum Tan Delta for winding	<=0.005
	(Tan delta Value at max. ambient temperature)	
37	Type of oil preservation.	Air cell type
38	(i)Minimum Insulation resistance at an ambient temperature of 30 deg.C with 5KV Megger for 600 seconds duration.	HV /E & LV/E-3000 M-ohms HV /LV-4000 M-ohms
	(ii) Polarisation index i.e. ratio of Megger values at 600 sec. to 60 sec. for H.V. to Earth,L.V. to Earth and H.V to L.V	Shall be greater than or equal to '2.0, but less than or equal to '5'.
39.	Zero Sequence Impedance	Shall be 80% or more of the positive Sequence value
40.	Core Assembly	BOLTLESS TYPE
41.	No. of pressure relief devices to be provided	Adequate

5.0 GENERAL TECHNICAL REQUIREMENTS:-

5.1 Duty Requirements.

5.1.1 The transformer will be used for bi-directional flow of rated power.

5.1.2 The transformer and all its accessories like C.Ts. shall be designed to withstand without injury, the thermal and mechanical effects of a short circuit at the terminals of any winding with full voltage, maintained on all other windings for duration of five seconds. The bidder is to furnish the supporting calculation towards above along with the bid offer. The short circuit level of the H.V. system to which the subject Transformer will be connected is **50KA(rms,3-phase fault) for 220KV,40KA for 132KV and 31.5KA for 33KV** system.

- 5.1.3 The transformer shall be capable of being loaded in accordance with IS: 6600 upto loads of 150 %. There shall be no limitation imposed by bushings, tap changer etc.
- 5.1.4 The transformer shall be capable of being operated without danger on any tapping at the rated KVA with voltage variation of $\pm 10\%$ corresponding to the voltage of that tapping.
- 5.1.5 Radio interference and Noise level:
- (i) The transformers shall be designed with particular attention to suppression of maximum harmonic voltage, especially the third and fifth.
 - (ii) The noise level, when energized at normal voltage and frequency with fans running shall not exceed, when measured under standard conditions, the values, specified in NEMA, TR-1.
The transformer noise levels shall be measured as a routine test and in accordance with IEC-60551:1981.
- 5.1.6 Transformer shall be capable of operating under the natural cooled condition upto the specified load. The forced cooling equipment shall come into operation by preset contacts of winding temperature indicator and the transformer shall operate as a forced cooled unit, as ONAF. **Cooling shall be so designed that during total failure of power supply to cooling fans, the transformer shall be able to operate at full load for at least ten (10) minutes without exceeding hot spot temp. of 140 degree centigrade.** Also stopping of one or two cooling fans should not have any effect on the cooling system. Transformers fitted with two coolers each capable of dissipating 50 percent of the loss at continuous maximum rating.
- 5.1.7 Transformer shall be capable of withstanding thermal and mechanical stresses, caused by symmetrical or asymmetrical faults on any winding.
- 5.1.8 Transformer shall accept, without injurious heating, combined voltage and frequency fluctuation, which produces the following over fluxing condition:
- i) 125% for 1 minute. The base voltage and frequency refer to those mentioned in Clause 4.0 (3& 4).
 - 140% for 5 seconds.
 - ii) Over fluxing withstand characteristics upto 170% shall be submitted along with the bid.

5.2.0 **TRANSFORMER LOSSES:-**

The bidder shall indicate values of No load losses (iron losses), load losses (copper losses) and auxiliary losses in his bid, which shall be firm.

The maximum permissible losses (No load loss, auxiliary loss and load loss) at rated voltage/current (at 75 deg C) have been specified below.

<u>TABLE - A</u>	
<u>Maximum permissible loss</u>	<u>Value in KW</u>
Max. No-Load Loss at rated voltage and frequency	18.5
Max. Load Loss at rated current and at 75°C for HV and LV windings at principal tap position	129
Max. Auxiliary Loss at rated voltage and frequency	1.5

Following **penalties as specified in Table-B** shall be levied on the manufacturer/contractor (as the case may be) if losses measured during routine test are found to be **within +2% tolerance of the losses specified in Table-A** beyond which the transformer/reactor shall be liable for rejection. No benefit shall be given for supply of transformer/reactor, with losses (measured during routine tests) less than the losses specified above.

<u>TABLE -B</u>

Sl.No.	Differential of specified losses vs Measured losses	RATE (in INR per KW)
1	No load Loss	Rs. 10,00,000/KW
2	Load Losses	Rs. 8,00,000/kw
3	Auxiliary Losses	Rs. 8,00,000/KW
Note: For a fraction of a kW, the penalty shall be applied on pro rata basis.		

5.2.1 In case of failure of the transformer, the supplier shall take back the faulty transformer from its plinth for repair at their own cost (or replace the transformer with a new transformer) and deliver, at their own cost, unload at the destination sub-station transformer plinth within three months period from the date of intimation of defects to the satisfaction of the owner, at free of cost. If the delivery after repair/replacement will not be completed within three months, then the supplier shall pay penalty @ 0.5% of the contract price for each calendar week of delay from the end of three months period from the date of intimation of defects. Also, the Purchaser reserves the right for forfeiture of the total Composite Bank Guarantee and all the Securities, available with OPTCL, in case the Supplier fails to pay the penalty by one month before the expiry of the guarantee period. Also, this will be taken as adverse in all future tenders.

5.3 **CLEARANCE :**

The overall dimensions of the transformer shall allow for sufficient clearances for installation in a 245/145 KV switchyard with bay width of 18000/10500 mm and boom height of 15/11 m.

5.4 **CONSTRUCTIONAL DETAILS:**

The features and constructional details of Power transformer shall be in accordance with the requirements, stated hereunder:-

5.4.1 **TANK AND TANK ACCESSORIES:**

5.4.1.1 **TANK : -**

- (a) The transformer shall be enclosed in a suitably stiffened welded steel tank such that the transformer can be lifted and transported without permanent deformation or oil leakage. The construction shall employ weldable, low carbon, tested quality structural steel of an approved grade to BS: 4360. The transformer tank shall have rectangular shape. The minimum thickness of base and tank cover shall be 12mm. and that of sides is 8mm.
- (b) The tank of the transformer shall be complete with all accessories and shall be designed so as to allow complete transformer in the tank and filled with oil, to be lifted by crane or jacks, transported by road or rail without over-straining any joint and without causing subsequent leakage of oil.
- (c) All seams and those joints, not required to be opened at site shall be factory-welded and wherever possible they shall be double welded. After completion of tank construction and before painting, dye penetration test shall be carried out on welded parts of jacking bosses, lifting lugs and all load bearing members. Also radiographic tests shall be carried out on 5% of total weld length. The requirement of post-weld heat treatment for tank/stress relieving parts shall be based on recommendations of BS: 5500, Table 4.4.3.1.
- (d) All necessary precautions shall be taken to prevent ingress of moisture between flange plates, around gaskets and O-rings, at insulator/flange interfaces etc. due

- to high humidity.
- (e) Tank stiffeners shall be provided, if required, for general rigidity and these shall be designed to prevent retention of water.
 - (f) The transformer shall be preferably of bell type tank construction with the joint at about 500 mm. above the bottom of the tank. In case the joint is welded, it shall be provided with flanges, suitable for repeated welding. The joint shall be provided with a suitable gasket to prevent weld splatter inside the tank. Proper tank shielding shall be done to prevent excessive temperature rise of the joint.
 - (g) The main tank body excluding tap-changing compartments, radiators and coolers shall be capable of withstanding vacuums i.e. 100.64 KN/m² of gauge pressure, 760 mm of Hg.
 - (h) The tank shall be designed to withstand:-
 - (i) Mechanical shocks during transportation.
 - (ii) Vacuum filling of oil.
 - (iii) Continuous internal pressure of 35 KN/m² over normal hydrostatic pressure of oil.
 - (iv) Short circuit forces.
 - (i) Wherever possible, the transformer tank and its accessories shall be designed without pockets wherein gas may collect. Where pockets cannot be avoided, pipes shall be provided to vent the gas into the main expansion pipe. The vent pipes shall have minimum inside diameter of 15 mm except for short branch pipes, which may be 6 mm minimum inside diameter.
 - (j) All joints other than those, which may have to be broken, shall be welded, when required, they shall be double-welded. All bolted joints to the tank shall be fitted with suitable oil-tight gaskets, which shall give a satisfactory service under the operating conditions and guaranteed temperature-rise conditions. Special attention shall be given to the methods of making hot oil tight joints between the tank and the cover as also between the cover and the bushing and all other outlets to ensure that the joints can be remade satisfactorily at site and with ease with the help of semi-skilled labour. If gasket is compressible, metallic stops shall be provided to prevent over compression.
 - (k) Adequate space shall be provided at the bottom of the tank for collection of sediments.
 - (l) The base of each tank shall be so designed that it shall be possible to move the complete unit by skidding in any direction without injury when using plates or rails.
 - (m) Tank shields shall be such that no magnetic fields shall exist outside the tank. They shall be of magnetically permeable material. If required, impermeable shields shall be provided at the coil ends. Tank shield shall not resonate when excited at the natural frequency of the equipment. Bidder may confirm use of tank shields in the schedule of additional information.
 - (n) Suitable guides shall be provided in the tank for positioning the core and coil assembly.
 - (o) The tank shall be designed such that it can be mounted on the plinth directly.
 - (p) When the transformers are provided with separately mounted radiators, flexible joints shall be provided in the main oil pipes, connecting the transformer tank to the radiator banks to reduce vibration and facilitate erection and dismantling.
 - (q) The transformer tank, fittings, radiators and all accessories shall be designed to withstand seismic acceleration, as specified.
 - (r) All connections, bolted to the tank shall be fitted with suitable gas oil resistant gaskets, made of such a material that no serious deterioration occurs under service conditions. Gaskets of nitrile rubber or equivalent shall be used to ensure perfect oil tightness. All gaskets shall be of closed design (without open ends) and shall be of one piece only. Rubber gaskets, used for flange connections of the various oil compartments shall be laid in grooves or in groove-equivalent retainers on both sides

of the gaskets throughout their total length. Care shall be taken to secure uniformly distributed mechanical pressure over the gaskets and retainers throughout the total length. Gaskets of neoprene and/or any kind of impregnated/ bonded cork or cork only which can easily be damaged by over-pressing are not acceptable. Use of hemp as gasket material is also not acceptable.

5.4.1.2 **LIFTING AND HAULAGE FACILITIES :-**

The transformer tank shall be provided with: -

- (a) Lifting lugs, suitable for the weight of the transformer, including core and windings, fittings and with the tank, filled with oil.
- (b) At least four jacking lugs and where required, with lugs suitably positioned for transport on a beam transporter.
- (c) Haulage lugs to enable a steel rope to be used safely for haulage in any direction.
- (d) The transformer must be provided with clearly marked locations for the fixing of jacks.

The free space between the bottom of the tank and the fixing for jacks must be must be 300 - 350 mm.

5.4.1.3 **FOUNDATIONS, CABLE DUCTING ETC.:**

The Supplier will have to liaise with the Purchaser or its authorised contractor immediately after Design approval to finalize the detailed design of the following:-

- Transformer main tank foundations.
- Cooler bank foundations.
- Marshalling kiosk/control cabinet location and foundation.
- Cable ducting requirements.
- Adequate bunding design for the complete containment of all oil spills.
- Any other civil/electrical requirements for the installation of the transformer.

5.4.1.4 **TANK COVER:**

- (a) The tank cover shall be of adequate strength, shall not distort when lifted and shall be provided with suitable flanges having sufficient and properly spaced bolts. At least two adequately sized inspection openings, one at each end of the tank shall be provided for easy access to the internal connections of bushings, winding connections and earthing links. The inspection covers shall not weigh more than 25 Kg. The inspection cover shall be provided with lifting handles.
- (b) The tank and cover shall be designed in such a manner so as to leave no external pockets in which water can lodge, no internal pockets in which oil can remain when draining the tank or in which air can be trapped when filling the tank, and to provide easy access to all external surfaces for painting. The design of the tank cover should not present a safety hazard to personnel working on top of the unit.
- (c) It must be possible to remove any bushing without removing the tank cover.
- (d) One pocket shall be provided for stem type thermometer in addition to those for the bulbs of the oil temperature and winding temperature indicators. These pockets shall be located in the position of the maximum oil temperature and it must be possible to remove any bulb without lowering the oil level in the tank. Captive screwed caps shall be provided to prevent the ingress of water to the thermometer pockets when they are not in use.
- (e) Bushings, turrets, covers of inspection opening, thermometer pockets etc. shall be designed to prevent ingress of water into or leakage of oil from the tank.
- (f) All bolted connections shall be fitted with weather proof, hot oil resistant gasket in between for complete oil tightness. If gasket is compressible, metallic stops shall be provided to prevent over-compression.
- (g) The top part of the tank cover shall be sloped to prevent retention of rain water and shall not distort when lifted.
- (h) The tank cover and all covers for mounting, cleaning, man-holes, hand holes and inspection openings on tank etc. shall be earthed by suitable grounding conductors of the flexible type, having a cross-section of minimum 95 mm². Appropriate earthing studs with bolts and washers, made of stainless steel shall be provided.

5.4.1.5 **AXLES AND WHEELS:**

- (a) The transformer shall be designed with flanged bi-directional wheels and axles of a suitable size to carry the full weight of the transformer, oil and accessories. These shall be so designed as not to deflect excessively to interfere with the movement of the transformer. Wheels, axles and bearings shall be fully corrosion - resistant and complete with fittings to facilitate lubrication.
- (b) Suitable locking arrangement along with foundation bolts shall be provided for the wheels to prevent accidental movement of the transformer.
- (c) The wheels are required to swivel and they shall be arranged so that they can be turned through an angle of 90 degrees when the tank is jacked up to clear of rails. Means shall be provided for locking the swivel movements in positions parallel to and at right angles to the longitudinal axis of the tank.
- (d) The rail track gauge shall be 5'6" (1676 mm) along longer axis as well as along shorter axis.
- (e) Foundation layout details will be furnished by the supplier during detailed Engineering.

5.4.1.6. **ANTI-EARTHQUAKE CLAMPING DEVICE :**

To prevent transformer movement during earthquake, clamping device shall be provided for fixing the transformer to the foundation. The Bidder shall supply necessary bolts for embedding in the concrete foundation. The arrangements shall be such that the transformer can be fixed to or unfastened from these bolts, as desired. The fixing of the transformer to the foundation shall be designed to withstand seismic events to the extent that a static coefficient of 0.3 g. applied in the direction of least resistance to that loading, will not cause the transformer or clamping devices as well as bolts to be overstressed. Special steps must be taken to prevent mal-operation of Buchholz relay in such conditions.

The details of the device used and its adequacy, suitability and design calculations to withstand seismic load shall be brought out in the additional information schedule.

5.4.1.7 **CONSERVATOR VESSELS, OIL GAUGES AND BREATHERS:**

- (a) A conservator, complete with sump and drain valve shall be provided in such a position, so as not to obstruct the electrical connections to the transformer having a capacity between highest and lowest visible levels of 7½% of the total cold oil volume in the Transformer and the cooling equipment from minimum ambient temperature to 100 Degree C. The minimum indicated oil level shall be with the feed pipe from the main tank covered with not less than 15 mm depth of oil and the indicated range of oil level shall be minimum to maximum.
- (b) If the sump is formed by extending the feeding pipe inside the conservator vessel, this extension shall be for at least 25 mm. The conservator shall be designed so that it can be completely drained by means of the drain valve provided, when mounted as in service.
- (c) The conservator tank shall be bolted on to its support of mounting to allow for its removal for cleaning/repair. It shall be bolted onto the main tank to allow for its removal for cleaning/repair.
- (d) The conservator for main tank shall be fitted with a magnetic oil level gauge with low oil level, electrically insulated alarm contacts. The indicator shall have the minimum and maximum levels, indicated along with the normal level at an oil temperature of 30° C. The temperature markings shall preferably be integral with the level-indicating device. The gauge should be readable from the transformer base level. Sight glasses of oil level indicators shall be of laminated security glass. Sight glasses of transparent plastics will not be accepted.
- (e) Taps or valves shall not be fitted to oil gauge.
- (f) The oil connection from the transformer tank to the conservator vessel shall be arranged at a rising angle of 3 to 9 degrees to the horizontal upto the Buchholz Relay and shall consist of 80 mm inside diameter pipes as per IS: 3639.
- (g) A valve shall be provided at the conservator to cut off the oil supply to the

transformer, after providing a straight run of pipe for at least a length of five times the internal diameter of the pipe on the tank side of the gas and oil-actuated relay and at least three times the internal diameter of the pipe on the conservator side of the gas and oil-actuated relay.

- (h) The conservator tank shall be equipped with a nitrile rubber diaphragm or bag filled with dry air, which isolates the transformer oil space from the ambient air. The bag shall work satisfactorily and without damage at all anticipated oil temperatures.
- (i) Provision shall be made for monitoring the integrity of rubber bag and giving an electrical alarm when the bag is damaged.
- (j) The space inside the bag is to be connected to ambient air through a removable silica-gel type breather with oil trap and dust filter and mounted about 1400 mm above ground. No valve is to be placed between this breather and the conservator. The moisture absorption, indicated by change in colour of the tinted crystals inside the breather can be easily observed from distance. Minimum quantity of silica gel will be 1 Kg. for every 3500 ltrs. of oil in the tank. The containers for the dehydrating agent shall be of transparent plastics. The quality of plastic material shall be got approved from the purchaser.
- (k) The conservator for the OLTC/diverter switch can be either an integral, but completely separated part of the main conservator or a separate oil tank. It shall have a prismatic or magnetic oil level gauge.

5.4.2 VALVES AND LOCATION: -

5.4.2.1 General: -

- (a) Blank flanges, plates or captive screw caps shall be fitted to all valves and pipe ends, not normally connected in service.
- (b) The omission of any, or the provision of alternative arrangements to the listed requirements, which alter the functional nature of the valve system, will not be accepted.
- (c) All valves upto and including 100 mm shall be of gun metal.. Larger valves may be of gun metal or may have cast iron bodies with gun metal fittings. They shall be of the full way type with internal screw and shall be opened by turning counter clockwise when facing the hand wheel.
- (d) Means shall be provided for padlocking the valves in the open and closed positions. Provision is not required for locking individual radiator valves.
- (e) Every valve shall be provided with an indicator to show clearly the position of the valve.
- (f) All valves shall be provided with flanges having machined faces.
- (g) All valves shall be suitable for continuous operation with transformer oil at 100° C.
- (h) Suitable valves shall be provided to take sample of oil from OLTC chamber during Operation of the transformer.
- (i) Oil sampling valves shall have provision to fix rubber hose of 10 mm size to facilitate oil sampling.
- (j) Each transformer shall be fitted with the valves, identified in the following Sub-sections as a minimum requirement.

5.4.2.2 MAIN TANK:-

- (a) One 50 mm (NW 50) bore filter valve located near to the top of the tank.
- (b) One 50 mm (NW 50) bore filter valve located near to the bottom of the tank and diagonally opposite to the filter valve required against (a). Where design permits, this valve may be combined with item (c).
- (c) One 50 mm (NW 50) drain valve with such arrangements as may be necessary inside the tank to ensure that the tank can be completely drained of oil as far as practicable. This valve shall also be provided with an approved oil sampling device.
- (d) Two 25 mm (NW 25) oil valves for taking oil samples from the top and bottom of the tank. The top-oil sampling point shall be brought down to be accessible from

- ground level.
- (e) A flanged 50 mm (NW 50) valve suitably positioned near the top of the main tank for the connection by the Purchaser of a 'Hydran' monitor.
 - (f) A 100 mm (NW 100) flange for the vacuum control switch tank will be provided on the tank cover.

5.4.2.3 **CONSERVATOR:-**

- (a) One valve between the conservator and gas actuated relay for the main tank and, where appropriate, for the tap change diverter switch tank.
- (b) One drain valve for oil conservator tank so arranged that the tank can be completely drained of all oil. It shall also be fitted with an oil-filling hole with cap.

5.4.2.4 **TAP CHANGER/DIVERTER SWITCH :**

50 mm filter and 50 mm (NW 50) drain valve where selector switches are contained in a separate tank.

5.4.2.5 **RADIATORS AND COOLER BANKS:-**

Valves of adequate size as per 'CBIP Manual on Transformers (Publication No. 275)' at each point of connection to the tank shall be provided.

5.4.2.6 Air release plug(s) of adequate size shall be provided.

5.4.3 **JOINTS AND GASKETS:-**

- (a) All joint faces shall be arranged to prevent the ingress of water or leakage of oil with a minimum of gasket surface exposed to the action of oil or air.
- (b) Nitrile base cork or equivalent shall be used for gaskets. Oil resistant synthetic rubber gaskets are not permissible except where the synthetic rubber is used as a bonding medium for cork or similar material or where metal inserts are provided to limit compression.
- (c) Gaskets shall be consistent with the provision of a good seal and full details of all gaskets sealing arrangement shall be shown on the drawings.

5.4.4 **PRESSURE RELIEF DEVICE:-**

- (a) Adequate No. of pressure relief device(s) of sufficient size shall be provided for rapid release of any pressure that may be generated within the tank and which might result in damage to the equipment. It shall positively operate, at a pressure of 7+/- 1PSi (48+/- 6.8KN/Sq.mm) and automatically reset when pressure falls below this value. There will be no leakage of oil after resetting of PRD. Means shall be provided to prevent the ingress of rain or dust. Pressure relief devices of the type mounted below normal oil level shall be of the resetting type once the dangerous pressure has been reduced to prevent unnecessary release of oil.
- (b) Contacts shall be provided for alarm and trip and initiation on operation of the device. Baffles shall be provided when necessary to safely control the direction in which oil or gas is ejected.
- (c) Unless otherwise approved, the pressure relief device(s) shall be mounted on the main tank and if on the cover, shall be fitted with a skirt projecting 25 mm. inside the tank to prevent gas accumulation.
- (d) One of the following methods shall be used for relieving or equalising the pressures in the pressure relief device.
 - (i) An equaliser pipe connecting the pressure relief device to the conservator or
 - (ii) The fitting of silicagel breather to the pressure relief device, the breather being mounted in suitable position for access at ground level.
- (e) Loss of oil on operation of the relief device shall be contained within the transformer oil retaining area.
- (f) The bidders shall furnish constructional, design details of pressure relief device(s) and calculations along with the bids to prove that the size and setting of pressure relief device(s) is adequate, considering the rating of the transformer, the quantity of oil in the Transformer

and the insulating oil will not catch fire in case of any short/ground fault inside the transformer,.

5.4.5 **EARTHING TERMINALS:**

Two substantial steel flag type terminals (each having two tapped holes with M10 bolts, plain and spring washers), capable of carrying for 5 seconds the full lower voltage short circuit current of the transformer and suitable for connection to 50 x 8 mm. Galvanised steel flat shall be located one on either side and near to the bottom of the transformer to facilitate connection to the local earthing system. The supplier shall provide earthing strips up to the ground level. Also each radiator, marshalling Kiosk, OLTC etc. shall be suitably earthed to the transformer tank or else have earthing terminals as appropriate.

5.4.6 **CORROSION PROTECTION:**

5.4.6.1 General:

- (a) Bidders shall state clearly the corrosion protection, applied to aluminum and aluminum-alloy parts.
- (b) Bidders shall draw attention to all exposed points in their equipment at which aluminum or aluminum- alloy parts are in contact with or in close proximity to other metals and shall state clearly the protection employed at each point to exclude air and moisture.
- (c) A full description of the corrosion prevention system, proposed by the Bidder shall be given and this is subject to acceptance by the purchaser. This description shall include details of surface preparation, rust inhibition, and paint thickness, treatment of fasteners and painting of surfaces in contact with oil.

5.4.6.2 The minimum standards acceptable to the purchaser are:-

- (a) **Hot Rolled Steel:**
 - (i) Grit blasting to grade sa 2.5 of ISO 8501-1.
 - (ii) Epoxy-base zinc primer. Coating thickness 25 micrometer.
 - (iii) Zinc spraying of tank bottom. Thickness 100 micrometer.
 - (iv) Epoxy-based micaceous iron-oxide paint. Coating thickness 40 micrometer.
 - (v) Alkyd or phenolic-based micaceous iron-oxide paint. Coating thickness-40 micrometer.
- (b) **Radiators and Fasteners larger than 12 mm:-**
 - (i) Hot dip galvanized to IS: 2633.
 - (ii) Cleaning and surface preparation followed by paint treatment as specified above.
- (c) **Smaller fasteners, cable clips:-**
Use of non-ferrous material, stainless steel or appropriate plated components.

5.4.7 **RATING, DIAGRAM AND VALVE PLATES:-**

The following plates or an approved combined plate shall be fixed to each transformer Tank at an average height of 1500 mm above the ground level:-

- (a) A rating plate bearing the data, specified in IEC 76 Part - I. This plate shall also include: -
 - (i) The short circuit current rating.
 - (ii) Time factor for each winding measured.
 - (iii) Measured no load current and no load losses at rated voltage and rated frequency.
 - (iv) Measured load losses at 75° C (Normal tap only).
 - (v) D.C. resistance of each winding at 75° C.
- (b) A diagram plate showing in an approved manner, the internal connections and the voltage vector relationship of the several windings, in accordance with IEC 76 Part-I with the transformer voltage ratio for each tap and, in addition, a plan view of the transformer giving the correct physical relationship of the terminals.
- (c) A plate showing the location and function of all valves and air-release cocks or plugs. This plate shall also if necessary warn operators to refer to the Maintenance Instructions before applying vacuum.

- (d) Current transformers Rating Plate.
- (e) Diagram plate, indicating the oil levels in the conservators dependent on the oil temperature.
- (f) Loading plan plate, showing transport dimensions and masses. This plate shall also warn the erection staff not to remove any cover, before filling the tank with oil to such a level where the windings are not exposed to the atmosphere. This shall be fixed directly on to the transformer tank and shall not be removed for transport.
- (g) Identification plates, alpha-numerical number in an approved manner, for all fans, marshalling cabinets, breathers, valves, cocks, accessories etc. (minimum size: 110mm x 50mm) rigidly fastened by rivets on corrosion proof base plates. In addition, the function (description) of the related devices shall be clearly indicated on these plates. The alphanumeric numbers on the identification plates shall be of such a size as to be clearly legible from the floor level.
- (h) Plates, showing all control, measuring and monitoring circuits and terminal blocks. These plates shall be rigidly fixed at the inner side of the hinged door of the concerned marshalling kiosk.
- (i) Plates, showing the control circuit/ block diagram of the OLTC. These plates shall be rigidly fixed at the inner side of the hinged door of the motor drive cubicle.

Out door arranged plates are to be of polished stainless steel of top quality only (back ground clear, engraving black, depth of engraving 0.5mm) stainless steel, capable of withstanding the rigours of continuous outdoor service at site. Plates, arranged inside control and marshalling cubicles may be of material in accordance with manufacturer's standard, e.g. glass -fibre reinforced synthetic resin (subject for approval). All plates other than those located on tank cover shall be easily and clearly legible from ground level.

5.4.8. **CORE:**

- (a) The core shall be constructed from high grade non-ageing cold rolled super grain oriented silicon steel laminations, known as HIB steel as trade name having high permeability and low hysteresis loss. B-H and specific loss curve shall be furnished in support of these materials. Laminations of one particular thickness i.e. 0.23mm. or better (quoted grade and type) shall be used. Laminations of different grade(s) and different thickness(s) are not allowed to be used in any manner or under any circumstance.
- (b) After being sheared, the lamination shall be treated to remove all burrs and shall be reannealed to remove all residual stress. The insulation of the lamination, which is to be stated in the tender, shall be inert to the action of the hot transformer oil and pressure.
- (c) The design of the magnetic circuit shall be such as to achieve minimum possible active and reactive core losses during the entire life of the transformer.
- (d) The design of the magnetic circuit shall be such as to avoid static discharges, development of short circuit paths within itself or to the earthed clamping structure and production of flux component at right angles to the plane of laminations, which may cause local heating. The joints of limbs and yokes shall be designed and constructed to keep the no-load losses and the hot spot temperature in the magnetic core as well as the noise level as low as possible.
- (e) The core and winding shall be capable of withstanding the shock during transport, installation, service and adequate provision shall be made to prevent movement of core and winding relative to tank during these conditions and reduce vibrations to a minimum for all operating conditions. Care shall also be taken to secure uniformly distributed mechanical pressure over all the laminations to prevent setting of the core and to limit noise and vibration to a minimum under service conditions.

- (f) The Transformer shall be of **BOLTLESS** core design. The Bidders shall furnish the following documentary evidence towards their experience and performance in such type of design.
- 1) Purchase order
 - 2) Approved drawings & GTP
 - 3) Any other documents related to boltless core design.
- (g) All steel sections, used for supporting the core shall be thoroughly sandblasted after cutting, drilling and welding. Any non-magnetic or high resistance alloy shall be of established quality.
- (h) When bell type construction is offered, suitable projecting guides shall be provided on core assembly to facilitate removal of tank. The supporting framework of core shall be so designed so as to avoid presence of pockets, which would prevent complete emptying of the tank through drain valve or cause trapping of air during oil filling.
- (i) The core shall be provided with lugs suitable for lifting the complete core and coil assembly of the transformer.
- (j) The core and coil shall be so fixed in the tank that shifting will not occur when the Transformer is moved or during a short circuit.
- (k) Oil ducts shall be provided where necessary to ensure adequate cooling. The winding structure and major insulation shall not obstruct the free flow of oil through such ducts. Where the magnetic circuit is divided into pockets by cooling ducts parallel to the planes of laminations or by insulating material above 0.25 mm thick, tinned copper strip bridging pieces shall be inserted to maintain electrical continuity between pockets.
- (l) The temperature gradient between the core and surrounding oil shall be maintained less than 20°C. The manufacturer shall demonstrate this either through a test (procedure to be mutually agreed) OR by a calculation.
- (m) The transformer shall be designed in such a way that the maximum flux density in any part of the core and yoke at rated M.V.A, minimum frequency and highest system voltage shall not exceed 1.6 Tesla. The Tenderer shall establish this by calculation as per given format.
- (n) **Minimum knee point voltage is 110% of rated voltage. Accordingly, the operating flux density for design should be carefully chosen within the stipulated value to achieve the above minimum knee point voltage. The tenderer shall quote the practical achievable no load current at different percentages of rated voltage as per Guaranteed Technical Particulars along with a linear graph confirming the above said knee point voltage which will be verified during no load test method that 10% increase in voltage from 110% rated voltage causes the excitation current to increase not by more than 50%.**
- (o) The tenderer will offer the core for inspection and approval by the Purchaser during manufacturing stage. Tenderer's notice for this purpose shall be accompanied with the following documents towards use of prime core.
- (i) Invoice of the supplier.
 - (ii) Mill's test certificates.
 - (iii) Packing list.
 - (iv) Bill of lading.
 - (v) Bill of entry certificates by customs.
- (p) Core material shall be directly procured either from the manufacturer or through their accredited marketing organizations of repute and not through any agent. **All the core import documents must be in the name of the transformer manufacturer.**
- (q) The bidder should preferably have in-house core-cutting facility for proper monitoring and control on quality and also to avoid any possibility of mixing of prime material with defective/ second grade material. However, the core-cutting operation may be witnessed by OPTCL's representatives) at the works of the manufacturer and specific loss, other tests will be conducted on samples of core materials, selected at random by OPTCL's representative.

The following procedure is to be adopted for those manufacturers who have no in-house core-cutting facility:

- (1) In the offer, against tender for transformers, the bidder should mention names of at least three manufacturers of Transformer core material who have at least 5 (five) years experience in manufacturing of Transformer grade core. The Transformer manufacturer (TM) can purchase the core from such manufacturer(s) for which approval will be accorded by OPTCL.
- (2) The bidder should specify the grade, thickness of core material in the offer along with submission of all graphs/ documents, relating to the grade of core material, offered by them.
- (3) The documents, as mentioned against Sl. '0' should be submitted to OPTCL, once the core materials are landed in any of the Indian ports and same should be offered to OPTCL for inspection. The representative, deputed by OPTCL for such inspection will record the following informations:-
 - a) Purchase order No. & Date.
 - b) No. of packed coils with package Nos.
 - c) Gross weight.
 - d) Net weight
 - e) Port of loading.
 - f) Port of discharge.
 - g) Name of the ocean vessel.
 - h) Grade and thickness of core material.
 - i) Any other information, as mentioned on the body of packed coils.
- (4) The bidder in its offer will mention the names of at least three Sub-vendors, to whom they intend to assign their core cutting. Such sub-vendors should have been approved by other Electricity Boards/ Electrical utilities and are accredited by some International recognised certification body like ISO: 9000 etc., to ensure that a minimum quality parameters and tolerances are maintained. The experience, the details of core-cutting facilities, finishing and testing facilities etc., as available with such sub-vendors should be clearly outlined in the bid.
- (5) On award of contract, the TM is to assign the core-cutting to such sub-vendor(s) for which approval is to be given by OPTCL
- (6) After the packed core coils are received by the OPTCL's approved sub-vendors, the TM is to offer the same to OPTCL for deputing representative(s) to first note down the details as per SL (3) above and witness the cutting of cores and relevant tests on core samples.
- (7) The TM will offer the core materials for inspection during assembly stage and witnessing the stage inspection and relevant tests.
- (8) Tenderer shall furnish along with the bid the calculation towards Air-core reactance of H.V. winding and maximum peak value of magnetising in- rush current and shall justify that the transformer will not trip due to this during initial charging and subsequent chargings.
- (9) **Tenderer shall furnish along with the bid the calculation towards Air-core reactance of H.V. winding and maximum peak value of magnetising in- rush current and shall justify that the transformer will not trip due to this during initial charging and subsequent chargings.**

5.4.8.1 **EARTHING OF CORE CLAMPING STRUCTURE:**

The top main core clamping structure shall be connected to the tank body by a copper strip. The bottom clamping structure shall be earthed by one or more of the following methods: -

- (a) By connection through vertical tie-rods to the top structure.
- (b) By direct-metal-to metal contact with the tank base maintained by the weight of the

core and windings.

- (c) By a connection to the top structure on the same side of the core as the main earth connection to the tank.

5.4.8.2. **EARTHING OF MAGNETIC CIRCUITS:**

- (a) The magnetic circuit shall be earthed to clamping structure at one point only through a removable link, placed in an accessible position just beneath an inspection opening in the tank cover and which, by disconnection, will enable the insulation between the core and clamping plates etc. to be tested at voltages upto 2.0KV(rms). The removable link shall have adequate section to carry ground fault current.
- (b) When magnetic circuits are subdivided into separate isolated sections by ducts perpendiculars to the plane laminations, all such sections shall be earthed.

5.4.8.3 **SIZE OF EARTHING CONNECTIONS:-**

To be proposed by the manufacturer for the Purchaser's approval.

5.4.9. **WINDINGS:**

- (a) The supplier shall ensure that the windings of all EHV class transformers are made in dust proof, conditioned atmosphere. **He shall furnish the facilities, available in this regard at his works along with the bid.**
- (b) The windings for system rated voltages of 220 KV and 132 KV shall have graded insulation, as defined in IEC-76 and IS-2026. The winding for 33 KV shall be fully insulated.
- (c) All neutral points shall be insulated to withstand the applied test voltage as per above standards.
- (d) The neutral ends of star connected three phase windings shall be connected at points, which are accessible from manholes in the cover and brought out via one bushing.
- (e) The conductors for the windings and connecting leads shall be of electrolytic grade copper, free from scales and burrs and shall have properly rounded corners to reduce electrostatic flux concentration.
- (f) The current density, adopted for all the windings shall not exceed 2.4 Ampere/sq.mm. The total net cross-sectional area of the strip conductors for calculating the current density for each winding shall be obtained after deducting the copper area, lost due to rounding up of the sharp edges of the rectangular conductors.
- (g) The copper conductors, used in the coil structure shall be best suitable to the requirements and all permanent current carrying joints of the windings and the leads shall be welded or braced.
- (h) The coils shall be supported between adjacent sections by insulating spacers and the barriers, bracings and other insulation, which shall be arranged to ensure a free circulation of the oil and to reduce hot spots in the windings. The stacks of windings shall receive adequate shrinkage treatment before final assembly. Adjustable devices shall be provided for taking up any possible shrinkage of coils in services.
- (i) The transformer shall be designed to withstand impulse and power frequency test voltages as specified in IEC 76 and IS: 2026.
- (j) The windings shall be capable of withstanding axial and radial forces during fault conditions as per clause No.5.1.2. of this specification. **The detailed calculation towards the above should be furnished along with the bid.**
- (k) The short circuit temperature rise should not exceed the limits, fixed as per IS:2026. **The calculation towards the above for 220 KV and 33 KV windings shall be furnished along with the bid.**
- (l) The insulation of transformer windings and connections shall be free from insulating compounds which are liable to soften, ooze out, shrink or collapse or be catalytic and chemically active in the hot transformer oil during service. The dielectric strength of winding insulation shall conform to the values, given in IS: 2026, as amended up to date.
- (m) The coil clamping arrangement and the finished dimensions of any oil duct shall be such as will not impede the free circulation of oil through the ducts.
- (n) No strip conductor wound on edge shall have a width exceeding six times its

- thickness.
- (o) The conductors shall be transposed at sufficient intervals in order to minimize eddy currents and equalize the distribution of currents and temperatures along the windings.
 - (p) The windings and leads of all transformers shall be able to withstand the shocks, which may occur through rough handling and vibration during transport, switching and other transient service conditions including external short circuit. Adequate barriers shall be provided between windings and core and between windings. All leads or bars from the windings to the terminal boxes and bushings shall be rigidly supported. Stresses on coils and connections must be avoided.
 - (q) The windings shall be located in a manner, which will ensure that they remain electromagnetically balanced and their magnetic centres remain co-incident under all conditions of operations.
 - (r) Tappings shall be so arranged as to preserve the magnetic balance of the transformer at all voltage ratios.
 - (s) The coils should be made up, shaped and braced to provide for expansion and contraction due to temperature changes.
 - (t) Coil clamping rings, if provided, shall be of steel or of suitable insulating material.
 - (u) All threaded connections shall be provided with locking facilities. All leads from the winding to the terminal board and bushing shall be rigidly supported to prevent injury from vibration. Guide tubes shall be used, where practicable.
 - (v) The assembled core and windings shall be vacuum dried and suitably impregnated before removal from the treating tank.
 - (w) Where coil-clamping rings are of metal at earth potential, each ring shall be connected to the adjacent core clamping structure on the same side of the transformer as the main earth connection. However, same shall be proposed by the manufacturer for the Purchaser's approval.
 - (x) Washers in contact with non-ferrous parts, which carry current, shall be of phosphorous bronze.
 - (y) The tenderer should have in house availability of vapour phase Drying (VPD) plant for proper drying of the insulation. In case VPD facility is not available, the bidder will prove that the method of drying adopted by them is equivalent or better than VPD in terms of level of dryness and other benefits of VPD.
 - (z) The air-core reactance of HV winding of Transformer shall not be less than 20%.
 - (aa) The transformer shall be designed to withstand a DC current of 30A per phase without injurious heating.
 - (bb) **Tan delta value for windings shall not be more than 0.005. (At max. ambient Temp.)**
 - (cc) The arrangement of the core and windings shall be in the following manner:-

CORE-LV-HV-REGULATING

5.4.10. GAS AND OIL-ACTUATED RELAYS:-

- (a) Each transformer shall be fitted with gas and oil-actuated relay equipment having alarm contacts, which close on collection of gas or low oil level, and tripping contacts which close following oil surge conditions. Separate relays shall be provided for on load tap changer.
- (b) Each gas and oil-actuated relay shall be provided with a test cock to take a flexible pipe connection for checking the operation of the relay.
- (c) Each relay shall be fitted with a calibrated glass window for indication of gas volume.
- (d) To allow gas to be collected at ground level, a small bore pipe shall be connected to the gas release cock of the gas and oil-actuated relay and brought down to a point, approximately 1400 mm above ground level,. Where it shall be terminated by a cock, which shall have provision for locking to prevent unauthorized operation.

- (e) The design of the relay mounting arrangements, the associated pipe work and the cooling plant shall be such that mal-operation of the relay will not take place under normal service conditions.
- (f) The pipe work shall be so arranged that all gas arising from the transformer will pass into the gas and oil-actuated relay. The oil circuit through the relay must not form a delivery path in parallel with any circulating oil pipe, nor is to be tied into or connected through the pressure relief vent. Sharp bends in the pipe work shall be avoided. For this reason, bushing turrets, if fitted shall have vent pipes, which will route any gas collection through the relay.
- (g) A machined surface shall be provided on the top of each relay to facilitate the setting of the relays and to check the mounting angle in the expansion pipe and the cross level of the relay.
- (h) A straight run of pipe work shall be provided for a length of five times the internal diameter of the pipe on the conservator side of the gas and oil-actuated relay.
- (i) The surge float contacts shall close at a rate of steady oil flow between the following limits. As far as possible, the limits shall also be met when the relay is subjected to oil surge conditions, produced by rapid opening of a lever operated gate valve.
- (j) The relays shall be so located as to be easily accessible from the top of the tank.
Oil Pipe Connection I.D. (mm) Operational Limits for Relay.

	[Rising angles of 1° to 9°.]
25	700-1300
50	750 - 1400
75	900 - 1600
- (k) The gas collection contacts shall operate within the angle limits, specified for test:
- (l) When a transformer is provided with two conservators, the gas and oil - actuated relays shall be arranged as follows:
 - (i) If the two conservators are connected to the transformer by a common oil pipe, one relay shall be installed in the common pipe.
 - (ii) If the two conservators are piped separately to the transformer, two relays shall be installed, one in each pipe connection.
- (m) The clearance between oil pipe work and live metal shall be not less than the minimum clearances as per standard practice.

5.4.11. **TEMPERATURE INDICATING DEVICES AND ALARMS:**

The Transformer shall be provided with approved devices for indicating the oil temperature and hot spot winding temperature of each winding. The devices shall have a dial type indicator and in addition, a pointer to register the highest temperature reached and re-setting device. Each temperature device shall have three separate contacts fitted, one of which shall be used to control the cooling plant motors, one to give an alarm and one to trip the associated circuit breakers.

- (a) **Oil Temperature Indicator (OTI)**
The thermometer for top oil temperature indication should be of 150mm. dial type with angular sweep of 270° Range of temperature should be 0-150°C with accuracy of ±1.5% (or better) of full scale deflection.. A temperature-sensing element, suitably located in a pocket on top oil shall be furnished. This shall be connected to the OTI by means of capillary tubing. Accuracy class of OTI shall be ± 1.5% or better. The temperature indicator dials shall have linear graduations to clearly read at least every 2 deg. C.
- (b) **Winding Temperature Indicator (WTI)**
A device for measuring the hot spot temperature of each of the HV/IV/LV windings shall be provided. It shall comprise of the following:-

- i) Temperature sensing element.
- ii) Image Coil.
- iii) Auxiliary CTS, if required to match the image coil, shall be provided and mounted in the cooler control cabinet. For autotransformers, an additional CT is required in the lead to the primary terminal to give a true image of the temperature in the common/secondary winding. The current transformers shall be of class 1, and the rated primary current shall correspond to the rated current of the related transformer winding. The effective resulting rated secondary current shall be 2A. Matching units between current transformers and thermal replicas shall not be provided.
- iv) **150 mm diameter with angular sweep of 270°, Range of temperature should be 0-150°C with accuracy of ±1.5% (or better) of full scale deflection.** Local indicating instrument with maximum reading pointer, mounted in cooler control cabinet and with two adjustable electrically independent ungrounded contacts (besides that required for control of cooling equipment), one for high winding temperature alarm and one for trip. The temperature indicator dials shall have linear graduations to clearly read at least 2 deg. C
- v) Calibration device.
- vi) In addition to the above, the following indication equipment shall be provided for each winding for remote indication.
 - 1) Conventional Remote winding temperature indicator & Remote Oil temperature indicator: - It shall be suitable for flush mounting on RTCC panel. The difference between local and remote indication at any given time shall not exceed 1 deg. C.
 - 2) Remote Optic Fibre temp. Indicators for winding (6 nos), oil (1no) & core (1no) temperature.
 - 3) Auxiliary supply, if required, in RTCC panel, for above, shall be 220V DC only.
 - 4) The drawing showing details of above shall be submitted to the purchaser.
 - 5) Accuracy class of WTI & OTI shall be +/- 1.5% or better.
 - 6) Any special cable(s), required for shielding purpose for connection between cooler control cabinet and remote winding temperature indicator control circuit shall be in Bidder's scope.
- (c) The winding temperature indicators shall be housed in the cooler control cabinet/marshalling kiosk. The tripping contacts of the winding temperature indicators shall be adjustable to close between 80°C and 150°C and to re-open when the temperature has fallen by not more than 10°C.
- (d) The alarm contacts and the contacts used to control the cooling plant motors on the above devices shall be adjustable to close between 50°C and 100°C and to re-open when the temperature has fallen by a desired amount between 10° C and 15° C.
- (e) All contacts shall be adjustable to a scale and must be accessible on removal of the relay cover. Alarm and trip circuit contacts shall be suitable for making or breaking 150 VA between the limits of 30 and 250 Volts AC or DC and of making 500 VA between the limits of 110 and 250 V DC. Cooler motor control contacts shall be suitable for operating the cooler contactors direct, or if necessary, through an interposing relay.
- (f) The temperature indicators in the marshalling kiosk shall be so designed that it is possible to move the pointers by hand for the purpose of checking the operation of the contacts and associated equipment.
- (g) The working parts of the instrument shall be made visible by the provision of cut-away dials and glass-fronted covers. All setting and error adjustment devices shall be

- easily accessible.
- (h) Connections shall be brought from the device to terminal boards, placed inside the marshalling cubicle.
 - (i) Terminals, links and a 63 mm moving iron ammeter shall be provided in the marshalling kiosk for each WTI for: -
 - (i) Checking the output of the current transformer.
 - (ii) Testing the current transformer and thermal image characteristics.
 - (iii) Disconnecting the bulb heaters from the current transformer secondary circuit to enable the instrument to be used as an oil temperature indicator.
 - (j) Sight glasses of temperature indicators shall be of laminated security glass. Sight glasses of transparent plastics will not be accepted.

In addition to the above, **'OPTIC FIBER TEMPERATURE SYSTEM'** of proven quality and performance in Indian Utilities shall be provided in each transformer for measurement of temperature of windings, oil and core. Bidders are required to state in their offers regarding performance of such Optic Fiber Temperature System along with the names of the end-users in India. The end-user's certificates for such system will be furnished by the Bidders along with their Tender offers.

Following is the criteria for temperature measurement of oil, windings and core by using Fiber Optic Sensors: -

1. System shall be with fiber optic sensors with proven and rugged technology. The probes shall be directly installed in each winding of both HV & LV of power transformer to measure the winding hot spot, top oil and core temperature. There will be **minimum eight probes** inside the transformer, out of which one probe should be installed in top of the transformer for the detection of top oil temperature.

2. The remaining Fiber Optic probes; one each shall be installed in each phase winding (both HV & LV)(6Nos.) at the hottest spot of each of the phase windings and the remaining one in hottest spot of the core. The locations of the probes shall be proposed by the Manufacturer and locations, to be finalized by agreement with the purchaser.

3. Probes shall be able to be completely immersed in hot transformer oil; they shall withstand exposure to hot kerosene vapour during the transformer insulation drying process. The probes shall meet the requirement to eliminate the possibility of partial discharge in high electrical stress areas in the transformer.

4. Temperature range of the system should be -30deg.C to $+200\text{deg.C}$ and accuracy of $\pm 2\text{deg.C}$ with no recalibration required.

5. Probes shall be all silica, double PFA Teflon jacketed; Kevlar cabled fiber with perforated outer jacket to allow complete oil filling; and white Teflon protective Helix wrap having improved visibility and mechanical strength.

6. A microprocessor based monitoring and recording unit shall be a part of the system, having 8(eight) channels. System should include analog outputs for each measurement channel. Temperature resolution of the analog outputs shall be ± 0.1 deg. C and the system shall offer user programmable temperature alarm outputs with 6 relays, alarm lights and controller system status indicators. All inputs and outputs of the system shall meet the requirements of surge test of IEEE C37.90.1-1989 in which a 3000V surge is applied to all the inputs and outputs without permanent damage to the instrument.

7. The system shall be capable of retaining temperature data of a minimum of 90 days at one (1) reading/minute and should retain max temperature of each channel until reset.

8. The transformer manufacturer should submit data showing that the probes are located in

the hottest point of the winding and oil, while submitting drawings for approval.

9. The Fiber Optic cables are to be brought out of the main tank through tank wall penetrator feed through plate. The Feed through plate shall be welded on to the Tank. The external fiber optic extension cable shall then be run to main control cabinet, routed inside the conduits with large bend radius. Protective cover shall be provided for the Tank Wall Feed through Plate.

10. The controller shall be housed in cooler control cubicle or in a separate enclosure having degree of protection IP56 class, mounted on the transformer tank. The position shall be clearly indicated in the GA drawings.

11. Temperature Rise Test Measurement shall be made with the FO Thermometers. The Optic Fiber Temperature System shall be operational during temperature tests and be demonstrated during these tests. During probe verification, the hottest probes for each phase shall be identified and temperature data for all probes (hourly readings) recorded and reported in the test report. The hot spot temperature rise of the windings above ambient temperature shall not exceed 54 deg. C (both for ONAN & ONAF) and the top oil temperature rise above ambient temperature shall not exceed 40 deg. C(both for ONAN & ONAF) as per this specification.

12. For remote indications on RTCC panel, output of 4 to 20mA shall be made available. Digital Temperature Indicators shall be provided in the RTCC Panel for indications of temperatures in each of the windings, top oil and core from the Optic Fiber Temperature Sensor Controller Unit. This shall also be demonstrated during temperature rise test.

13. The cooler control shall be made from optic fibre temperature sensors and the oil temperature high & winding temperature high alarm & trip contacts shall be provided from the optic fibre temperature sensors.

14. The supply & laying of Fibre optic cable from Transformer OFTs Local control panel to RTCC panel for display of temp.(through OFTS) in the RTCC panel is in the scope of the Transformer manufacturer. The approximate distance is around 500 Meters. However, if the distance is more than 500 meters, then the cost of the additional length of the fibre optic shall also be borne by the firm.

15. **Supervision of Erection, Testing & Commissioning:-** The erection, testing and commissioning of the Optic Fiber Temperature System (OFTS) at OPTCL site shall be carried out under direct supervision of the Service Engineer of OFTS manufacturer(s). The Bidder shall furnish authorization letter(s) from such manufacturer(s) with their bid, as per the format given in technical Annexure-X.

5.4.12. COOLING EQUIPMENT AND ITS CONTROLS:

5.4.12.1. Cooling Equipment:

- (a) The Cooler shall be designed using 2 x 50 % radiator banks.
- (b) Each radiator bank shall have its own cooling fans, shut off valves, lifting lugs, top and bottom oil filling valves, air release plug, a drain valve and thermometer pocket, fitted with captive screw cap on the inlet and outlet oil pipes.
- (c) One stand by fan of at least 20% capacity shall also be provided and identified with each radiator bank.
- (d) Cooling fans shall not be directly mounted on radiator bank which may cause undue vibration.
- (e) The exhaust airflow from cooling fan shall not be directed towards the main tank in any case.
- (f) Cooling fans for each radiator bank shall be located so as to prevent ingress of

rainwater.

- (g) It shall be possible to remove the blower complete with motor without disturbing or dismantling the cooler structure framework.
- (h) The blades of cooling fans shall be of galvanised steel or cast aluminum alloy unless otherwise approved. Thickness of galvanization shall be minimum 55 microns.
- (i) Blower casings shall be made of galvanised steel of thickness not less than 2 mm or aluminum alloy and shall be suitably stiffened by angles or tees.
- (j) Galvanised wire guards with mesh not exceeding 12.5 mm shall be provided to prevent accidental contact with the blades. Guards shall also be provided over all moving parts. Guards shall be designed such that blades and other moving parts can not be touched by test fingers to IEC - 529:1976 (BSEN60529). Direction of rotation shall be indicated.
- (k) Cooling fan motors shall be suitable for operation from 415 volts, three phase and 50 Hz power supply and shall conform to IS: 325. The motor winding insulation shall be conventional class 'B' type. Motors shall have hose proof enclosure - equivalent to IP: 55 as per IS: 4691.
- (l) Each cooling fan motor shall be provided with starter thermal overload and short circuit protection.
- (m) Each radiator shall be provided with:
 - One shut off valve at the top (80 mm size).
 - One shut-off valve at the bottom (80 mm size).
 - Air release device at the top.
 - Main and sampling device at the bottom.
 - Lifting lugs to lift entire cooling assembly.
 - Loose blanking plates for blanking off the main oil connections.

One additional Radiator to be provided on Each radiator Bank in addition to designed number of radiator for Temp. rise test. This additional radiator should not be considered for heat dissipation calculation. Valves of these additional radiator used in each radiator bank should be closed during temp. rise test..

N. B.: - The omission of any or the provision of alternative arrangements to the above requirements will not be accepted.

- (n) **OIL PIPES AND FLANGES :**
 - All oil piping, necessary for connecting of each transformer to its conservator, cooler banks shall be supplied under this contract.
 - The oil piping shall be of approved material with machined flanged joints.
 - Copper pipe work is to comply with BS.61.
 - Dimensions of steel pipes shall be in accordance with BS. 3600: 1973 and the drilling of all pipe flanges shall comply with BS: 4504:1969.
 - An approved expansion piece shall be provided in each oil pipe connection between the transformer and each oil cooler bank.
 - All necessary pipe supports, foundation bolts and all other attachments are to be provided.
 - It shall be possible to drain any section of pipe work independently of the rest and drain valves or plugs shall be provided as necessary to meet this requirement

5.4.12.2. **COOLING EQUIPMENT CONTROL (ONAN/ONAF COOLING):**

- (a) Automatic operation control (switching in and out) of fans/pumps shall be provided (with temperature change) from contacts of winding temperature indicator. The supplier shall recommend the setting of WTI for automatic change over of cooler control from ONAN to ONAF. The setting shall be such that hunting i.e., frequent start operations for small temperature differential do not occur.

- (b) Suitable manual control facility for cooler fans with manual/automatic select or switches and push buttons shall be provided.

5.4.12.3. INDICATING DEVICES:

Following lamp indications shall be provided in cooler control cabinet.

- Fan 'ON' Fan 'OFF'.
- Cooling system 'On Automatic Control'.
- Cooling system 'On Manual'.
- Selector switch in 'auto' or 'manual' for each fan
- 415 volts cooler supply auto changeover.
- Cooler supply failure for each supply.
- Cooling fan failure for each fan.
- Control supply failure for main and stand by.
- One potential free initiating contact for all the above indications shall be wired independently to the terminal blocks of cooler control cabinet exclusively for purchaser's use.
- A 12-window annunciator shall be provided in the RTCC panel for visual and audible signaling of important functions of cooling equipment and tap changer.

5.4.12.4. COOLER CONTROL CABINET:

- (a) Each transformer unit shall be provided with a cooler control cabinet.
- (b) The cooler control cabinet shall have all necessary devices, meant for cooler control and local temperature indicators. All the contacts of various protective devices, mounted on the transformer shall also be wired upto the terminal board in the cooler control cabinet. All the secondary terminals of the bushing CTs shall also be wired up to the terminal board at the cooler control cabinet.
- (c) The cooler control cabinet shall have two (2) sections. One section shall have the control equipment, exclusively meant for cooler control. The other section shall house the temperature indicators, auxiliary CTs. and the terminal boards, meant for termination of various alarm and trip contacts as well as various bushing CT Secondaries. Alternatively, the two sections may be provided as two separate panels, depending on the standard practices of the supplier.
- (d) The temperature indicators shall be so mounted that the dials are not more than 1600 mm from ground level. Glazed door of suitable size shall be provided for convenience of reading.

5.4.12.5. TERMINAL BLOCK:

- (a) The terminal blocks ("ELMEX" Make, type – OAT 6 or equivalent) to be provided shall be fully enclosed with removable covers and made of moulded, non-inflammable plastic material with block and barriers, moulded integrally. Such block shall have washer and binding screws for external circuit wire connections, a white marking strip for circuit identification and moulded plastic cover. All terminals shall be clearly marked with identification numbers or letters to facilitate connection to external wiring.
- (b) All internal wiring to be connected to the external equipment shall terminate on terminal blocks, preferably vertically mounted on the side of each panel. The terminal blocks shall be 1100 V grade and have 10 Amps continuous rating moulded piece, complete with insulated barriers, non-disconnecting stud type terminals, washers, nuts and lock nuts. Terminal block design shall include a white fibre-marking strip with clear plastic, slipon/clipon terminal cover. Markings on the terminal strips shall correspond to wire number and terminal numbers on the wiring diagrams.

- (c) Terminal blocks for current transformer's secondary leads shall be provided with test links and isolating facilities. Also current transformer secondary leads shall be provided with short-circuiting and earthing facilities.
- (d) At least 20% spare terminals shall be provided on each panel and these spare terminals shall be uniformly distributed on all terminal blocks.
- (e) Unless otherwise specified, terminal blocks shall be suitable for connecting the following conductors on each side.
 - (i) For all circuits except current transformer circuits, minimum of two nos. 2.5 sq.mm copper.
 - (ii) For all CT circuits, minimum of two nos. 4 sq. mm. copper.
- (f) There shall be a minimum edge-to-edge clearance of 250 mm. between the first row of terminal block and the associated cable gland plate. Also the clearance between two rows of terminal blocks shall be minimum of 150 mm.
- (g) Arrangement of the terminal block assemblies and the wiring channel within the enclosure shall be such that a row of terminal blocks is run parallel and in close proximity long each side of the wiring duct to be provided for convenient attachment of internal panel wiring. The side of the terminal block, opposite the wiring duct shall be reserved for the owner's external cable connection. All adjacent terminal blocks shall also share this field-wiring corridor. A steel strip shall be connected between adjacent terminal block rows at 450 mm intervals for support of incoming cables.
- (h) The number and sizes of the purchaser's multi-core incoming cable will be furnished to the Bidder after placement of the order.

5.4.12.6 **LABELS.**

- a) Labels shall be provided for all the apparatus such as relays, switches, fuses etc., contained in control cabinets/marshalling box.
- b) Description labels for mounting indoor or inside control cabinets/marshalling box shall be of such material that will ensure permanence of lettering. A matt of satin finish shall be provided to avoid dazzle from reflected light. Labels, mounted on dark surfaces shall have white lettering on a black background. All plates shall be of a material, which will not get corroded.
- c) Labeling shall be clear, concise and adequate.
- d) Labels shall be supplied as far as possible in the following four standard sizes
 - (i) Label for fuses and links shall measure approximately 28mm. to 45mm by 13mm. to 19mm. and lettering of 3mm to 6mm. shall be used according to the amount of inscription required. The lettering shall have strokes of approximately 1mm. width.
 - (ii) Labels for relays, contactors, thermal devices and similar apparatus shall measure 65mm. by 20mm. and shall have lettering as specified in (i) above.
 - (iii) Labels for controllers and changeover switches shall measure 70mm. by 30 mm and where practicable have 20 mm lettering with 1.5 mm strokes.
 - (iv) The labels for the doors of junction boxes, marshalling boxes and similar equipment shall measure 125 mm x 50 mm and have 13 mm, lettering with 1.5 mm wide strokes.
- (e) The labels for mounting outdoor shall be weather and corrosion proof. The letters/diagrams thereon shall be framed by etching or other such process, which will ensure permanence of the lettering/markings.
- (f) Labels shall be attached to panels with brass screws or with steel screws which have received rust preventive treatment.

5.4.13 VOLTAGE SELECTION AND CONTROL :

5.4.13.1. On load tap changers:

5.4.13.1.1 General:

- (a) The OLTC shall be of In Tank, Hi Speed Resistor type.
- (b) OLTC gear shall be motor-operated for local as well as remote electrical operation. An external hand wheel/handle shall be provided for local manual operation.
- (c) On-load tap-changer shall be sourced from reputed manufacturer and it should be type tested as per relevant IEC-60214 and test methods shall be in full conformance to the procedures, indicated in IEC-60214.
- (d) The details of the method of diversion of the load current during tap-changing, the mechanical construction of the gear and control features of OLTC gear shall be submitted with the bid. Information regarding the service experience on the gear and a list of important users shall be furnished. The tap-changer shall change the effective transformation ratio without producing phase displacement.
- (e) The current diverting contacts shall be housed in a separate oil chamber, not communicating with the oil in the main tank of the transformer. On load tap changer shall have maximum rated through current to meet the normal rated load as well as over-load as per standards. The OLTC should also be suitable for an occasional switching at 200% of the OLTC rating as per IEC-60214 which shall be validated with by the type test. The OLTC shall have BIL rating as per relevant IEC standards.
- (f) All terminals shall be clearly and permanently marked with numbers corresponding to the cables connected thereto.
- (g) Tap positions shall be numbered consecutively ranging from one upwards. Tap one being the highest voltage ratio.
- (h) Current rating and voltage steps shall be as specified.
- (i) On-load tap changers shall comply with IEC 214:1976 and BS: 4571:1970 and shall be suitable for power flow in both the directions. **Only designs, which have been type tested in accordance with these standards will be accepted. All the type test certificates as per the above standards shall be submitted along with the tender bid.**
- (j) Current making and breaking switches, associated with the tap selectors shall be contained in a tank in which the head of oil is maintained by means, completely independent of that on the transformer itself.
- (k) Details of maintaining oil separation, oil levels, oil draining/filling/sampling, and detection of oil surges and provision of alarm and trip contacts will be dependent on the design of tap-changer and be to the approval of the purchaser. However, a suitable pressure relief device shall be provided for all on-load tap changer compartments. It should be possible to inspect the diverter switch contacts without having to lower the oil in the transformer. Contact tips should be replaceable.
- (l) Transformer on load tap changers shall be equipped with a fixed resistor network, capable of providing discrete voltage steps for input to the supervisory system.
- (m) The Bidder shall indicate the safeguards in order to avoid harmful arcing at the current diverting contacts in the event of operation of the OLTC gear under overload conditions of the transformer.
- (n) Any 'DROP DOWN' tanks, associated with the tap changing apparatus shall be fitted with guide rods to control the movements during lifting or lowering.
- (o) All relays and operating devices shall operate correctly at any voltage between the limits specified.
- (p) The OLTC shall be suitably protected through oil surge relay. This surge relay shall

be tested for an oil flow velocity of 1.20 +/-0.20m/s.

5.4.13.1.2. **MECHANISMS:**

- (a) The drive mechanism chamber shall be mounted on the tank in an accessible position. It should be adequately ventilated and provided with anti-condensation metal clad heaters with thermostatic control. All components inside shall be protected against corrosion, deterioration due to condensation, fungi etc. The door shall be pad-lockable.
- (b) The tap change mechanism shall be designed in such a way that when a tap change has been initiated, it will be completed independently of the operation of the control relays and switches. If a failure of the auxiliary supply during tap change or any other contingency would result in that movement, not being completed, an approved means shall be provided to safeguard the transformer and its auxiliary equipment.
- (c) Limit switches shall be provided to prevent over-running of the tap changing mechanism. These shall be directly connected in the operating motor circuit. In addition, mechanical stops shall be fitted to prevent over-running of the mechanism under any condition. For on-load tap change equipment, these stops shall withstand the full torque of the driving mechanism without damage to the tap change equipment. Limit switches may be connected in the control circuit of the operating motor, provided that a mechanical de-clutching mechanism is incorporated.
- (d) Thermal devices or other approved means shall be provided to protect the motor and control circuit.
- (e) A permanently legible lubrication chart shall be provided and fitted inside the tap-changing chamber.

5.4.13.1.3 **TAP CHANGE CONTROL PHILOSOPHY:**

5.4.13.1.3.1 **General:**

The following operating conditions are applicable to the on-load tap changer controls:-

- (a) It must not be possible to operate the electric drive when the manual operating gear is in use.
- (b) It must not be possible for two electric control points to be in operation at the same time.
- (c) Operation from a control switch shall cause one tap movement only unless the control switch is returned to the off position between successive operations. Subsequent tap changes shall be initiated only by a new or repeat command.
- (d) It shall not be possible for any transformer operating in parallel with one or more other transformers in a group to be more than one tap out of step with the other transformers in the group. On load tap changers shall be equipped with a time delayed INCOMPLETE STEP alarm, consisting of a normally open contact which closes if the tap changer fails to make a complete tap change. The alarm shall not operate for momentary loss of auxiliary power.
- (e) All electrical control switches and local manual operating gear shall be clearly labelled in an approved manner to indicate the direction of tap changing i.e., raise and lower tap number.

5.4.13.1.3.2. **Manual Control:**

- (a) The cranking device for manual operation of the OLTC gear shall be removable and suitable for operation by a man, standing at ground level.
- (b) The manual control shall be considered as back up to the motor operated control and shall be inter locked with the motor to block motor start up during manual operation. The manual operating mechanism shall be labeled to show the direction of operation for raising the terminal voltage and vice-versa.
- (c) Manual tap position indicator which shall be complete with the following:-
 - (i) Mechanical tap position indicator which shall be clearly visible from near the transformer.
 - (ii) A mechanical operation counter.

- (iii) Mechanical stops to prevent over-cranking of the mechanism beyond the extreme tap positions.

5.4.13.1.3.3. **Local and Remote Control:**

Equipment for local, manual and electrical operation shall be provided in an outdoor cubicle. Electrical remote control equipment shall also be supplied on the tap changer. The following control facilities shall be provided: -

- (a) 'Local - Remote' Selector Switch, mounted in the local OLTC, control cabinet. When the selector switch is in 'local' position, it shall be possible to operate the 'raise-lower' control switches, specified in (b) below. Remote control of the raise-lower functions shall be inhibited. When the selector switch is in 'remote' position, the local OLTC control cabinet mounted 'raise-lower' switch, specified in clause (b) below shall be inoperative. Remote control of the raise/lower function shall be possible from the remote control panel. The 'local-remote' selector switch shall have at least two spare contacts per position, which are closed in that position, but open in the other position.
- (b) A 'raise-lower' control switch/push button shall be provided in the local OLTC control cabinet. This switch shall be operative only when 'local-remote' selector switch is in 'local' position.
- (c) An 'ON-OFF' tap changer control switch shall be provided in the local OLTC control cabinet of the transformer. The tap changer shall be in operative in the 'OFF' position. The 'OFF-ON' switch shall have at least one spare contact per position, which is closed in that position, but open in the other position.

5.4.13.1.3.4. **Remote group control:-**

The offered OLTC control scheme shall have provision of remote electrical group control during the parallel operation of transformer. This is in addition to independent control of OLTC.

- (a) A four position selector switch having 'Master', Follower', 'Independent' and 'Off' position shall be provided in the remote OLTC control panel for each transformer. This shall be wired to enable operator to select operation of OLTC in either 'Master', 'Follower', 'Independent' or, 'Off' mode.
- (b) Out of step relays with timer contacts shall also be provided to give alarm and indication in case tap position in all the transformers under group control are not in same position.
- (c) Master Position: If the selector switch is in Master position, it shall be possible to control the OLTC units in the OLTC units in the follower mode by operating the controls of the master unit. Independent operation of the units under Follower mode shall be prevented. However, the units under Independent mode will be controlled independently.
- (d) Follower Position: - If the selector switch is in follower mode, control of OLTC shall be possible only from panel of the Master Unit.
- (e) Independent Position: - In this position of selector switch, control of OLTC of individual unit only shall be possible.

5.4.13.1.4. **Control Circuits:-**

The control circuits shall comply with following conditions:-

- (a) An interlock to cut off electrical control automatically upon recourse being taken to the manual control.
- (b) Re-enforcement of the initiating impulse for a tap changer, ensuring a positive completion, once initiated to the next (higher or lower) tap.
- (c) "Step-by-step" operation ensuring only one tap change from each tap changing impulse and a lockout of the mechanism if the control switch (or push button) remains in the "operation" position.
- (d) An interlock to cut out electrical control when it tends to operate the gear beyond either of the extreme tap positions.
- (e) An electrical interlock to cut-off a counter impulse for reverse step change being initiated during a progressing tap change and until the mechanism comes to rest and

resets circuits for the new position.

- (f) Tap change in progress indication shall be provided by means of an indicating lamp at the purchaser's control panel. Necessary contacts for this and for remote tap position indicator at purchaser's control panel shall be provided by the Bidder.
- (g) Protective apparatus, considered essential by the Bidder according to specialties of the gear.

5.4.13.1.5. **Indications:**

Apparatus of an approved type shall be provided on each transformer:-

- (a) To give indication mechanically at the transformer and electrically at the remote control point of the number of the tapping in use.
- (b) To give electrical indication, separate from that specified above, of tap position at the remote supervisory point. Suitable tap position transducer to be incorporated for indication.
- (c) To give indication at the remote control point and at the supervisory control point that a tap change is in progress, this indication to continue until the tap change is complete.
- (d) To give indication at the remote control point and at the supervisory control point when transformers operating in parallel are out of step.
- (e) To indicate at the tap change mechanism the number of operations, completed by the equipment. A six digit counter should be provided for this.

5.4.13.2. **Automatic Voltage Control:-**

- (a) Automatic control shall be suitable for control of transformers in parallel.
- (b) In addition to the methods of control covered above, the following methods shall also be provided: -
 - (i) Automatic Independent: - It shall be possible to select automatic independent control for each transformer irrespective of the method of control, selected for any other of the associated transformers.
 - (ii) Automatic parallel: - It shall be possible to select any transformer for master or follower control.
 - (iii) Automatic control by AVR shall only be possible if HV circuit breaker is closed.
 - (iv) It must not be possible to operate any tap changer by supervisory, remote or local, electrical, manual control while the equipment is selected for automatic operation.

5.4.13.3 **VOLTAGE REGULATING RELAYS:-**

- (a) Automatic voltage control shall be initiated by a voltage regulating relay of an approved type and suitable for flush mounting. The relay shall operate from the nominal reference voltage, derived from a circuit mounted LV voltage transformer having class B accuracy to BS: 3941 and the relay voltage reference balance point shall be adjustable at the Remote location.
- (b) The relay bandwidth shall preferably be adjustable to any value between 1.5 times and 2.5 times the transformer tap step percentage, the nominal setting being twice the transformer tap step percentage.
- (c) The relay shall be insensitive to frequency variation between the limits of 47HZ and 51.5HZ. The relay shall be complete with a time delay element, adjustable between 10 and 120 seconds. The relay shall also incorporate an under voltage blocking facility which renders the control inoperative if the reference voltage falls below 80 percent of the nominal value with automatic restoration of control when the reference voltage rises to 85 percent of nominal value.
- (d) The voltage control relay shall include an adjustable line drop compensation element, supplied from a current transformer, accommodated within the transformer bushing.
- (e) On each transformer, the voltage transformer supply to the voltage-regulating relay shall be monitored for partial or complete failure. The specified indicating lamp and alarm will be inoperative when the circuit breaker, controlling the lower voltage side of the transformer is open and also when the tap changer is on control other than

automatic control.

5.4.13.4 LOCAL CONTROL CABINET: -

The local OLTC control cabinet shall house all necessary devices, meant for OLTC control and indication. It shall be complete with the following: -

- (a) A circuit breaker/contactors with thermal overload devices for controlling the A.C. auxiliary supply to the OLTC motor.
- (b) Cubicle light with door switch.
- (c) Space heaters to prevent condensation.
- (d) Padlocking arrangement for hinged door of cabinet.
- (e) Cable terminal glands for power and control cables to the OLTC gear.

5.4.13.5. REMOTE CONTROL PANELS: -

- a) All controls, alarms and indications for transformers shall be incorporated within the appropriate switchgear control panels. The supplier shall provide all indications, relays, switches etc. for remote indication and operation of the transformer from the substation control room. Comprehensive and detailed instructions shall be provided to the purchaser regarding correct installation of this remote panel.
- (b) The remote tap changer control panel shall be mounted in the purchaser's control room. Size and colour of the panel shall be to the approval of the purchaser.
- (c) Operation of remote control scheme shall be entirely suitable for the distance between the transformer and remote control panel. Details of the connection of the remote control panel to the transformer shall be provided by the supplier.
- (d) The standard requirements (which may be varied to suit manufacturer's design) shall be out lined in the following sub-clauses:

5.4.13.5.1. INSTRUMENTS:

- (a) Voltmeter (voltage at the low voltage terminals of the transformer).
- (b) Tap position indicator
- (c) Conventional winding & oil temperature indicator.
- (d) Optic fibre temperature indicators for winding(6 nos), Oil (1 no) and core(1 no).

5.4.13.5.2. RELAYS:

- (a) Automatic voltage control.
- (b) Supervisory interface.

5.4.13.5.3. CONTROLS:

- (a) Automatic/non-automatic voltage control selector switch.
- (b) Remote/supervisory tap change control selector switch.
- (c) Raise/lower push-buttons.
- (d) Independent/Master/Follower selector switch.
- (e) AVR Voltage reference adjuster.

5.4.13.5.4. INDICATIONS AND ALARMS :

- (a) Tap changer on manual control - white lamp.
- (b) Tap change in progress - white lamp.
- (c) Tap change out of step-alarm.
- (d) Cooling equipment running-white lamp.
- (e) Cooling equipment failure-alarm.
- (f) AVR reference voltage failure-alarm.
- (g) Tap changer supply voltage failure-alarm.
- (h) Tap change incomplete step-alarm.

5.4.13.6. AUXILIARY SUPPLY FOR OLTC CONTROL AND POWER CIRCUIT :-

Auxiliary supplies as indicated in the specification will be provided by the purchaser at any one place. All loads shall be fed by one of the two feeders through an

electrically interlocked automatic transfer switch, housed in the marshalling Kiosk. The design feature for the transfer switch shall include the following: -

- (a) Provision for the selection of one of the feeders as normal source and the other as standby.
- (b) Upon failure of normal source, the loads shall be automatically transferred after an adjustable time delay to the stand by source.
- (c) Indication for failure of the normal source and for transfer to standby source and also for failure to transfer shall be provided locally as well as at the remote control panel.
- (d) Automatic re-transfers to normal source with an adjustable time delay following re-energisation of the normal source.
- (e) Both the transfer and the re-transfer shall be dead transfers and AC feeders shall not be paralleled at any time.
- (f) Necessary isolating switches, MCBs and other components for the above power supply transfer arrangement shall be provided by the supplier.

5.4.14. **SUPERVISORY CONTROL:-**

5.4.14.1 **General:-**

- (a) Tap change control equipment shall be suitable for supervisory control and indication with make before break multi-way switch-having one potential free contact for each tap position. This switch shall be provided in addition to any other switch/switches, which may be required in remote tap position indication.
- (b) Transformer on-load tap changer shall be equipped with a fixed resistor network, capable of providing discrete voltage steps for input to the supervisory system.
- (c) Transformer tap change control will be effected from the sub-station control room with facilities for remote control from the supervisory control centre. Provision for such supervisory control shall be included in this contract.
- (d) The supervisory facilities, outlined in the following sub-clauses will be required and control circuit design must make provision for these.

5.4.14.2. **CONTROLS:**

- (a) Tap change control remote/supervisory select/deselect:-
N.B.:- Selection of supervisory control shall render voltage control non-automatic.
- (b) Tap position Raise/lower.

5.4.14. 3 **INDICATIONS AND ALARMS:**

- (a) Tap change remote/supervisory indication.
- (b) Tap position indication through appropriate transducer.
- (c) Tap change out of step alarm.
- (d) Tap changer auto/non-auto indication.
- (e) Independent/master/follower indication.
- (f) Tap change in progress indication.
- (g) AVR reference voltage failure alarm.
- (h) Tap changing incomplete (TCINCL).
- (i) Tap changer supply failure alarm.
- (j) Cooling equipment running indication.
- (k) Cooling equipment failure alarm.
- (l) All contacts for supervisory alarms and indications shall be potential free.

5.4.15. **TERMINAL AND CONNECTION ARRANGEMENTS :**

5.4.15.1 **RATING:**

Current rating shall be 1.5 times the rated current of the transformer.

5.4.15.2. **OUTDOOR BUSHINGS:**

a) Bushings shall be robust and designed for adequate cantilever strength to meet the requirement of seismic condition, substation layout and movement along with the spare transformer with bushing erected and provided with proper support from one foundation to another foundation within the substation area. The electrical and mechanical characteristics of bushings shall be in accordance with IEC: 60137/DIN 42530. All details of the bushing shall be submitted for approval and design review. Bushings must have been type tested successfully as per IS: 2099/IEC-60137. The type test report need to be furnished during approval stage.

b) Bushing for voltage of 36 kV and above shall be RIP/RIS bushing with composite polymer insulator.

c) RIP/RIS type bushing shall be provided with tap for capacitance and tan delta test. Test taps relying on pressure contacts against the outer earth layer of the bushing is not acceptable.

d) Where current transformers are specified, the bushings shall be removable without disturbing the current transformers.

e) Bushings of identical rating shall be interchangeable to optimize the requirement of spares.

f) Porcelain used in bushing manufacture shall be homogenous, free from lamination, cavities and other flaws or imperfections that might affect the mechanical or dielectric quality and shall be thoroughly vitrified, tough and impervious to moisture.

g) Composite polymer insulator shall be seamless sheath of a silicone rubber compound. The housing & weather sheds should have silicon content of minimum 30% by weight. It should protect the bushing against environmental influences, external pollution and humidity. The interface between the housing and the core must be uniform and without voids. The strength of the bond shall be greater than the tearing strength of the polymer. The manufacturer shall follow non-destructive technique (N.D.T.) to check the quality of jointing of the housing interface with the core. The technique being followed with detailed procedure and sampling shall be decided during finalization of QAP.

The weather sheds of the insulators shall be of alternate shed profile as per IEC 60815-3. The weather sheds shall be vulcanized to the sheath (extrusion process) or moulded as part of the sheath (injection moulding process) and free from imperfections. The vulcanization for extrusion process shall be at high temperature and for injection moulding shall be at high temperature & high pressure. Any seams / burrs protruding axially along the insulator, resulting from the injection moulding process shall be removed completely without causing any damage to the housing. The track resistance of housing and shed material shall be class 1A4.5 according to IEC60587. The strength of the weather shed to sheath interface shall be greater than the tearing strength of the polymer. The composite insulator shall be capable of high pressure washing.

End fittings shall be free from cracks, seams, shrinks, air holes and rough edges. End fittings should be effectively, sealed to prevent moisture ingress, effectiveness of sealing system must be supported by test documents. All surfaces of the metal parts shall be perfectly smooth with the projecting points or irregularities which may cause corona. All load bearing surfaces shall be smooth and uniform so as to distribute the loading stresses uniformly.

The hollow silicone composite insulators shall comply with the requirements of the IEC publications IEC 61462 and the relevant parts of IEC 62217. The design of the composite insulators shall be tested and verified according to IEC 61462 (Type & Routine test).

- h) Clamps and fittings shall be of hot dip galvanized /stainless steel.
- i) Bushing turrets shall be provided with vent pipes, to route any gas collection through the Buchholz relay.
- j) No arcing horns shall be provided on the bushings.
- k) RIP/**RIS** bushings shall be specially packed to avoid any damage during transit & suitable for long storage with non-returnable packing wooden boxes with hinged type cover, without any gaps between wooden planks. Packing box opening cover with nails/ screws type packing arrangement shall not be acceptable. Bushing oil end portion shall be fitted with metal housing with positive dry air pressure and a suitable pressure monitoring device shall be fitted on the metal housing during storage to avoid direct contact with moisture with epoxy. Alternatively oil filled metal housing with suitable arrangement for taking care oil expansion due to temperature variations shall also be acceptable. Manufacturer shall submit drawings / documents of packing for approval during detail engineering. Detail method for storage of bushing including accessories shall be brought out in the instruction manual.
- l) The terminal marking and their physical position shall be as per IEC: 60076.
- m) Tan Delta measurement at variable frequency (in range of 20 Hz to 350 Hz) shall be carried out on each condenser type bushing at transformer manufacturing works as routine test before dispatch and the result shall be compared at site during commissioning to verify the healthiness of the bushing. If the bushing Tan Delta goes beyond **0.004** or increase is more than 0.001(at max ambient temp.) within the guarantee period with respect to the pre-commissioning values, the contractor shall arrange to replace the defective bushing by new one. No temperature correction factor shall be applicable for Tan Delta.

5.4.15.3. **TERMINAL CONNECTORS:**

- (a) Bushing terminals shall be provided with terminal connectors of approved type and size for connection to external parts. Terminal connectors, offered must have been successfully type tested as per IS: 5561.
- (b) (i) All castings shall be free from blow holes, surface blisters, cracks and cavities. All sharp edges and corners shall be blurred and rounded off. The aluminum alloy castings, if used, shall conform to designation A6 of IS: 617.
- (ii) No part of clamp shall be less than 10 mm. Thick.
- (iii) All ferrous parts shall be hot dip galvanized conforming to IS: 2633. Spring washers and H.T. bolts shall be dectrogalvanized conforming to IS: 1573.
- (iv) For bimetallic clamp, copper alloy linear of minimum thickness of 2 mm. Shall be cast integral with aluminum body.
- (v) Flexible connectors shall be made from tinned copper sheets.
- (vi) Size of terminal/conductor for which the clamp is suitable and rated current under site conditions shall be embossed/punched on each component of the clamp, except hardware.
- (vii) All current carrying parts shall be designed and manufactured to have minimum contact resistance.
- (viii) The short time rating of terminal connector shall not be less than the short time rating of respective bushing.
- (ix) Terminal connectors shall be subject to all type, routine and acceptance tests as per IS: 5561 (latest).
- (x) Malleable cast iron for terminal connectors or any of its parts and accessories shall not be acceptable.
- (xi) Bolts and Nuts used shall be of stainless steel or galvanized/passivated mild steel.

5.4.15.4. **TERMINAL MARKING:**

Transformer terminals are to be provided with phase markings to the requirements of IEC616 and are subject to the agreement of the purchaser. Transformer terminals shall be silver/tin-plated copper.

5.4.15.5 **NEUTRAL** **EARTHING:**

The neutral terminals shall be brought to ground level by a brass or tinned copper grounding bar of approved size which shall be supported from the tank with porcelain insulators and connected to purchaser's local earth grid. The supplier must liaise with the purchaser or its approved contractor to finalise the details of installation of this earthing and mounting of the outdoor neutral C.T. on this.

5.4.16. **SPECIFICATION FOR CONTROL CABINETS:**

- (a) Control cabinets shall be of the free standing floor mounting type.
- (b) Control cabinet of the operating mechanism shall be made **out of 2 mm thick stainless steel plate**. Hinged door shall be provided with pad locking arrangement. Sloping rain hood shall be provided to cover all sides. 15 mm thick neoprene or better type of gaskets shall be provided to ensure degree of protection of at least IP-55 as per IS: 2147.
- (c) Bus bars shall be of tinned copper of adequate cross-section to carry the normal current without exceeding the permissible temperature rise over an ambient temperature of 50 degree centigrade outside the cubicle. The buses shall be braced to withstand forces corresponding to short circuit current of 25KA.
- (d) Motors rated 1 KW and above being controlled from the control cabinet would be suitable for operation on a 415V, 3 Phase, 50 HZ system. Fractional KW motors would be suitable for operation on a 240V, 1- Phase, 50 HZ supply system.
- (e) Isolating switches shall be group operated units (3 pole for use on 3-MCBS phase supply systems and 2 pole for single phase supply systems) quick make quick break type, capable of breaking safely and without deterioration, the rated current of the associated circuit. Switch handle shall have provision for locking in both fully open and fully closed positions.
- (f) Push button shall be rated for not less than 6 Amps, 415V A.C. or 2 Amps, 220/110V D.C. and shall be flush mounted on the cabinet door and provided with appropriate nameplates. Red, Green and Amber indicating lamps shall be flush mounted.
- (g) For motors upto 5 KW, contactors shall be direct-on-line, air break, single throw type and shall be suitable for making and breaking the stalled current of the associated motor which shall be assumed equal to 6.5 times the full load current of the motor at 0.2 p.f. For motors above 5 KW, automatic star delta type starters shall be provided. 3 Pole contactors shall be furnished for 3 Phase motors and 2 Pole contactors for single phase motors. Reversing contactors shall be provided with electrical interlocks between forward and reverse contactors. If possible, mechanical interlocks shall also be provided. Contactors shall be suitable for uninterrupted duty and shall be of duty category class AC4 as defined in IS: 2959. The main contacts of the contactors shall be silver plated and the insulation class for the coils shall be class E or better. The dropout voltage of the contactors shall not exceed 70% of the rated voltage.
- (h) Contactors shall be provided with a three element positive acting, ambient temperature compensated, time lagged, hand reset type, thermal overload relay with adjustable setting. Hand reset button shall be flush with the front door of the cabinet and suitable for resetting with starter compartment door closed.
- (i) Single phase preventer relay shall be provided for 3 Phase motors to provide positive protection against single phasing.
- (j) Mini starters shall be provided with no volt coils, whenever required.

- (k) Purchaser's power cables will be of 1100 Volts grade stranded aluminum conductor PVC insulated, PVC sheathed, single steel wire armoured and PVC jacketed. All necessary cable terminating accessories such as glands, crimp type tinned copper lugs etc. for power as well as control cables shall be included in Bidder's scope of supply. Suitable brass cable glands shall be provided for cable entry.
- (l) Wiring for all control circuits shall be carried out with 1100Volts grade PVC insulated tinned copper stranded conductors of sizes not smaller than 2.5 sq.mm. At least 20% spare terminal blocks for control wire termination shall be provided on each panel. The terminal blocks shall be of non-disconnecting stand type. All terminals shall be provided with ferrules, indelibly marked or numbered and these identifications shall correspond to the designations on the relevant wiring diagrams. The terminals shall be rated for adequate capacity which shall not be less than 10Amps.
- (m) Separate terminal blocks shall be provided for terminating circuits of various voltage classes. CT loads shall be terminated on a separate block and shall have provision for short circuiting the CT secondary terminals.
- (n) Control cabinet shall be provided with 240V, 1 Phase, 50 HZ, 20 W fluorescent light fixture and a suitably rated 240 V, 1 Phase, 5 Amps, 3 Pin socket for hand lamps.
- (o) Strip heaters shall be provided inside each cabinet complete with thermostat (preferably differential type) to prevent moisture condensation. Heaters shall be controlled by suitably rated double pole miniature circuit breakers.
- (p) Signal lamps, provided shall be of neon screw type with series resistors, enclosed in bakelite body. Each signal lamp shall be provided with a fuse, integrally mounted in the lamp body.
- (q) Electric measuring instruments shall be of moving iron type. Ammeters for measuring current upto 30 Amps shall be directly connected while those for measuring above 30 Amps shall be connected through suitable CTs. Ammeters shall be provided with selector switches.
- (r) Items inside the cabinet, made of organic material shall be coated with a fungus resistant varnish.

5.4.17

INSULATING OIL:-

- (a) The quality of the oil, supplied with the transformer shall conform to IEC 296 (Mineral oil class 1) and IS: 335 with latest amendment, if any. The percentage of Naphthenic content in the oil will be more than 40 percent and paraffinic content will be less than 56 percent. No oil shall be supplied or used at any stage of manufacture or test without a certificate, acceptable to the Purchaser that it has a PCB content of less than 2 mg/kg. No inhibitors shall be used in the oil. The oil samples will be drawn as follows:-
 - (i) Prior to filling.
 - (ii) Before and after heat run test.
 - (iii) Before energising.

All tests as per relevant IEC & ISS shall be conducted on all samples.
- (b) Sufficient quantity of oil, necessary for first filling of all tanks, coolers and radiators at the proper level along with 10% extra oil for topping up shall be supplied in non-returnable containers, suitable for outdoor storage.
- (c) The supplier shall despatch the transformer, filled with oil or in an atmosphere of Nitrogen. In the former case, the Bidder shall take care of the weight limitation on transport and handling facility at site. In the latter case, necessary arrangement shall be ensured by the supplier to take care of pressure drop of nitrogen during transit and storage till completion of oil filling during erection. A gas pressure testing valve with necessary pressure gauge and adapter valve shall be provided.
- (d) **The transformer shall also be fitted with an impact recorder during transportation. This impact recorder is on returnable basis.**
- (e) The Bidders shall ensure that the oil supplied is in accordance with the latest editions

of the following specifications with amendments, if any.

Sl. No.	Characteristics	Requirement.	Method of Test.
1	Appearance	The oil shall be clear and transparent & free from suspended matter or sediments.	A representative sample of oil shall be examined in a 100mm thick layer at ambient temperature.
2	Density at 27 deg.C (Max)	0.89 g/cu.cm.	IS: 1448
3	Kinematic viscosity at 27Cst.		IS: 1448 27 deg.C (max.)
4	Interfacial tension at 27 deg.C (min.)	0.04 N/m	IS: 6104
5	Flashpoint penskey Marten (closed) (min.)	140 deg.C	IS: 1448
6	Pour point (max.)	-6 deg.C	IS: 1448
7	Neutralization value (max.) (Total acidity).	0.03 mg KOH/g	IS: 335
8	Corrosive Sulphur (In terms of classification of copper strip)	Non-corrosive	IS: 335 (Appendix 'B')
9.	Electric strength (break down voltage) min.		
	a) New unfiltered oil.	30 KV (rms) if the above value is not attained, the oil shall be filtered)	IS: 6792.
	b) After treatment.	60 KV (rms)	
10	Di-Electric dissipation factor (tan delta) at 90 deg.C (max.)	0.002	IS: 6262
11.	Specific resistance (resistivity)		
	a) at 90 deg.C (min.)	35 x 10 ¹² Ohm-cm.	IS: 6103
	b) at 27 deg.C (min.)	1500 x 10 ¹² Ohm-cm.	
12.	Oxidation stability.		
	a) Neutralization value after oxidation (max.)	0.4 mg KOH/g.	
	b) Total oxidation (max.).	0.10%	Sludge by after weight.
13.	`Presence of Oxidation inhibitor	The oil shall not contain anti oxidant inhibitors.	IS: 335 (Appendix 'D')
14.	Water content (max.)	a) Untreated and unfiltered Oil- 50 ppm. b) Before commissioning- 10 ppm.	IS: 2362
15.	Aging characteristics after 96 hrs. with catalyst (Copper)	As per AS TMD/934/IS: 12177	
	a) Resistivity.		
	i) 27 deg.C	2.5 x (10) ¹² Ohm-cm.	
	ii) 90 deg.C	0.2 x (10) ¹² Ohm-cm.	
	b) Tan delta at 90 deg.C	0.2 (max.).	
	c) Total acidity.	0.05 mg KOH/gm (max.)	
	d) Sludge content by weight.	0.05% (max.)	
16.	a) Napthenic content	More than 40%	Spectroscopic method
	b) Paraffinic content	Less than 56%	or any other prescribed method.

The Test certificates to conform the quality of the oil shall be submitted by the supplier. The purchaser at his discretion may depute his representative for witnessing the tests at the works of the supplier or its sub-vendor. The purchaser's representative may recommend for testing of sample oil at CPRI/ERDA including ensuring the percentage of and paraffinic content in the offered oil. The cost for such testing shall be borne by the supplier. The purchaser at his discretion may also get the supplied oil, tested at Govt. approved laboratory for determination of quality, naphthenic and paraffinic contents as per specification.

5.4.18 **CLEANING, PAINTING AND TROPICALISATION:-**

- (a) All steel surfaces except galvanized surfaces or where otherwise specified, shall be shot blasted to remove all rust, scale and foreign matters from the surface. Oil, grease, dirt and swarf shall be thoroughly removed by emulsion cleaning. The surfaces shall then be chemically cleaned and surface treated by phosphating and dried in accordance with IS6005 - "Code of practice for phosphating of iron and steel". Immediately after phosphating, the surfaces shall be given two coats of high quality zinc chromate primer.
- (b) The interior surfaces of mechanism chambers, boxes and kiosks, after preparation, cleaning and priming shall be painted with one coat of zinc chromate primer, one coat of phenolic based undercoating, followed by two coats of phenolic based finishing paint to white colour, followed by a final coat of anti-condensation white paint of a type and make to the approval of the Purchaser. A minimum overall paint film thickness of 200 microns shall be maintained throughout.
- (c) All steel work and metal work, after preparation and priming shall be painted with one coat zinc chromate primer, one coat of phenolic based under coating and two coats of micaceous iron oxide paint to an overall thickness of 200 microns to hard gloss finishing Light Grey Shade No. 697 of IS:5. Each successive coat of paint shall be of slightly different shade to enable inspection. The finished surface shall present a pleasing appearance free from dents or unevenness surfaces.
- (d) It is the responsibility of the supplier to ensure that the quality of paints used shall withstand the tropical heat and extremes of weather conditions. The paint shall not peel-off, wrinkle, be removed by wind, storm and handling on site and the surface finish shall neither rust nor fade during the service life of the equipment.
- (e) After erection at site, the interior surfaces of mechanism chambers and kiosks shall be thoroughly examined and any deteriorated or mechanically damaged surfaces of such shall be made good to the full specification, described above.
- (f) After erection at site, all surfaces of steel works and metal works shall be thoroughly washed down and examined. Any deteriorated or otherwise faulty paint work shall be removed down to bare metal and made good to the full specification described above, then painted one further coat of phenolic based under coating and one coat phenolic based hard gloss finishing paint to provide an overall minimum paint film thickness of 200 microns.
- (g) All paint work shall be left clean and perfect on completion of the site works.

5.4.19. **BOLTS AND NUTS:-**

- (a) All bolts, studs, screw threads, pipe threads, bolt heads and nuts shall comply with the appropriate Indian Standards for metric threads, or the technical equivalent.
- (b) Except for small wiring, current carrying terminal bolts or studs for mechanical reasons shall not be less than 6 mm in diameter.
- (c) All nuts and pins shall be adequately locked.
- (d) Wherever possible, bolts shall be fitted in such a manner that in the event of failure of locking resulting in the nuts working loose and falling off, the bolt will remain in position .
- (e) All bolts, nuts and washers, placed in outdoor positions shall be treated to prevent corrosion, by hot dip galvanizing. Bolts and Nuts below M12 (12mm.) size shall be of stainless steel. Appropriate precautions shall be taken to prevent electrolytic action

- between dissimilar metals
- (f) Where bolts are used on external horizontal surfaces and where water can collect, methods of preventing the ingress of moisture to the threads shall be provided.
- (g) Each bolt or stud shall project at least one thread, but not more than three threads through the nut, except when otherwise approved for terminal board studs or relay stems. If bolts or nuts are placed so that they are inaccessible by means of ordinary spanners, special spanners shall be provided.
- (h) The length of the screwed portion of the bolts shall be such that no screw thread may form part of a shear plane between members.
- (i) Taper washers shall be provided where necessary.
- (j) Protective washers of suitable material shall be provided front and back on the securing screws.

5.4.20. **WIRING AND CABLING:-**

5.4.20. 1 (a) Cable box/sealing end shall be suitable for following types of cable.

- | | |
|-------------------|---|
| i) 415 Volt Power | 1100 Volt grade PVC
Insulated aluminum conductor cable with
armour. |
| ii) Control. | 1100 Volt grade PVC insulated
7/0.737 mm stranded copper conductor cable
with armour. |
- (b) Compression type cable connector shall be provided for termination of power and control cables.
 - (c) All controls, alarms, indicating and relaying devices, provided with the transformer shall be wired up to the terminal blocks inside the local control cabinets (both cooler and OLTC control cabinets)
 - (d) All devices and terminal blocks with the cooler control cabinet shall be clearly identified by symbols, corresponding to those used on applicable schematic or wiring diagrams.

5.4.20.2 **EXCLUSION IN SCOPE OF CABLING:**

Following cabling works are specifically excluded from the scope of the supplier. However, interconnection drawings for the same are to be submitted by the supplier

- (a) Cabling between Remote OLTC panel to cooler control cabinet.
- (b) Cabling between Remote OLTC panel to local OLTC cabinet.
- (c) Cabling between Remote OLTC to supplier's panel.
- (d) Cabling between cooler control cabinet to supplier's panel.
- (e) Cabling between local OLTC cabinet to supplier's panel.

5.4.21. **FITTINGS:**

The following fittings shall be provided with each transformer, covered in this specification.

- (a) Conservator for main tank with oil filling hole and cap, air-cell, vacuum application valve, vacuum equalizing valve, isolating valves, drain valve, shut off valve, magnetic oil level gauge with low level alarm contacts, dehydrating breather, with oil seal.
- (b) Conservator for OLTC with drain valve, surge relay (oil flow operated), vacuum application valve, vacuum equalizing valve, magnetic type oil level gauge with low level alarm contacts, oil-level indicator and silica gel breathers.
- (c) Oil preservation equipment.
- (d) Pressure relief devices with alarm/trip contacts.
 - (e)
 - (i) Buchholz relay, double float/read type with isolating valves on both sides, bleeding pipe with pet cock at the end to collect gases and

alarm and trip contacts (02 nob. for alarm, 03 nob. for Trip, Rating 10 Amp. 220V DC) test cock, gas collection box and gas check valve at ground level.

(ii) Separate Oil Surge Relay (04 trip contacts , Rating 10 Amp. 220V DC),with above features to be provided for OLTC chamber.

- (f) Air release plug.
- (g) Inspection openings and covers.
- (h) Bushing with metal parts and gaskets to suit the termination arrangement.
- (i) Winding temperature indicators for local and remote mounting. One RWTI with a four point selector switch shall be provided for three windings.
- (j) Top Oil temperature indicators with maximum pointer along with two sets of contactors.
- (k) Cover lifting eyes, transformer lifting lugs, jacking pads, towing holes and core and winding lifting lugs.
- (l) Protected type mercury or alcohol in glass thermometer.
- (m) Bottom and top filter valves with threaded male adoptors, bottom sampling valve and drain valve.
- (n) Rating and diagram plates on transformers and auxiliary apparatus.
- (o) Earthing terminals.
- (p) Flanged bi-directional wheels.
- (q) Cooler Control Cabinet with pad locks.
- (r) On load tap changing equipment and OLTC control cabinet with pad locks.
- (s) Drain valve plugs shall be provided in order that each section of pipe work can be drained independently.
- (t) Insulating Oil.
- (u) Terminal marking plate.
- (v) Jacking pads/lugs
- (w) Lifting bollards.
- (x) Haulage lugs.
- (y) Cover lifting lugs.
- (z) Valve schedule plate.
- (aa) Cooling fans
- (bb) Marshalling Box
- (cc) RTCC Panel
- (dd) Bushing Terminal Clamps & Connectors
- (ee) Valves, as indicated at Cl.No.5.4.2 of this Specification
- (ff) Wiring upto marshalling box with PVC SWA PVC copper cables, 1100Volts grade.
- (gg) Suitable NIFPES to be installed in accordance to the specification of OPTCL. Type test report reports(if any) , relevant drawings, logic circuit, functional philosophy to be submitted along with the bid offer
- (hh) Thermosyphon Filter
- (ii) 8(Eight) Probes & 8(eight) Channel Optic Fiber Temperature Sensor System as per this specification

Note: - The fittings listed above are only indicative and any other fittings which generally are required for satisfactory operation of the above rated Power transformers are deemed to be included.

5.4.22. **LIMITS OF TEMPERATURE RISE:-** The temperature rise on any part of equipment shall not exceed the maximum temperature rise specified below under the conditions specified in test clauses. The permissible temperature rise indicated is for a maximum ambient temperature of 50 degree C. If the maximum ambient temperature rises, permissible values shall be reduced accordingly. For actual maximum temperature at the location of installation, refer perfect synopsis.

		Temperature.	Temperature rise at a maximum ambient air temp. not exceeding 50 degree C.
1	Contacts in air, silver-faced copper, copper alloy or aluminium alloy (see notes (i) & (ii). Bare copper or tinned aluminium alloy.	95	40/45
2	Contacts in oil: Silver-faced copper, copper alloy or aluminium alloy [see note-(i)].	75 90	25 40
3	Terminals to be connected to external conductors by screws or bolts silver faced (see note (iii)).	80 105	30 55
4	Metal parts acting as springs.		(See note iv). (See note iv).
5	Metal parts in contact with insulation of the following classes: Class Y: (for non-impregnated materials). Class A: (for materials immersed in oil or impregnated). Class E: in air In oil Class B: in air In oil Class F: in air In oil Enamel: oil base Synthetic, in air Synthetic, in oil	90 100 120 100 130 100 155 100 100 120 100	40 50 70 50 80 50 105 50 50 70 50
6	Any part of metal or of insulating material in contact with coil, except contacts.	100	50
7	Oil	90	40

Notes: (i) When applying the temperature rise of 45° C, care should be taken to ensure that no damage is caused to the surrounding insulating materials.

- (ii) The quality of the silver facing shall be such that a layer of silver remains at the points of contact after the mechanical endurance test. Otherwise, the contacts shall be regarded as 'bare'.
- (iii) The values of temperature and temperature rise are valid whether or not the conductor connected to the terminals is silver-faced.
- (iv) The temperature shall not reach a value where the elasticity of the material is impaired. For pure copper, this implies a temperature limit of 75°C.

5.4.23. **MOTORS & MCBS:**

- (a) All motors shall comply with IS: 325 and IEC 34 and dimensions with IEC-72. They shall be capable of operating continuously under actual service conditions without exceeding the specified temperature rises, determined by resistance, at any frequency between the voltage and frequency fluctuation, stated in this specification.
- (b) All miniature circuit breakers shall be provided with auxiliary contacts for remote indication of circuit breaker operation. Means shall be provided to prevent the miniature circuit breakers, being inadvertently switched to the 'OFF' Position. Miniature circuit breakers shall be mounted in such a manner so as to give easily visible indication of breaker position and shall be grouped and spaced according to

their function in order to facilitate identification and easy replacement.

5.4.24. **LIST OF MANDATORY SPARES FOR EACH UNIT OF TRANSFORMER**

- (a) The supplier shall provide the mandatory spares, detailed below and shall, where considered necessary, provide a list of recommended spare parts together with their individual prices. The purchaser may order all or any of the spare parts, listed at the time of contract award and the spare parts, so required by the purchaser, shall be supplied as part of this contract. Additional spares may be ordered at anytime during the contract at the rates, stated in the purchase order.

<u>Sl.No.</u>	<u>Description.</u>	<u>Quantity.</u>
1	HV Bushing with metal parts & gaskets	2 No
2	LV Bushing with metal parts & gaskets	1No
3	HV Neutral Bushing with metal parts & gaskets	1 No
4	LV Neutral Bushing with metal parts & gaskets	1 No
5	Local & remote winding Temperature indicators with contacts	1 set
6	Oil Temperature indicators with contacts	1set
7	Pressure Relief Device	1 No
8	Magnetic oil level gauge with low oil level alarm contacts	1 No
9	Cooler fan with motor	1 No
10	Buchholz relay	1 No
11	Set of starter, contactor relays and switches (1 No. of each type & size)	1 set
12	Tap position Indicator (Local & Remote)	1 No
13	Fuses (control)(complete replacement for transformer)	100%
14	Lamps (indicative) (complete replacement of transformer)	100%

N.B.:-

- (a) The Supplier shall ensure that sufficient spare parts and consumable items are available for his own use during commissioning of the transformer. The spares, provided with the transformer shall not be used by the supplier without the written consent of the Purchaser and any spares, used during the commissioning of the transformer shall be replaced by the supplier at his own expense.
- (b) The Supplier shall provide a list in the schedule, of additional recommended spare parts together with their individual prices. The Purchaser may order at a later date, at a price, indicated on the schedule, such additional spare parts, listed at the time of contract award.
- (c) Spares shall be available during the life of the equipment and the Supplier shall give 12 months notice of his or any Sub-Suppliers, intention to cease manufacture of any component used in the equipment.
- (d) Any spare apparatus, parts and tools shall be subject to the same Specification, tests and conditions as similar material, supplied under this contract. They shall be strictly interchangeable and suitable for use in place of the corresponding parts, supplied with the transformer and must be suitably marked and numbered for identification and prepared for storage by greasing and painting to prevent deterioration.
- (e) All spare apparatus or materials, containing electrical insulation shall be packed and delivered in cases, suitable for storing such parts or material over a period of years without deterioration. Such cases shall have to be affixed to both the underside and top side of the lid a list detailing its contents. The case will remain as the property of the Purchaser.

5.4.25 NITROGEN INJECTION TYPE FIRE PREVENTION & EXTINGUISHING SYSTEM:-

5.4.25.1 General:- Scope of work is to design, supply, erection, testing and commissioning of Nitrogen Injection system for protection against the transformer explosion and fire for above

Transformers including all required civil works of oil sump, foundations, any other required for satisfactory working of system. The NIFPS shall be guaranteed as per clause no. 18 of GTCC.

Each oil filled transformer shall be provided with a dedicated Nitrogen Injection system for prevention against the transformer explosion which shall use nitrogen as quenching medium. The system shall prevent transformer oil tank explosion and possible fire in case of internal / external cause. In the event of fire by external causes such as bushing fire, OLTC fires, fire from surrounding equipment etc., it shall act as a fast and effective fire fighter. It shall accomplish its role as fire preventer and extinguisher without employing water or carbon dioxide. Fire shall be extinguished within reasonable time (not more than 3 minutes so as not to harm the transformer) of system activation and within 30 seconds (maximum) of commencement of nitrogen injection. The offered NIFPS system should have been in successful operation in Indian installations for at least last five years for protection of transformers of 220 KV and higher voltage class. The list of past supplies in India along with performance certificate from Central or State Government Power sector utilities, using the above system shall be submitted along with the bid offer.

Nitrogen Injection system should be a dedicated system for each oil filled transformer. It should have a Fire Extinguishing Cubicle (FEC) placed on a plinth at a distance of 5-10 m away from transformer / reactor or placed next to the firewall (if fire fighting wall exists). The FEC shall be connected to the top of transformer / reactor oil tank for depressurization of tank and to the oil pit (capacity is approximately equal to 10% of total volume of oil in transformer / reactor tank / or existing oil pit) from its bottom through oil pipes. The FEC should house a pressurized nitrogen cylinder (s) which is connected to the oil tank of transformer / reactor oil tank at bottom. The Transformer Conservator Isolation Valve (TCIV) is fitted between the conservator tank and Buchholz relay. Cable connections are to be provided from signal box to the control box in the control room, from control box to FEC and from TCIV to signal box. Detectors placed on the top of transformer / reactor tank are to be connected in parallel to the signal box by Fire survival cables. Control box is also to be connected to relay panel in control room for receiving system activation signals.

5.4.25.2 Activation of the system

The system shall work on the principle of Drain & stir. On activation, it shall drain a pre-determined quantity of oil from the tank top through drain valve to reduce the tank pressure, isolate conservator tank oil and inject nitrogen gas at high pressure from the bottom side of the tank through inlet valves to create stirring action and reduce the temperature of oil below flash point to extinguish the fire. On operation, the quantity of oil removed from the tank shall be such that adequate amount of oil shall remain to cover active part (i.e. core coil assembly).

Mal-functioning of the Nitrogen injection system could lead to interruption in power supply. The supplier shall ensure that the probabilities of chances of malfunctioning of the Nitrogen injection system are practically zero. To achieve this objective, the supplier shall plan out scheme of activating signals which should not be too complicated to make the system inoperative in case of actual need. The system shall be provided with automatic controls to prevent the explosion of transformers. Besides automatic control, remote electrical push button control at Control box and local manual control in the cubicle shall also be provided. The following electrical-signals shall be used for activating the system under prevention mode/fire extinguishing mode.

5.4.25.2.a Auto Mode

For prevention:

- Differential relay operation.
- Buchholz relay paralleled with pressure relief valve or RPRR (Rapid Pressure Rise Relay)
- Tripping of all circuit breakers (on HV & LV/IV side) associated transformer / reactor is the pre-requisite for activation of system.

For extinguishing

- Fire Detector
- Buchholz relay paralleled with pressure relief valve or RPRR (Rapid Pressure Rise Relay).

Tripping of all circuit breakers (on HV & LV/IV side) associated with transformer / reactor is the pre-requisite for activation of system.

5.4.25.2.b Manual Mode (Local / Remote)

Tripping of all circuit breakers (on HV & LV / IV side) associated with transformer / reactor is the pre-requisite for activation of system.

5.4.25.2.c Manual Mode (Mechanical)

- Tripping of all circuit breakers (on HV & LV / IV side) associated with transformer / reactor is the pre-requisite for activation of system.

The system shall be designed to be operated manually in case of failure of power supply to the system.

5.4.25.3 Operation

On receipt of all activating signals, the system shall drain - pre-determined volume of hot oil from the top of tank (i.e. top oil layer), through outlet valve, to reduce tank pressure by removing top oil and simultaneously injecting nitrogen gas at high pressure for stirring the oil at pre-fixed rate and thus bringing the temperature of top oil layer down. Transformer conservator isolation valve blocks the flow of oil from conservator tank in case of tank rupture / explosion or bushing bursting. Nitrogen occupies the space created by oil drained out and acts as an insulating layer over oil in the tank and thus preventing aggravation of fire.

- Electrical isolation of transformer shall be an essential pre-condition for activating the system, to avoid nitrogen injection in energized transformer.
- The system shall have provision of testing on live transformers to ensure healthiness at all times.
- The system shall have mechanical locking arrangement for nitrogen release system as well as oil drain to avoid unnecessary operation during maintenance and /or testing of the transformer and / or system.
- The system shall have provision to monitor nitrogen injection pressure as well as cylinder pressure.
- Pressure monitoring switch for back up protection for nitrogen release as redundancy to first signal of oil draining commencement for nitrogen release shall preferably be provided.
- System shall have individual mechanical release devices and provision for oil drain and nitrogen release to operate manually in case of operation DC supply failure.
- Nitrogen release scheme shall be designed in such a way that the nitrogen gas shall not enter the energized transformer tank even in case of passing / leakage of valve.

- Individual system component / equipment should operate on station DC voltage. AC-DC / DC-DC converter shall not be used for reliable operation.
- All outdoor panels / equipment shall be of IP-55 protection class.

5.4.25.4 System components:-

Nitrogen Injection system shall broadly consist of the following components. However, all other components which are necessary for fast, reliable and effective working of the system shall be deemed to be included in the scope of supply.

5.4.25.4.a CUBICLE (FEC):-

The Cubicle Frame shall be made of CRCA sheet of 3 mm (minimum) thick complete with the base frame, painted inside and outside with post office red colour (shade 538 of IS -5). It shall have hinged / hinged split doors fitted with high quality tamper proof lock. The doors, removable covers and panels shall be gasketed all round with neoprene gaskets. The degree of protection shall be IP55. The following items shall be provided in the Cubicle.

- Nitrogen gas cylinder with regulator and falling pressure electrical contact manometer.
- Oil drain pipe with mechanical quick drain valve.
- Electro mechanical control equipment for draining of oil of pre-determined volume and injecting regulated volume of nitrogen gas.
- Pressure monitoring switch for back-up protection for nitrogen release.
- Limit switches for monitoring of the system.
- Butterfly valve with flanges on the top of panel for connecting oil drain pipe and nitrogen injection pipes for transformer / reactors.
- Panel lighting (LED Type)
- Oil drain pipe extension of suitable sizes for connecting pipes to oil pit.
- Space heater.

5.4.25.4.b Under Ground Oil Storage Tank:-

Each transformer unit shall be provided with an underground oil storage tank. The oil storage tank shall have Non Corrosive, water proof, epoxy coated (from Inside) mild steel (minimum thickness 6 mm) to store drained-out oil on operation of NIFPS. The tank shall be painted from outside as per Clause no. 5.4.8. The total capacity of storage tank shall be at least 10% of transformer tank oil to avoid overflowing of oil considering that drained oil volume shall be around 10% of transformer tank oil. Necessary arrangement shall be made on underground storage tank so as to take out the drained oil from the tank for further processing and use. All the pipes and physical connections from transformer to oil pit shall be in the scope of contractor.

This storage tank shall be placed in the pit made up of brick walls with PCC (1:2:4) flooring with suitable cover plates to avoid ingress of rain water. The design of tank and pit shall be finalized during detailed engineering.

5.4.25.4.c Control box:-

Control box is to be placed in the control room for monitoring system operation, automatic control and remote operation. The following alarms, indications, switches, push buttons, audio signal etc. shall be provided.

- System Oil.
- TCIV open.
- Oil drain valve closed.
- Gas inlet valve closed
- TCIV closed
- Detector trip
- Buchholz relay trip
- Oil drain valve open
- Extinction in progress
- Cylinder pressure low
- Differential relay trip
- PRV / RPRR /OSR trip
- Transformer / reactor trip
- System out of service
- Fault in cable connecting fault detector
- Fault in cable connecting differential relay
- Fault in cable connecting Buchholz relay
- Fault in cable connecting PRV / RPRR / OSR
- Fault in cable connecting transformer reactor trip
- Fault in cable connecting TCIV
- Auto / Manual / Off
- Extinction release on / off
- Lamp test
- Visual / Audio alarm for AC supply fail
- Visual / Audio alarm for DC supply fail

As far as possible, the control box should be so devised that all the transformers and reactors or group thereof should be controlled from single spot.

5.4.25.4.d Transformer Conservator Isolation Valve:-

Transformer conservator isolation valve (TCIV) is to be fitted in the conservator pipe line, between conservator and buchholz relay, which shall operate for isolating the conservator during abnormal flow of oil due to rupture / explosion of tank or bursting of bushing. The valve shall not isolate conservator during normal flow of oil during filtration or filling or refilling, locking plates to be provided with handle for pad locking. It shall have proximity switch for remote alarm, indication with visual position indicator.

The TCIV should be of the best quality as malfunctioning of TCIV could lead to serious consequence. The closing of TCIV means stoppage of breathing of transformer / reactor. Locking plates shall be provided for pad locking.

5.4.25.4.e Detectors:-

The system shall be complete with adequate number of detectors (quartz bulb) fitted on the top cover of the transformer / reactor oil tank.

5.4.25.4.f Signal box:-

It shall be mounted away from transformer / reactor main tank, preferably near the transformer marshaling box, for terminating cable connections from TCIV & detectors and for further connection to the control box. The degree of protection shall be IP55.

5.4.25.4.g Cables:-

Fire survival cables (capable to withstand 750° C.) of 4 core x 1.5 sq. mm size for connection of detectors in parallel shall be used. The fire survival cable shall conform to BS 7629-1, BS 8434-1, BS 7629-1 and BS 5839-1, BS EN 50267-2-1 or relevant Indian standards.

Fire Retardant Low Smoke(FRLS) cable of adequate size shall be used for connection of signal box / marshaling box near transformer / reactor and FEC mounted near transformer/ reactor with control box mounted in control room.

Fire Retardant Low Smoke (FRLS) cable of 4 core x 1.5 sq. mm size shall be used for connection between control box to DC & AC supply source, FEC to AC supply source, signal box / marshaling box to transformer conservator isolation valve connection on transformer / reactor. Separate cables for AC supply & DC supply shall be used.

5.4.25.4.h Pipes:-

Pipes complete with connections, flanges, bends and tees etc. shall be supplied along with the system.

5.4.25.4.i Other items to be supplied:-

- a) Oil drain and nitrogen injection openings with gate valves on transformer / reactor tank at suitable locations.
- b) Flanges between Buchholz relay and conservator tank for fixing TCIV.
- c) Detector brackets on transformer / reactor tank top cover.
- d) Spare potential free contacts activating the system i.e. in differential relay, Bucholz relay. Pressure Relief Device / RPRR , Circuit breaker of transformer / reactor.
- e) Pipe connections between transformer / reactor and FEC and between FEC and oil pit required for collecting top oil.
- f) Cabling for detectors mounted on transformer / reactor top cover.
- g) Inter cabling between signal box, control box and FEC.
- h) Butterfly valves / Gate valves on oil drain pipe and nitrogen injection pipe which should be able to withstand full vacuum.
- i) Supports, signal box etc. which are to be painted with enameled paint.
- j) Any other item required for satisfactory operation of system.

5.4.25.5 Power supply:-

For Control Box: As per substation DC voltage i.e.220V, DC, 2 Wire.

For FEC Auxiliary: 230 V AC

5.4.25.6 Modification on the transformer:-

No modification on the transformer shall be allowed which affects its performance (i.e. efficiency, losses, heat dissipation ability etc.) safety, life etc. or its any other useful parameter. This requirement shall be of paramount importance and shall form the essence of the contract.

However, in any case, performance of transformer should not be affected in any manner by having Nitrogen Injection Fire Prevention Cum Extinguishing System (NIFPES) and the Contractor / Sub-Contractor shall give an undertaking to this effect. All pipes should be washed

/ rinsed with transformer oil. If any damage is done to the transformer and / or any connected equipment during installation, commissioning, full recovery therefore shall be effected from the Contractor / Sub-Contractor, of NIFPES system.

It shall be solely the responsibility of supplier / Sub-Contractor to install, carry out pre-commissioning tests & commission NIFPES at the mentioned Sub-Station in this specification, to the entire satisfaction of the OPTCL.

5.4.25.7 Interlocks:-

It shall be ensured that once the NIFPES gets activated manually or in auto mode, all the connected breakers shall not close until the system is actually put in OFF mode. Also PRV shall get closed only if all the connected breakers are open.

5.4.25.8 Tests:-

Supplier has to carry out the type test as per relevant IS/IEC. Specifically IP 55 on FEC or have to produce the report from NABL approved Lab.

Reports of all routine test conducted as per relevant IS/IEC standards in respect of various bought out items including test reports for degree of protection for FEC / control box / signal box shall be submitted by the supplier.

The supplier shall demonstrate the entire functional tests, associated with the following as Factory Acceptance Tests:

- FEC, Control Box
- Fire Detector
- Transformer Conservator Isolation Valve

The performance test of the complete system shall be carried out after erection of the system with transformer at site.

Detailed layout drawings, equipment drawing along with 4 sets of Operation and Maintenance manual along with soft copies (In CDs) shall be submitted by the supplier along with the consignment.

The guaranteed technical particulars for the offered system are indicated in Ann-IV. Any other particulars, considered necessary in addition to those listed in that Section may be furnished by the Bidder.

5.4.25.9 Supervision of Erection, Testing & Commissioning:- The erection, testing and commissioning of the Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES) at OPTCL site shall be carried out under direct supervision of the Service Engineer of NIFPES manufacturer(s). The Bidder shall furnish authorization letter(s) from such manufacturer(s) with their bid, as per the format given in **technical Annexure-XI**.

5.5 CENTRE OF GRAVITY:

The center of gravity of assembled transformers shall be as low and as near the vertical center line as possible. The transformer shall be stable with and without oil. The location of the center of gravity, relative to track shall be clearly marked in the out line drawing, accompanying bid.

6 INSPECTION AND TESTING:-

6.1 TESTING FACILITIES:

6.1.1 Bidders shall submit along with the bid, the details of testing facilities, available at their works for carrying out all the routine and type tests, as specified.

6.1.2 In case, the test facilities for any particular test are not available at the bidder's works, this shall be clearly brought out in the additional information schedule and proposed arrangement of carrying out that test shall be clearly indicated.

6.1.3 All the measuring systems, used for the tests have certified, traceable accuracy and are subjected to periodic calibration, according to the rules of 4.11 of ISO 9001[Ref-Cl.No.10 (Tests) of IEC-60076-1]

6.1.4 OPTCL at its discretion may use their own testing equipments or third party testing equipments such as Power Analyzer, Resistance meter etc during Routine test/Type test of the Transformers at the Bidder's Works. The test results of OPTCL/Third party instrument will be accepted for the purpose of the contract. During testing & inspection, of the Transformer, it shall be ensured to the Inspecting Officers that there must be direct connections from the secondary of the unit auxiliary testing transformer and from the secondaries of the testing instrument transformers to the power analyzer without any termination or any other parallel connection what so ever. The measuring instruments with connections should be positioned in such a manner that there shall be easy access to the above instruments / equipments at the time of testing by Inspecting Officers.

6.2 GENERAL:

Inspection and testing shall be carried out on the transformer as detailed here and generally in accordance with IEC 76 and IS: 2026. The Purchaser shall have the right to reject a transformer, if test results do not comply with the standards/values, specified and informations/data, given in the schedules. For the purpose of determining when type tests are required, a transformer is considered to be representative of others only if it is fully identical in design, rating and construction.

Before and after acceptance testing, samples of oil shall be taken from the transformer and analysed for dissolved gases, using the procedures, specified in IEC Publications 567 and 599. Results of the analysis of gases, dissolved in the oil shall be immediately submitted to the Purchaser and included in the Acceptance Test Report. On completion of acceptance testing, the Supplier shall provide the Purchaser with seven copies of the complete test reports.

Full details of the proposed methods of testing including connection diagrams shall be submitted by the Supplier for approval at least one month before testing. All tests will be witnessed by the Purchaser.

The Purchaser shall have full access at all times to the works and all other places of manufacture of the transformers. The Supplier shall report to the Purchaser monthly or other period, as agreed between the two on manufacturing progress. The Supplier shall give the Purchaser on award of contract a complete manufacturing inspection program to allow the Purchaser, at its discretion, to inspect at all stages of transformer manufacture.

6.3 STAGE INSPECTION:

Stage inspection on core, windings, tank, OLTC and all other accessories etc. will be carried out by the Supplier in the presence of OPTCL's representative on free of cost to OPTCL before tanking of the core and windings. All the measurements will be taken on the above components, so as to ensure their compliance to the above Specification and the Guaranteed Technical Particulars. The possible routine tests like measurement of D.C. resistance, no load current and no load loss, determination of Knee Point Voltage, specific core loss, tank tests

etc. will be conducted during stage inspection. For determination of number of turns in the windings, the manufacturer shall provide dummy core, so as to accommodate the winding and determining the ratio between the unknown No. of turns (winding) and known No. of turns, wrapped around the winding. The purchaser's representative at his discretion may choose small strips of core for testing at CPRI. Also, a small piece of conductor for each type of winding shall be made available to the purchaser's representative. Apart from the above, the purchaser at his discretion reserves the right to carry out the stage inspection at other stages also, for which advance intimation shall be given and all necessary co-operation shall be rendered by the manufacturer. The Supplier shall give at least three weeks notice in advance for deputing Inspecting Officer(s) to their works. Type Tests and routine tests on the transformer shall be conducted only if the stage inspection report and the pre-tanking tests are found to be in order as per this Specification.

6.4 **FINAL INSPECTION & TESTING:-**

Before offering for final inspection, type tests and routine tests, the Supplier shall furnish the factory test results (except dielectric tests) of the offered transformer(s) along with list of equipments/meters/instruments, to be used, during testing (both routine and type tests) as per Annex of this Specification along with calibration certificates of measuring instruments. The Purchaser may direct the Supplier for use of better equipments/meters during inspection/testing. The calibration of all the meters/instruments to be used during testing should have been done in Government approved laboratory.

6.4.1 **TYPE TESTS & SPECIAL TESTS:**

The followings shall be regarded as type tests and shall be carried out in presence of Purchaser's representative on one unit out of the lot at the discretion of the purchaser. The charges for conducting each type test shall be quoted in the relevant price schedule.

(a) **Temperature Rise Test:-**

Test of temperature rise (IEC Publ. 76.2): This test shall be carried out on the tap giving the worst combination of loading on the transformer windings. The transformer shall be tested by feeding the tested losses or quoted losses, whichever is higher. The supplier, before carrying out such tests, shall submit detailed calculations, showing the alternatives possible on various taps and for the two different ratings (ONAN/ONAF) of the transformer and shall recommend the combination that results in highest temperature rise for the test. Temperature rise shall be measured at ONAN&ONAF ratings. Gas chromatographic analysis on oil shall be carried out before and after the temperature rise test and the results recorded in the test report. Sampling shall be in accordance with IEC 60567. For evaluation of the gas analysis in temperature rise test, the procedure shall be as per IS: 9434 (based on IEC: 60567) and the results will be interpreted as per IS: 10593 (based on IEC-60599). These results shall be treated as reference during future maintenance of Transformers. The calibration of OTI and WTI shall be done by transformer manufacturer and these calibrated OTI, WTI shall be used during testing of the transformer. The Sr.No. of WTI and OTI should be recorded during testing of the Transformer and only these OTI & WTI shall be supplied with the Transformer.

N.B.:- The purchaser at his discretion may opt for conducting Temperature rise test on all transformers or more than one transformer of the lot, by paying extra

(b) **Measurement of Zero Sequence Impedance:**

Measurement of open circuit and short circuit zero sequence impedances of the primary and secondary windings

(c) **Auxiliary Power Consumption:**

Measurement of power taken by fan and oil pump motors.

(d) **Vacuum Test:**

The transformer tank shall be subject to full vacuum and tested at an internal pressure of 3.33 KN/Sq.m. (25 Torr) for one hour. The permanent deflection of plates after the vacuum has been released shall not exceed the values, specified below and the performance of the transformers shall not be affected in any way.

<u>Horizontal length of flat plate (mm.)</u>	<u>Permanent deflection (mm.)</u>
Upto and including 750	5.0
751 to 1250	6.5
1251 to 1750	8.0
1751 to 2000	9.5
2001 to 2250	11.0
2251 to 2500	12.5
2501 to 3000	16.0
Above 3000	19.0

The purchaser at his discretion may opt for vacuum test for the tanks of all the transformers, by paying extra cost to the supplier at their quoted price(s).

(e) **Pressure Test:**

One transformer tank of each size together with its radiators, conservator vessel and other fittings shall be subjected to a pressure, corresponding to twice the normal head of oil or to the normal pressure plus 35KN/Sq.m. whichever is lower. The applied pressure shall be measured at the base of the tank and maintained for one hour. The permanent deflection of flat plates after excess pressure has been released shall not exceed the values, specified in (d).

The purchaser at his discretion may opt for pressure test for the tanks of all the transformers, by paying extra cost to the supplier at their quoted price(s).

(f) **IP-55 Test:**

One cooler control cabinet and OLTC cabinet for each type of transformer shall be tested for IP-55 protection in accordance with IS-2147/IEC-529.

(g) **Dynamic Short Circuit test:-** If desired by Purchaser, the 'Dynamic Short Circuit Test' shall be conducted on any unit randomly selected out of the lot, at CPRI. The firm needs to quote price for above testing and transportation/other charges separately in the price bid. The firm will make all necessary arrangements for above Test. The delivery period of the said transformer is to be extended accordingly.

N.B.: -1) The transformer offered or higher capacity (Both MVA & voltage rating) should have been tested as per the above type tests [6.4.1(a) to (f)] and chopped Lightning Impulse tests, as prescribed in this specification in presence of authorized representative(s) of Government Utilities. The bidder shall furnish four sets of such type & special test reports including Lightning Impulse Test Report (chopped Impulse) (indicating therein the type and design details) along-with the offer without which the tender may be rejected. These tests should have been conducted not before five years from the date of opening of bid.

2) Test reports towards all type tests as per IEC-214: 1976 and BS: 4571:1970 for the offered OLTC along with approved drawings to be submitted. Purchaser at his discretion may insist on repetition of some or all the applicable type tests as per above IEC & BS, at supplier's cost, if any discrepancy/deviation/deficiency is noticed in the type test reports.

3) If it is desired by the Purchaser that the 'Short Circuit Test' at CPRI, Bangalore/Bhopal needs to be conducted on any unit, randomly selected for 'Short Circuit Test', the firm will make all necessary arrangements for above Test and expenditure on above will be reimbursed by OPTCL on actual basis.

6.4.2. ROUTINE TESTS:-

The followings shall be regarded as routine tests and shall be conducted on each transformer in the presence of purchaser's representative. No extra cost shall be paid for these tests.

- (a) **Measurement of winding resistance.**
- (b) **Voltage- ratio measurement and check of vector group.**
- (c) **Measurement of capacitance and dielectric dissipation factor.** (Before and after the series of dielectric tests). The capacitance test shall be carried out with the help of ampere turn bridge method on fully assembled transformer (filled with oil) to determine capacitance and tan delta between winding and earth as under:
 - i) HV winding with LV winding and tank earthed.
 - ii) LV winding with HV winding and tank earthed.
 - iii) HV and LV windings with tank earthed.
- (d) **Measurement of Insulation Resistance and Determination of Polarisation Index:**
This measurement shall be made with ten minute and one minute IR tests and should be repeated after all other tests.
- (e) **Impulse Test:**
 - (i) Full Wave Impulse Voltage withstand Test: - The test voltage shall be applied to each line. The applied voltage shall be the relevant lightning impulse voltage, specified in the schedule of requirements. This test shall be applied to each HV & LV Phase terminal.
 - (ii) Chopped wave impulse voltage withstand test: - The test voltage shall be applied to each line terminal. The applied voltage shall be 100% of the specified relevant lightning impulse voltage. This test shall be applied to each HV & LV Phase terminal.
 - (iii) An impulse test on transformer neutrals as per IEC-76-3 Clause 12.3.2 shall be carried out.

Tests (i) and (ii) shall be combined in a single sequence as follows for each line terminal:-

- 1 One reduced full impulse (calibration).
- 2 One 100% full impulse.
- 3 One or more reduced chopped impulse(s).
- 4 Two 100% chopped impulses.
- 5 Two 100% full impulses.

The sequence for test (iii) shall be as follows:-

2. One reduced full impulse at 50-75% of full level.
3. Three 100% full impulses.

In carrying out the above tests, the two extreme taps and another tap to be selected by the purchaser with each of the three phases, being tested on a different tap.

- (f) **Separate source voltage withstand test/Applied Voltage test:-**
The test shall be conducted as per Cl. No- 10 of IEC-76-3; 2013 or its latest amendments. The applied voltage shall be the specified/relevant power frequency voltage.
- (g) **Line terminal AC withstand voltage Test(LTAC):-**
The test shall be conducted as per Cl. No- 10 of IEC-76-3; 2013 or its latest amendments. The firm shall have to submit the over-potential diagram with details of calculation and explanation alongwith the offer for inspection.

(h) Induced voltage Test with PD measurement(IVPD):-

The test shall be conducted as per Cl. No- 10 of IEC-76-3; 2013 or its latest amendments. This test shall be carried out using a broad band instrument. The apparent charge (q) shall be in accordance with IEC 76-3.

(i) Measurement of Impedance voltage on all taps.

(j) Measurement of the load loss at normal tap and extreme taps. (To be carried out by three wattmeter method with low power factor wattmeters at full rated current). The voltage, current, wattage, power factor and frequency meter reading in individual phases (u, v, w) shall be recorded during testing and shall be reflected in the test report.

(k) Measurement of no load loss, no load current and determination of knee point voltage:-

This test is to be carried out with three wattmeter method by using low power factor wattmeters, three power factor meters, phase sequence meters, three low range ammeters and three each of average value and RMS value voltmeters. The test voltage from 10% voltage to 121% voltage shall be applied and currents, voltages (Average value and RMS value), wattmeters, power factor and frequency meter readings in all the three phases are to be recorded during the test. A saturation characteristic curve between the no load voltage (rms) vs. Measured current is to be plotted on the graph sheet, so as to determine the voltage at which increasing voltage by 10% (ten percent), the excitation current shall not increase by more than 50% (fifty percent). The knee point voltage as per specification will be complied if the excitation current at 121% of rated no load voltage shall not exceed by not more than 50% over the excitation current, obtained at 110% of the rated no load voltage. During the no load test, supplier's own generator set shall be used for feeding the above no load voltages at rated frequency. If the applied frequency is greater than the rated frequency, then proportionate voltage as per the rated frequency will be fed during the above no load test and following frequency correction formula along with the formula, stipulated at Clause No 16.5 of IS:2026 (Part-I) shall be used.

$$K = 0.5 [(f/f_1) + (f/f_1)^2]$$

Where f = rated frequency and f_1 = applied frequency.

For Example: -If measured loss = X Watts, correction factor due to r.m.s. and average voltage as per ISS = K_1 and frequency correction factor = K as per above formula, then corrected loss will be calculated as = measured loss • K_1 • K .

If applied frequency is less than the rated frequency, no frequency correction formula will be applied. Rated voltage at that frequency will be fed during the no load test.

- N.B.:- 1) If power analyser is to be used for determination of no load loss, no load current, Impedance Voltage, short circuit losses etc., its manual of operation, calibration certificate and the relevant standard for its use shall be produced prior to one month of test offer for studying its feasibility and reliability.
- 2) C.Ts. and P.Ts. of accuracy class 0.2 or better as per IS: 2705 are to be used during determination of no load losses and short circuit losses which involves financial implication. The calibration certificates of these C.Ts. & P.Ts. from independent Government approved laboratory shall be produced along with the traceability while offering for inspection. The accuracy class of reference standard C.T. & P.T. used for

determination of the errors of the above C.Ts. & P.Ts. shall be 0.05 or better as per Clause No.2.9 of IS : 1248 (Part-9).

- (l) **Measurement of Harmonic level** (1st to 24th Harmonic) in no-load current in all three phases at 90%, 100% and 110% of no-load voltage. The magnitudes of no load currents for all the three phases at the above excitation levels shall also be recorded and reflected in the test report for measurement of harmonic levels.
- (m) **Measurement of capacitance and dielectric dissipation factor [Repeat © above).**
- (n) **Measurement of polarisation Index (Repeat (d) above).**
- (o) **Tests on no-load tap-changer (as per IS: 2026)**
- (p) **Transformer noise measurement:-**
Noise level measurement in accordance with IEC Publication 551 using a precision sound level meter conforming to IEC Publication 651.
- (q) **Auxiliary circuit tests:-**
All auxiliary circuits shall be subjected to application of 2KV (rms) withstand test voltage. Correct operation of all auxiliary control circuits will be tested.
- (r) **Core earth test:-**
A test voltage of 2KV shall be applied between the core and the earthed structural steel work to prove that the core is earthed through the removable link, at one point only.
- (s) **Oil BDV test.**
- (t) **Measurement of Neutral current** during load loss test which shall not be more than 2% of the rated current of the transformer.
- (u) **Magnetic balance test.**
- (v) **DGA test before and after all the tests.**
- (w) **Oil Leakage test on transformer tank:**
- (X) **Any other test suggested by the purchaser at the time of final Inspection.**
All tanks and oil-filled compartments shall be tested for oil tightness by completely filling with oil of viscosity, not greater than that of insulating oil, conforming to IS: 335 at the ambient temperature and applying a pressure, equal to the normal pressure plus 35KN/Sq.m., measured at the base of the tank. This pressure shall be maintained for a period of not less than 12 hours, during which time, no leakage shall occur. Bidder shall arrange for witnessing the leakage test of each tank.
- (x) **Pressure Relief Device Test:**
The pressure relief device of each size shall be subjected to increasing oil pressure. It shall operate before reaching the test pressure, specified at Cl.No.5.4.4 of this specification. The operating pressure shall be recorded. The device shall seal off after the excess pressure has been relieved. The following functional checks shall be conducted as acceptance tests on each of the pressure relief devices.
 - i) Air- Pressure Test.
 - ii) Liquid Pressure Test.
 - iii) Leakage Test.
 - iv) Contact Test.
 - v) Di-electric Test.
- (y) **Frequency Response Analysis (FRA) test:-**
The supplier shall conduct the test at the time of final testing of the transformer and record the amplitude and phase shift results on CDs for subsequent analysis. The test shall also be carried out by the supplier before commissioning at site and compare this result with the results, obtained before dispatching the transformer and submit the report along with the above results in CDs for future analysis. Each transformer is subjected to FRA test and frequency responses, recorded as above and analysed in any of the following:-
 - i) Shift in the response of the winding.
 - ii) Differences between the responses of all the phases of the transformer.
- (z) **Dew point measurement test before dispatching:-**

Positive Gas pressure is generally maintained at 0.175 Kg/m² during transportation and during storage. To ensure the same, dew point measurement shall also be carried out at site. The procedure and acceptance limits are as per CBIP Manual Pub. No.295 (2006) or latest.

Besides the above, the OLTC manufacturer shall conduct the following routine tests fully in compliance with IEC:60214 on every unit, as given below, for which no extra cost will be payable by OPTCL.OPTCL may authorize its representative(s) for witnessing the said routine tests on any or some or all the OLTCs for the Transformers as per contract. It is the responsibility of the supplier to offer the OLTCs for following routine tests, to be conducted at the works of OLTC Manufacturer.

SL. No.	IEC reference	Test Description	Acceptance level
01	60214 I. No.5.3.1	Mechanical Endurance Test	Minimum 1000 operations
02	60214 Cl. No.5.3.2	Sequence Test	Switching operation with timing less than 50m-sec.
03.	60214 Cl. No.5.3.4	Pressure Test	10PSI(0.7kg/sq.cm.) for 8hours at room temperature.
04.	60214 Cl. No.5.3.4	Vacuum Test	Vaccum level, as guaranteed by Manufacturer
05.	Special Test	Gas tightness Test,	Helium based or any other mutually agreed method
06.	60214 Cl. No.5.3.4	Auxiliary Circuits Insulation Test	Should withstand 2kV relative to earth for 1 Minute.
07	Special Test	Contact resistance	< 2 milli Ohms.
08	Special Test	Physical & Dimensional Checks.	As per approved drawing.

All the relevant Test reports shall be submitted for OPTCL's approval.

N: B- The Purchaser reserves the right to have the tests carried out on the transformer(s) at his own cost in an independent Government approved laboratory to ensure that the Transformer complies with the requirements of this Specification.

6.4.3 CHALLENGE TEST :

CLAUSE SHALL BE DELETED AND ADDED IN TENDER SPEC.

~~6.4.3(a) Any participating bidder can challenge whether the supplier has supplied the transformer as per the purchase order / tender technical specification or not. Challenge testing can be done on any one transformer of a supplier, out of the ordered quantity, during guarantee period from the date of dispatch instruction but before commissioning at site.~~

~~6.4.3(b) The challenger shall have to make written request to the Senior General Manager(CPC) for challenge testing giving details of manufacturer, purchase order and rating of transformer supplied by the party challenged along with the following :~~

~~i) Demand draft / Banker's cheque in favour of DDO, Head Quarter, OPTCL, Bhubaneswar amounting to Rs. 5,00,000/- (Rs. Five lacs only) towards challenge testing (non refundable).~~

~~ii) Demand draft / Banker's cheque in favour of the party challenged amounting to rs. 1,00,000/- (Rs. One lac only) to meet their contingencies which shall be handed over to the party challenged at the time of sealing of the selected transformer for testing.~~

~~iii) Confirmation of test date from the test lab (CPRI / ERDA). The test date shall not be later than 6 months from the date of submission of application for challenge testing. The test date at CPRI / ERDA is to be obtained by the challenger by deposit the required test charges.~~

~~6.4.3(c) All the expenses mentioned below during challenge testing shall be incurred by the challenger:~~

~~i) Dismantling (if the transformer is already installed) and loading at site.~~

~~ii) To & Fro transportation (including insurance) charges from site to testing platform and back to site (anywhere in ODISHA). The transformer lifted from site shall be fully insured against all the risk for the period starting from lifting of the transformer from the site till return back to site (anywhere in ODISHA) after testing.~~

~~iii) Unloading and assembly at testing platform.~~

~~iv) Dismantling after testing & loading from testing platform.~~

~~v) Unloading at site.~~

~~vi) Taxes, duties, levies, etc., during transportation of transformer from site to test lab & back to site, if any.~~

~~vii) Re installation charges of transformer at site, in case the selected transformer had already been installed.~~

~~viii) Testing fee / charges demanded by CPRI / ERDA.~~

~~All the arrangements in regards to above activities shall be exclusively made by the challenger.~~

~~6.4.3(d) The challenger shall intimate the proposed date of lifting of selected transformer to the Senior General Manager(CPC),OPTCL,Bhubaneswar,ODISHA at least, 15 days in advance, along with the following:~~

~~i) Bank guarantee, in acceptable form of an amount equivalent to F.O.R. Destination cost of the selected transformer including entry tax as per purchase order, in lieu of security of selected transformer for challenge testing. The Bank Guarantee shall be valid initially for one year.~~

~~ii) Insurance cover for full value of transformer against all the risk for the period starting from proposed date for lifting of the transformer from site till return back to site (anywhere in ODISHA) after testing.~~

~~Thereafter, permission for lifting of the transformer shall be granted to the challenger. The challenger shall also intimate the proposed date of lifting of selected transformer simultaneously to the party challenged.~~

~~6.4.3(e) The selected sample shall be lifted after sealing the same in the presence of~~

~~authorized representative (s) of the challenger, the party challenged and OPTCL within 45 days prior to the date of proposed testing. If the party challenged fails to depute its representative to seal / witness the lifting of the proposed transformer on the intimated date, the transformer shall be lifted for testing without waiting for their representative for sealing / witness and the absence of their representative will be treated as their consent about sealing as well as challenge testing. The sealed transformer shall be transported to CPRI / ERDA for testing in order to proceed as per reserved testing schedule. Both party i.e. challenger, the party challenged may accompany the truck during transportation of selected sample from site to CPRI / ERDA and back.~~

~~6.4.3(f) The challenger, the party challenged and OPTCL shall witness the test. If any party i.e. challenger and / or the party challenged and / or OPTCL fails to attend / witness the testing, the sample shall be tested in their absence and all the parties have to accept the test results whatsoever.~~

~~6.4.3(g) The challenge testing would cover the following tests:-~~

- ~~a) — Measurement of No load losses (including confirmation on requirement of minimum knee point voltage as per OPTCL's Technical Specification).~~
- ~~b) — Measurement of load losses at rated full (100%) load at principal tap duly converted to 75 deg.C winding temperature.~~
- ~~c) — Temperature rise test.~~

~~All the tests shall be conducted in above mentioned sequence.~~

~~6.4.3(h) If all the test results conform to the specification, action shall be taken as detailed below:~~

- ~~a) — The challenger will not be reimbursed the expenses incurred by him for challenge testing of the transformer.~~
- ~~b) — Since the challenge testing may take about 8 month's period for which the transformer may not be in operation. In such case, the actual performance guarantee of the transformer will be available for lesser period than prescribed performance period i.e. 36 months from the date of receipt or 30 months from the date of commissioning whichever is earlier, as per contract. Therefore, after expiry of contractual performance guarantee period of the transformer, the party challenged (Transformer manufacturer) shall have to further guarantee the transformer equivalent to the period starting from the date of application for challenge testing till return back to site after testing. For this, the party challenged shall have to furnish bank guarantee equivalent to 10% of the cost of transformer towards performance for the period as stated above.~~
- ~~c) — The Bank Guarantee, equivalent to the cost of transformer furnished in lieu to security, will be released on receipt of certificate by the consignee / site in charge regarding receipt of the transformer complete with all fittings and accessories anywhere in Rajasthan to the challenger after recovery of re-installation charges etc, if any.~~

~~6.4.3(i) If any of the test results does not conform to the specification, action shall be taken as detailed below:~~

- ~~a) — The party challenged shall be declared as unsuccessful manufacturer and~~

~~would be debarred from participating in all future tenders of power transformers for the period of 5 years. Further, the order for balance quantity under that particular order shall be cancelled.~~

~~b) — The party challenged shall have to reimburse all the expenses as detailed at Clause No. 6.4.3(e) incurred by the challenger on challenge testing directly to the challenger on furnishing requisite documents towards the expenses incurred. The party challenged shall also have to reimburse Rs. 5,00,000/- (Rs. One lac only) to the challenger which had been incurred by the challenger as detailed at Clause No. 3.40.2 above.~~

~~e) — If the losses are found beyond guaranteed value then the penalty towards excess losses shall be recovered at twice the rate prescribed at Clause No. 5.2.2 of Specification for each supplied transformers in this order.~~

~~d) — If the transformer does not conform to the specification in temperature rise test, penalty @ 5% of F.O.R. Destination cost (including entry tax) of all the transformers supplied in that particular order till date shall be recovered.~~

~~e) — Any type of recoveries arising out due to challenge testing shall be recovered from the financial hold of the party challenged available with the OPTCL in any form in any order placed by the OPTCL.~~

~~f) — The Bank Guarantee(s) of the party challenged available with the Nigam against the purchase order shall be released after successful completion of performance guarantee period (including extended period as at Clause No. 3.40.8(b)) and recovery of all dues including the charges due to be reimbursed to the challenger.~~

6.4.4 **TESTS ON SITE:-**

The following site tests shall be performed on all units:-

- (a) General mechanical checks.
- (b) Core and winding insulation tests (Earth fault check on arrival at site).
- (c) Ratio and HV magnetisation current tests.
- (d) Vector group check.
- (e) Motors - Overload protection tests.
- (f) Motor pumps and motor/fans - Direction of rotation check for correct flow.
- (g) Buchholz device tests.
- (h) Silicagel breather check.
- (i) Temperature instrument calibration and tests.
- (j) Operational tests on tap change equipment.
- (k) Electric strength tests on insulating oil.
- (l) Bushing tests.
- (m) Impedance voltage at highest, rated and lowest voltage taps.
- (n) Zero sequence impedance at rated voltage tap.
- (o) DC resistance at all voltage taps.
- (p) Correct operation of all C.Ts
- (q) On-load tests.

7.0 **TEST REPORTS:-**

- (a) Six (6) sets of certified test reports and oscillograms shall be submitted for approval prior to the despatch of the equipment. The equipment shall be despatched only when all the required type and routine tests have been carried out and test reports have been approved by the Purchaser.
- (b) Each test report shall contain the following informations:-

- (i) Complete identification, date, including serial number of the transformer.
- (ii) Method of application, where applied, duration and interpretation of test results for each test.
- (c) Four (4) copies of the test reports for the tests carried out on the ancillary apparatus be furnished to the Purchaser for approval prior to despatch.
- (d) All auxiliary equipments/accessories shall be tested as per the relevant standards for the tests, as mentioned in this Specification. Test Certificates for the same shall be submitted to the Purchaser in four copies for scrutiny and record.

8.0 **LIST OF TRANSFORMER ACCESSORIES AND TEST CERTIFICATES REQUIRED FOR THEM:-**

Before offering for stage inspection of the Transformer, the supplier shall have to furnish the test certificates for the Transformer accessories, as enumerated below, wherever required.

<u>Sl. No.</u>	<u>Accessory Standard</u>	<u>Ref.</u>	<u>Test Certificates required.</u>
1..	Condenser Bushing	IS-2099	1. Appearance, construction and dimensional check. 2. Test for leakage of internal filling at a pressure of 1.Kg/Cm ² for 12h 3. Insulation resistance measurement with 2 KV megger. 4 Dry power frequency voltage withstand test. 5. Dry power frequency voltage withstand test for test tap insulation. 6. Partial discharge measurement upto 1.5UN/ 1.732KV 7. Measurement of tan delta and capacitance.
2.	Bushings.	IS-2099	1. Appearance, construction and dimensional check. 2. Insulation resistance measurement with 2 KV megger. 3. Dry power frequency voltage withstand test.
3.	OLTC	IS-8468	1. Oil tightness test for the diverter switch oil chamber at oil pressure of 0.5 Kg/Cm ² at 100 degree C for 1 h. 2. Mechanical operation test. 3. Operation sequence measurement. 4. Insulation resistance measurement using 2 KV Megger. 5. Power frequency voltage withstand test on diverter switch to earth and between even and odd contacts 6. Power frequency voltage withstand test on tap selector between maximum and minimum taps, between phases and supporting frames, between phases. 7. Operation test of complete tap changer. 8. Operation and dielectric test of driving mechanism. & other tests, as stipulated at Cl. No.6.4.2 of this Specification.
4.	Winding temperature indicator.		1 Calibration test. 2 Dielectric test at 2 KV for one minute 3 Accuracy test for indication and switch setting scales. 4 Test for adjustability of switch setting. 5 Test for switch rating. 6 Measurement of temperature rise with respect to the heater coil current.
5.	Oil temperature		1 Calibration test 2 Dielectric test of 2 KV for one minute.

	indicator.		3 Accuracy test for indication and switch setting scales. 4. Test for adjustability of switch setting. 5 Test for switch rating.
6.	Pressure Relief Valve.		1 Functional test with compressed air to check bursting, pressure indication, flag operation and switch operation. 2. Dielectric tests at 2 KV for one minute. 3. Switch contact testing at 5A, 240V AC.
7.	Cooling fan	IS: 2312	1. Insulation resistance measurement. 2. Dielectric test at 2 KV between winding and body for 1 minute. 3. Operation check. 4. Appearance, construction and Dimensional check.
8.	Buchholz ` Relay.	IS-3637	1. Leak test with transformer oil at a pressure of 3 Kg. /Cm ² for 30 minutes at ambient temperature for relay casing. 2. Insulation resistance measurement with 500 V Megger. 3. Dielectric test at 2 KV for 1 minute. 4. Elements' test at 1.75 Kg/ Cm ² for 15 minute using transformer oil at ambient temperature. 5. Loss of oil and surge test. 6. Gas volume test. 7. Mechanical strength test. 8. Velocity calibration test. 9. Appearance, construction and dimensional check.
9.	Oil level Indicators.		1 Test for oil levels. 2 Switch operations for low level alarm. 3 Switch contact test at 5A, 240V, A.C. 4 Dielectric tests at 2 KV for 1 minute 5 Appearance, construction and dimensional check.
10.	Pressed Steel Radiators.		1. Air pressure test at 2 Kg/ Cm ² under water for 15 minutes. 2. Appearance, construction and dimensional check.
11.	OLTC		1 Appearance, construction and Dimensional check.
	Control Cubicle/cooler control cubicle.		2. Electrical operation. 3. Insulation resistance measurement using 500 V megger at ambient temperature. 4. Dielectric test at 2 KV for 1 minute.
12.	Current Transformer	IS-2705	1. Appearance, construction and dimensional check. 2. Polarity check. 3. Measurement of insulation resistance. 4. High voltage power frequency test. 5. Determination of ratio error and phase angle of measuring and protection CTS. 6. Determination of turns ratio error for PS Class CTS. 7. Inter-turn insulation withstand test. 8. Excitation current characteristic test. 9. Secondary winding resistance measurement. 10. Knee-point voltage measurement for PS Class CT.

9.0 INSPECTION:-

9.1 GENERAL:-

- (i) The purchaser shall have access at all times to the works and all other places of manufacture where the transformer is being manufactured and the supplier shall provide all facilities for unrestricted inspection of the supplier's works, raw materials, manufacture of all the accessories and for conducting necessary tests, as detailed herein.
- (ii) The supplier shall keep the purchaser informed in advance of the time of starting and of the progress of the manufacture of the equipment in its various stages so that arrangements could be made for inspection.
- (iii) No material shall be despatched from its point of manufacture unless the material has been satisfactorily inspected and tested.
- (iv) The acceptance of the equipment shall in no way relieve the supplier of his responsibility for meeting all the requirements of this specification and shall not prevent subsequent rejection of such equipment, if found to be defective later.

9.2 **INSPECTION PROGRAMME:-**

- (a) The supplier shall chalk out a detailed inspection and testing programme for manufacturing activities for the various components. An indicative programme of inspection as envisaged by the purchase is given below. This is not however intended to form a comprehensive programme, as it is supplier's responsibility to draw up and carry out such a programme, duly approved by the Purchaser. Stage inspection on core and winding will be carried out before tanking of core. For this, the supplier shall give atleast three weeks notice in advance. **The purchaser reserves the right to carry out the stage inspection, final inspection & testing by a third party.**
- (b) Additional tests, if required, are deemed to be included in the scope of work.
- (c) Stages of inspection and purchaser's participation would be defined and tied up at the time of award of contract within 15 days of issue of the Purchase order.
- (d) The supplier shall arrange all his tests in such a fashion that the inspection and testing shall not exceed 5 (five) days for the above transformer.
- (e) On site testing, if any discrepancies will occur, the supplier will be asked immediately for its rectification and the supplier shall depute his representative for rectification without any delay.
- (f) At the time of final inspection, the supplier shall identify each & every item/accessories of the particular Transformer under testing. Unless all items are identified, the manufactures will not be treated as complete. Serial No. of bushings, Tap-changer, WTI, OTI and other details shall be entered into the Test reports to ensure that these items are not being applied to the subsequent Transformer units while testing. Various tests as per the specification shall be performed in the presence of OPTCL Engineers or when the inspection waiver has been given, in such a case, the testing as per the specification shall be done at the manufacturers works and same should be confirmed by documentary evidence by way of Test Certificate, which shall be got approved by OPTCL.
- (g) In case, for any reason(s), inspection is not completed or the equipment is not found to be complete with all accessories as per confirmation, given with the inspection call, the purchaser reserves the right to recover the complete cost of deputation of inspection team to the works of the manufacturer.
- (h) The supplier shall submit the test certificates of the bought-out items and Raw materials at the time of the routine testing of the fully assembled equipments.
- (i) It may be noted that " No change in any accessory or associated equipment after passing all the tests successfully shall be allowed and if this is subsequently detected, it shall be binding on the supplier to replace with the same item with which the initial tests were conducted at his works, failing which the entire test shall become null & void. The purchaser at his discretion may consider for rejection of the units, thus supplied. The entire cost for replacement of such rejected units, thus supplied and for repeating acceptance tests shall be borne by the suppliers.

9.2.1 **TANK AND CONSERVATOR:-**

- (a) Certification of chemical analysis and material test of plates.
- (b) Welder's qualification and welding procedure.
- (c) Testing of electrodes for quality of base materials and coatings.
- (d) Inspection of major weld preparation.
- (e) Crack detection of major strength weld seams by dye penetration test.
- (f) Measurement of film thickness of:
 - (i) Oil insoluble varnish.
 - (ii) Zinc chromate paint.
 - (iii) Finished coat.
- (g) Check correct dimensions between wheels, demonstrate turning of wheels through 90 degree and further dimensional check.
- (h) Check for physical properties of materials for lifting lugs, jacking pads etc. All load bearing welds including lifting lug welds shall be subjected to N.D.T.
- (i) Leakage test of the conservator.
- (j) Certification of all test results.

9.2.2 **CORE:**

- (a) Sample testing of core material for checking specific loss, bend properties, magnetisation characteristics and thickness.
- (b) Check on quality of varnish, if used on the stampings.
 - (i) Measurement of thickness and hardness of varnish on stamping.
 - (ii) Solvent resistance test to check that varnish does not react in hot oil.
 - (iii) Check overall quality of varnish by sampling to ensure uniform shining colour, no bare spot, no over-burnt varnish layer and no bubbles on varnished surface.
- (c) Check on the amount of burrs.
- (d) Bow-check on stampings.
- (e) Check for overlapping of stampings, corners of the sheets are to be apart.
- (f) Visual and dimensional check during assembly stage.
- (g) Check for interlaminar insulation between core sections, before and after pressing.
- (h) Check on completed core for measurement of iron loss, determination of knee point voltage and check for any hot spot by exciting the core so as to induce the designed value of the flux density in the core.
- (i) Visual and dimensional checks for straightness and roundness of core, thickness of limbs and suitability of clamps.
- (j) High voltage test (2 KV for one minute) between core, its bolts and clamps.
- (k) Certification of all test result.

9.2.3 **INSULATING MATERIAL.**

- (a) Sampling check for physical properties of materials.
- (b) Check for dielectric strength.
- (c) Visual and dimensional check.
- (d) Check for the reaction of hot oil on insulating materials.
- (e) Dimensional stability test at high temperature for insulating material.
- (f) Tracking resistance test on insulating materials.
- (g) Certification of all tests results.

9.2.4 **WINDING:**

- (a) Sample check on winding conductor for mechanical properties and electrical conductivity.
- (b) Check insulating distance between high voltage connection, cables and earth and other live parts.
- (c) Check insulating distance between low voltage connection and earth and other parts.

- (d) Check for proper cleanliness and absence of dust.
- (e) Visual dimensional checks on conductor for scratches, dent marks etc.
- (f) Sample check on insulating paper for PH value, electric strength.
- (g) Check for the bonding of insulating paper on the conductor.
- (h) Check for absence of short circuit between parallel strands.
- (i) Check for brazed joints wherever applicable.
- (j) Measurement of voltage ratio to be carried out when core/yoke is completely restacked and all connections are ready.
- (k) Certification of all test results.

9.2.5 CHECKS BEFORE DRYING PROCESS:

- (a) Check condition of insulation on the conductor and between the windings.
- (b) Check insulating distances between high voltage connections, cables and earth and other live parts.
- (c) Check insulating distances between the low voltage connection and earth and other parts.
- (d) Insulation test of core earthing. Insulation of the core shall be tested at 2 KV/min. between core to clamp plates and core bolts.
- (e) Check for proper cleanliness and absence of dust etc.
- (f) Certification of all test results.

9.2.6 CHECKS DURING DRYING PROCESS:

- (a) Measurement and recording of temperature, vacuum and drying time during vacuum treatment.
- (b) Check for completeness of drying by measuring IR value and TAN DELTA. Polarisation index of the winding i.e., ratio of IR value taken at 10 minutes to 1 minute shall be taken. The P.I. Value should not be less than '2.0' and less than 5.0.
- (c) Certification of all test results.

9.2.7 ASSEMBLED TRANSFORMER:

- (a) Check completed transformer against approved out line drawings, provision for all fittings finish level etc.
- (b) Jack test with oil on the assembled transformers.
- (c) DP test shall be carried out after jacking test.

9.2.8 OIL:

Site test shall be performed on oil samples before and after filling in the transformer. Oil parameters shall conform to relevant IEC & ISS prior to filling at site and oil samples taken from the tank top, bottom and cooling system after filling shall possess characteristics as per above standards. The supplier shall warrant that oil furnished is in accordance with the relevant clause of this specification. The purchaser at his discretion may send oil sample(s) to Govt. approved laboratory for determination of quality of oil including confirmation on percentages of naphthenic and paraffinic content, as specified at Cl. No.5.4.17(a) of this Specification.

9.2.9 The makes of all major bought out items shall be subject to purchaser's approval. The supplier shall also prepare comprehensive inspection and testing programme for all bought-out/subcontracted items and shall submit the same to the purchaser for approval. Such programme shall include the following components.

- (a) Buchholz Relay.
- (b) Axles and wheels.
- (c) Winding temperature indicators for local and remote mounting.
- (d) Oil temperature indicators.
- (e) Bushings.
- (f) Neutral current transformers.

- (g) Cooler control cabinet.
- (h) Cooling equipments.
- (i) Fans/Air blowers.
- (j) Tap changing switch.
- (k) Terminal connectors.
- (l) Optic Fiber Temperature System as per this Specification
- (m) Transformer Oil

9.3 **PRE-SHIPMENT CHECK AT SUPPLIER'S WORKS:**

- (a) Check for proper packing and preservation of accessories like radiators, Bushings, explosion vent, dehydrating breather, rollers, Buchholz relay, fans, control cubicle, connecting pipes, conservator etc.
- (b) Check for proper provision of bracing to arrest the movement of core and winding assembly inside the tank.
- (c) Gas tightness test to conform tightness.
- (d) Deviation of leakage rate and ensure adequate reserve gas capacity.

9.4 **RECOMMENDED COMMISSIONING CHECKS:**

- (a) Check the colour of sillicagel breather.
- (b) Check the oil level in the breather housing, conservator tanks, cooling system, condenser bushing etc.
- (c) Check the bushing for conformity of connection to the lines etc. and tan delta test for bushings at 10 KV (min.)
- (d) Check for correct operation of all protection and alarm.
 - (i) Buchholz Relay.
 - (ii) Excessive winding temperature.
 - (iii) Excessive oil temperature.
 - (iv) Low oil flow.
 - (v) Low oil level indication.
 - (vi) Fan failure protection.
- (e) Check for the adequate protection of the electric circuit supplying the accessories.
- (f) Check resistance of all windings on all the taps.
- (g) Insulation resistance measurement of:
 - (i) Control wiring.
 - (ii) Tap changer motor and control.
 - (iii) Cooling system motor and control.
 - (iv) Main windings.
- (h) Check for cleanliness of the transformer and the surroundings.
- (i) Continuously observe the transformer operation at no load for 24 hours.
- (j) Gradually put the transformer on load, check and measure increase in temperature in relation to the load and check the operation with respect to temperature rise, noise level etc.
- (k) Phase sequence and vector group test.
- (l) Ratio tests on all taps.
- (m) Magnetising current test.
- (n) Tan delta measurement of windings.

10.0 **QUALITY ASSURANCE PLAN:**

The Bidder shall invariably furnish following information alongwith his offer, failing which the offer shall be liable for rejection.

- (i) Statement giving list of important raw materials, names of Sub-suppliers for the raw materials, list of standards according to which the raw materials are tested, list of tests normally carried out on raw material in presence of Bidder's representative,

- copies of test certification.
 - (ii) Information and copies of test certificates as in (i) above in respect of bought out items.
 - (iii) List of manufacturing facilities available.
 - (iv) Level of automation achieved and list of areas where manual processing exists.
 - (v) List of areas in manufacturing process, where stage inspections are normally carried out for quality control and details of such tests and inspection.
 - (vi) Special features provided in the equipment to make it maintenance free.
 - (vii) List of testing equipments available with the Bidder for final testing of equipment specified and test plant limitation, if any, vis-à-vis the type, special, acceptance and routine tests specified in the relevant standards. These limitations shall be very clearly brought out in 'Schedule of Deviations'.
- 10.1 The supplier shall within 30 days of placement of order, submit the following informations to the purchaser.
- (i) Name of the raw materials as well as bought- out accessories and the names of sub-suppliers selected from those furnished along-with the offer.
 - (ii) Type test certificates of the raw material and bought out accessories.
 - (iii) Quality Assurance Plan (QAP) with hold points for purchaser's inspection. The QAP and hold points shall be discussed between the purchaser and the supplier before the QAP is finalised. The QAP shall include all the quality checks as stipulated in this specification.
- 10.2 The supplier shall submit the routine test certificates of bought out items and raw material at the time of routine testing of the fully assembled transformer.

11 DOCUMENTATION:

- 11.1 All drawings shall conform to relevant International Standards Organisation (ISO) specification. All drawing shall be in ink and suitable for microfilming. All dimensions and data shall be in S.I.Units.
- 11.2 The Bidder shall furnish along-with the bid dimensional drawings of transformer and all other accessories. These drawing shall include the following informations.
- (a) Dimensions.
 - (b) Tolerances on dimensions.
 - (c) Material designation used for different components with reference to standards.
 - (d) Fabrication details such as welds, finishes and coatings.
 - (e) Catalogue or part members for each component and the total assembly with bill of materials.
 - (f) Identification marking.
 - (g) Weight of individual components and total assembled weight.
- 11.3
- 11.3.1 **The supplier shall, within 15 (fifteen) days of placement of order submit four sets of final version of all the following drawings/ documents for purchaser's approval. All Drawings and Designs in complete shape (not in a piece-meal manner) as per the specification and without any deviation should be submitted within 15 (Fifteen) days of placement of Purchase Order. The Design Engineer(s) of the firm should be present in the office of the Sr. G.M (CPC) to complete the Design Review and Drawing Approval as soon as possible**
- a) Out line dimensional drawings of transformer and accessories.
 - b) Table of fittings for OGA.
 - c) Combined Rating and Diagram plate.
 - d) **RIP/RIS HV Bushing.**
 - e) **RIP/RIS LV Bushing.**
 - f) **RIP/RIS Neutral Bushings.**

- g) Twin Bi-directional Roller.
- i) Valve schedule plate
- j) Foundation plan along with weights of foundations.
- k) Oil filling Instruction plate.
- l) Thermo Syphon Filter.
- m) Schematic control and wiring diagram for all auxiliary equipments including OLTC cooler control etc.
- n) GA of Marshalling Kiosk.
- o)) General Arrangement of RTCC panel.
- p) Assembly of core with details of stacks, dimensions and weights etc.
- q) Details of winding arrangement, conductor cross-section & weights etc.
- r) CT rating plate.
- s) Schematic diagram showing the flow of oil in the cooling system as well as each limb and winding Longitudinal and cross-sectional view showing the duct sizes, cooling pipes etc. for the transformer/ heat exchanger, drawn to scale shall be furnished.
- t) Inter connection-cabling diagram between transformer and all panels.
- u) Constructional details and sectional views of on-Load Tap Changer.
- v) Complete bill of materials.
- w) Detailed dimensions, assembly and description of auxiliaries.
- x) Constructional details of tank including material, dimensions thickness, reinforcing members, used, if any.
- y) Galvanising and painting procedure.
- z) Factory Test procedures, lay-out of testing equipments/circuits and Test schedules for tests.
- aa) Commissioning test procedure and report.
- bb) Operation and Maintenance Manual.

- cc) QAP during manufacturing and during erection of the transformer.

- dd) Any other drawings(s) as required by the purchaser.

The purchaser shall communicate his comments/ approval on the drawings/documents to the supplier within reasonable period. The supplier shall, if necessary, modify the drawings and resubmit four copies of the modified drawings for purchaser's approval within one week from the date of comments. After receipt of purchaser's approval the bidder shall, within one week, submit 15 prints and one good quality reproducible of the approved drawings for purchaser's use.

11.3.2 **DESIGN REVIEW:**

- 11.3.2.1. The Transformers shall be designed, manufactured and tested in accordance with the best international Engineering Practices under strict Quality Control to meet the requirements, stipulated in the Technical specification. Adequate safety margin with respect to thermal, mechanical, dielectric, electrical stresses and electrical clearances shall be maintained during design, selection of raw materials, manufacturing process etc. so that the Transformer provides long life with least maintenance.
- 11.3.2.2. The design review will commence after placement of award with successful Bidder and shall be finalized before final drawing approval. The supplier shall depute their design engineer(s) to OPTCL for design review and finalisation of drawings. However, the entire responsibility of design shall rest with the manufacturer.
- 11.3.2.3 The representative of the purchaser may visit to the manufacturer's works to inspect design, manufacturing and testing facilities.
- 11.3.2.4 The design review shall be conducted generally following the "Guidelines for conducting design reviews, prepared by CIGRE SC12 working Group 12.22.
- 11.3.2.5 The manufacturer shall provide all necessary informations and calculations during design

review to demonstrate that the Transformer meets the requirements for short circuit strength and durability. The latest recommendations of IEC and CIGRE SC12 shall be applied for short circuit withstand evaluation.

11.3.2.6 The manufacturer will be required to demonstrate the use of adequate safety margin for thermal, mechanical, dielectric and vibration etc. to take into account the uncertainties of his design and manufacturing processes..

11.3.2.7 The scope of such a design review shall atleast include the followings:-

- i) Core design
- ii) Winding, tapping and Insulation design
- iii) Short-circuit withstand capability
- iv) Electrical clearances between windings to core(both axially and radially) between windings, outer windings to tank etc.
- v) Thermal design including areas,prone to hot spots.
- vi) Cooler design
- vii) Over-load capacity
- viii) Over-fluxing
- ix) Magnetising Inrush current
- x) Eddy current losses
- xi) Seismic design
- xii) Insulation co-ordination
- xiii) Tank &Accessories
- xiv) Bushings & barrier design
- xv) Tap-changer
- xvi) Protective devices
- xvii) Fans & radiators
- xviii) Oil & oil preservation system
- xix) Corrosion protection
- xx) Electrical and physical interfaces with sub-station
- xxi) Earthing
- xxii)Processing and assembly
- xxiii) Testing capabilities
- xxiv) Inspection and Test plan

- xxv) Transport and storage
- xxvi) Sensitivity of design to specified parameters
- xxvii) Accoustic noise
- xxviii) Spares, inter-changeability and standardization
- xxix) Maintainability
- xxx) Any other design aspect, as deemed necessary

xxxi) **NIFPES** Functional logics

- 11.4 The supplier shall also furnish five copies of bound manuals for each transformer covering erection, commissioning, operation and maintenance instructions and all relevant information and drawings pertaining to the main equipment as well as auxiliary devices. Marked erection drawings shall identify the component parts of the equipment as shipped to enable purchaser to carry out erection with his own personnel. Each manual shall also contain one set of all the approved drawings, type test reports as well as acceptance reports of the corresponding consignment despatched.
- 11.5 The manufacturing of the equipment shall be strictly in accordance with this Specification, approved drawings and no deviation shall be permitted without the written approval of the purchaser. All manufacturing and fabrication work in connection the equipment prior to the approval of the drawings shall be at the supplier's risk.

However, approval of the drawings by the purchaser shall not relieve the supplier of his responsibility and liability for ensuring correctness and correct interpretation of the latest revision of applicable standards, rules and codes of practices. The Transformer shall conform in all respects to high standards of engineering, design, workmanship and latest revisions of relevant standards at the time of ordering and the purchaser shall have the power to reject any material, which in his judgement is not in full accordance therewith.

11.5.1 **TEST REPORTS:**

- (i) Four copies of type test reports shall be furnished to the purchaser. One copy will be returned duly certified by the purchaser to the supplier.
- (ii) Four copies of routine test reports shall be furnished to the purchaser. One copy will be returned duly certified by the purchaser and only thereafter shall the materials be dispatched.
- (iii) All records of routine test reports shall be maintained by the supplier at his works for periodic inspection by the purchaser.
- (iv) All test reports for tests conducted during manufacture shall be maintained by the supplier. These shall be produced for verification as and when requested for by the purchaser.

12.0 **TRANSPORTATION, PACKING AND FORWARDING:-**

- 12.1 The supplier shall dispatch the transformer, filled with oil or in an atmosphere of nitrogen or dry air at positive pressure. In the former case, the supplier shall take care of the weight limitation on transport and handling facility at site. In the latter case, necessary arrangement shall be ensured by the supplier to take care of pressure drop of nitrogen or dry air during transit and at site of installation. The nitrogen or dry air cylinder, provided to maintain positive pressure can be taken back by the supplier after oil filling. A gas pressure testing valve with necessary pressure gauge and adapter valve shall be provided. **Transformer shall also be fitted with at least one "Electronic Impact Recorder" (on returnable basis) during transportation to measure the magnitude and duration of the impact in all three**

directions. The acceptance criteria and limits of impact in all three directions, which can be withstood by the equipment during transportation and handling, shall be submitted by the supplier during detailed engineering. The recording shall commence in the factory before dispatch and must continue till the unit is received/installed at destination substation. The data of electronic impact recorder(s) shall be downloaded at site and a soft copy of it shall be handed over to Engineer-in-charge. Further, within three weeks, the supplier shall communicate the interpretation of the data.

- 12.2 The equipment shall be suitable for vertical/horizontal transport as the case may be and suitable to withstand handling during transport and outdoor storage during transit. The supplier shall be responsible for any damage to the equipment during transit, due to improper and inadequate handling during transfer, loading and unloading. The easily damageable material shall be carefully packed and marked with the appropriate caution symbol. Whenever necessary, proper arrangement for lifting, such as lifting hooks etc. shall be provided. Any material found short inside the packing cases shall be supplied by supplier without any extra cost.
- 12.3 Each consignment shall be accompanied by a detailed packing list containing the following Information:-
- (a) Name of the consignee.
 - (b) Details of consignment.
 - (c) Destination.
 - (d) Total weight of consignment.
 - (e) Sign showing upper/lower side of the crate.
 - (f) Handling and unpacking instructions.
 - (g) Bill of materials indicating contents of each package.
 - (h) Two sets of approved copies of drawings, instruction and commissioning manuals, approved test certificates and certificates of bought out items, approved copies of guarantee certificate.
- 12.4 The supplier shall ensure that the packing and bill of materials are approved by the purchaser before despatch.

13.0 **SUPERVISION OF ERECTION, TESTING AND COMMISSIONING (ET&C):**

The erection, testing and commissioning of the transformers shall be supervised by trained personnel (Engineer) of the supplier. The Engineer shall direct the sequence of ET& C. The Engineer shall correct in the field, any errors or omissions on the part of the supplier, in order to make the equipment and material properly perform in accordance with the intent of this specification. The Engineer shall also instruct the plant operators in the operation and maintenance of the commissioned equipment. The supplier shall be responsible for any damage to the equipment, on commissioning the same, if such damage results from faulty or improper ET&C procedure. Purchaser shall provide adequate number of skilled/semi-skilled workers as well as all ordinary tools and equipment and cranes required for equipment erection, at his own expenses. Apart from the above, the purchaser shall not be responsible for any other expenses such as Engineer's salary, insurance against personal injuries to the Engineer etc. Special tools, if required for erection and commissioning, shall be arranged by the supplier at his cost and on commissioning, these shall be supplied to the purchaser, free of cost for future use. The supervision of erection, testing and commissioning charges will be borne by the Purchaser as per tender price schedule.

14.0 **QUANTITY AND DELIVERY REQUIREMENTS:**

- (i) This is set out in Annexure -I of this Specification. **The firm will submit a 'PERT CHART', indicating the manufacturing, inspection, testing and delivery schedule in details immediately after receipt of the Purchase Order.**
- (ii) The scope of supply shall also include supply of 2.5% extra quantity of bolts, nuts,

washers, split pins, cotter pins and such other small loose items, free of cost in addition to the materials/equipments as spelt out in this specification.

15.0 Values quoted in the G.T.P. and in details of loss calculations shall not differ. In case if it differs, then values quoted in the G.T.P. will be taken as final for all purposes.

16.0 METHOD OF TECHNICAL EVALUATION :

Bids will be evaluated in the following manner.

- (a) To check the flux density at the rated voltage i.e., 220KV/132KV/33KV rated frequency i.e., 50 Hz and maximum stacking factor as 0.97.
- (b) To check the data furnished in the GTP as correct as per the Technical Specification. If on calculation, GTP data will be different from the calculated data, then the bid will not be considered or owner may take any other decision. GTP furnished in incomplete shape will not be considered for evaluation.
- (c) If HI-B grade sheet steel for core material has not been quoted and specific loss and B-H curve for the said material alongwith the materials name and test report has not been furnished, the bid will be rejected. Details of HIB core particulars like length, Breadth, thickness of each stack alongwith core dia., L.V., & H.V. No of turns and lamination thickness, weight of core shall be submitted alongwith the bid failing which tender will be liable for rejection.
- (d) Bid will be rejected, if firm will not accept all the specified Technical terms and conditions.
- (e) Bid will be rejected if Maximum Flux Density and Core weight calculation(As per Annex-II) and details of Loss calculations(As per Annex-III) will not be found to be in order and if there is any ambiguity/discrepancy, noticed in the above calculations.
- (f) The Bidder shall submit alongwith the bid the graph depicting the saturation characteristic curve between the no load voltage (RMS) vs.-measured excitation current starting from 10% of rated no load voltage to 125% of the same, failing which the tender is liable for rejection. The knee point voltage shall have to satisfy the specified value as per the criteria stipulated at Clause No.4 (18) of this Specification.

Bidders are required to be careful in choosing the maximum flux density, best possible core materials (HIB or better) and type of corner joints of the core etc.so as to quote the practicable no-load current at different percentages of rated no-load voltage as per given GTP format and submit a linear graph along with the tender, confirming to achieve the specified minimum knee point voltage i.e.110% of the rated voltage during no-load test as per the method, stipulated at CL.No.6.4.2 (k) of this Technical Specification, which will be confirmed through testing both during stage inspection and final inspection.

ANNEXURE-I SCHEDULE OF QUANTITY AND DELIVERY Sl.No	Description materials of	Quantity required	Desired Delivery	Destination	Remarks
1	2	3	4	5	6

1	40MVA,220/33KV power transformer.	6(SIX)Nos.	Within 6(six) months from the date of issue of purchase order.	Any Grid S/S of OPTCL (Existing or New) inside the state of Odisha.	

N.B: -The delivery schedule, destination Sub-station will be intimated at the time of placement of purchase order/release order.

Place:

Date:

Signature of Tenderer
with seal of Company.

ANNEXURE-II

MAXIMUM FLUX DENSITY AND CORE WEIGHT CALCULATION

[To be filled in by the Bidder]

Name of the bidder: -

Address:-

Type and Grade of Core: -

Thickness [in mm]:-

<u>Step No</u>	<u>Width of steps [mm]</u>	<u>Stack thickness [mm]</u>	<u>Gross Iron area [mm²]</u>
1			
2			
3			
4			
5			
6			
7			
8			
9			
10			
11			
12			
13			
14			
15 to			

$$E = 4.44 \times f \times B_{\max} \times A_i \times N$$

Where E = L.V. winding rated voltage / phase = 33000 / 1.732 volts.

f = Rated frequency = 50 HZ.

B max. = Maximum flux density in Tesla.

A_i = Net iron area in sq.m = Gross iron area x stacking factor in sq.m

N = Number of L.V. winding turns/phase

$$B_{\max} = E / 4.44 \times f \times A_i \times N$$

Core weight calculation:-

Core dia [in mm] =

Window height [in mm] =

Limb center [in mm] =

i) W=Weight of core = [3 x window height + 4 x limb centre + 2 x max. width] x Net iron area x Density of core

ii) Core loss in watt/kg. from graph for grade/type of core material and selected Flux density-

iii) Building factor-

iv) No-load loss in watts=core weight x watts/kg. x Building factor

v) Guaranteed No-load loss in watts=

- NB: -
1. Specific loss vs. flux density graph for the type of core lamination to be used has to be furnished.
 2. VA/Kg. Vs flux density graph for the core lamination to be used has to be furnished.
 2. Any other factor assumed for above calculation to be explained with reasons.

Place

Date

Bidder's name:

Signature, designation, seal

NB- The Bidders are required to up load this calculation sheet duly filling the required data, in PDF format.

ANNEXURE-III

DETAILS OF LOSS CALCULATIONS FOR 40 MVA,132/33 KV POWER TRANSFORMER

[To be filled in by the Bidder]

1. Name of the Firm
2. Flux density at
 - i (245)/36 KV and 48.5 Hz [Tesla]
 - ii (220)/33 KV & 50.0Hz [Tesla]
3.
 - i Core weight in Kg.
 - ii Gross core area [mm²]
 - iii. Stacking factor.
 - iv. Net core iron area [mm²] [ii x iii]
4. [a] Specific losses [W/Kg.]
 - i At maximum flux density corresponding to (245)/36 KV and 48.5 HZ.
 - ii At maximum flux density corresponding to (220)/33 KV and 50Hz.[b] Volt ampere/Kg
 - (i) At maximum flux density corresponding to (245)/36 KV and 48.5 Hz
 - (ii) At maximum flux density corresponding to (220)/33 KV and 50 Hz.
5. Calculated/guaranteed iron loss in KW at:-
 - i Rated voltage and rated frequency
 - ii Maximum system voltage and lowest system frequency
6. Current density [A/Sq. mm] at normal tap for
 - i HV
 - ii Regulating
 - iii LV
7. Conductor size [in mm²]
 - a HV
 - i Bare
 - ii Insulated
 - iii No of conductors in parallel
 - b Regulating winding
 - i Bare
 - ii Insulated
 - iii No of conductors in parallel
 - c L.V. winding
 - i. Bare
 - ii. Insulated.
 - iii. No. of conductors in parallel.
8. Total Bare copper conductor area(A) (Sq.mm.)
 - i HV
 - ii LV
 - iii Regulating
9. No. of turns/phase(N) at

Highest tap	Lowest tap	Normal tap
-------------	------------	------------

 - i HV
 - ii Regulating
 - iii LV
10. Internal Diameter(in mm.)
 - i HV
 - ii Regulating
 - iii LV

NB- The Bidders are required to up load this calculation sheet duly filling the required data, in PDF format.

ANNEXURE-IV

GUARANTEED TECHNICAL PARTICULARS

[TO BE FILLED IN BY THE BIDDER]

<u>Sl. No</u>	<u>Description</u>	40MVA,220/33KV
1	Name of the Manufacturer	
2.	Installation [indoor/outdoor]	
3	Reference standards	
4.	Continuous Ratings	
	a Type of cooling	
	b Rating [MVA]	
	i With ONAN cooling	
	ii With ONAF cooling	
	c Rated voltage	
	i HV [KV rms.]	
	ii LV [KV-rms.]	
	d Highest system voltage	
	i HV [KV rms.]	
	ii LV [KV-rms.]	
	e Rated frequency with $\pm\%$ variation	
	f Number of phases	
	g Current at rated full load and on principal tap	
	i HV [Amps]	
	ii LV [Amps]	
5.	Connections	
	HV	
	LV	
6.	Connection symbol and vector group	
7.	Temperature rise	
	a Temperature rise of oil above ambient temperature [by Thermometer & Optic Fiber Temperature Sensor]	
	i At full ONAN rating [$^{\circ}\text{C}$]	
	ii At full ONAF rating [$^{\circ}\text{C}$]	
	b Temperature rise of windings above ambient temperature [By resistance method]	
	i At full ONAN rating [$^{\circ}\text{C}$]	
	ii At full ONAF rating [$^{\circ}\text{C}$]	
	c. Hot Spot Temperature rise of Windings above ambient Temperature [By Optic Fiber Temperature Sensors]	
	i At full ONAN rating [$^{\circ}\text{C}$]	
	ii At full ONAF rating [$^{\circ}\text{C}$]	
	d. Temperature gradients between windings & oil.	
	e. Limit of Hot spot temperature for which the Transformer is designed [$^{\circ}\text{C}$]	
	f. Period of operation of transformer at full load	

		without calculated winding hot spot Temperature exceeding 140°C and with		
	i	50% Coolers		
	ii	100% Coolers		
8		Type of ON load tap changing switch		
9.		Tapping on windings for		
	i	Constant flux/variable flux/combined regulation.		
	ii	Tapping provided at		
	iii	Number of steps		
	iv	Range of tapping for variation [+ percent to- percent]		
10.	i	No load loss at rated voltage and frequency at principal tap [KW]		
	ii	No load loss at the voltage corresponding to highest tap [KW]		
11.		Load loss at rated output, rated frequency, corrected for 75 °C winding temperature at:- [Copper loss + cooler loss]	<u>ONAN</u>	<u>ONAF</u>
	i	Principal tap [In KW]		
	ii	Highest tap [In KW]		
	iii	Lowest tap [In KW]		
12		Auxiliary losses at rated output, normal ratio, rated voltage, rated frequency and ambient temperature [KW]		
13.		Total losses at normal ratio inclusive of auxiliary equipment losses [KW]		
14.		Positive sequence impedance on rated MVA base at rated current and frequency at 75° Centigrade winding temperature at		
	i	Principal tap [%]		
	ii	Highest tap [%]		
	iii	Lowest tap [%]		
15.		Zero sequence impedance at reference temperature of 75°C at principal tap [%]		
16		% reactance at rated MVA base at rated current and rated frequency at		
	i	Principal tap [%]		
	ii	Highest tap [%]		
	iii	Lowest tap [%]		
17.		% resistance at rated MVA base at rated current and rated frequency at		
	i	Principal tap [%]		
	ii	Highest tap [%]		
	iii	Lowest tap [%]		
18		% Impedance at rated MVA base at rated current and rated frequency at		
	i	Principal tap [%]		
	ii	Highest tap [%]		
	iii	Lowest tap [%]		
19.	a	Polarisation index i.e. ratio of Megger values at 600 secs to 60 secs, (H.V. to E , L.V. to E, H.V. to L.V.		

- b Regulation at full load and 75°C winding temperature expressed as a percentage of normal voltage
- i At unity power factor [%]
- ii At 0.8 power factor [lagging][%]
- 20 Efficiency at 75°C winding temperature as derived from guaranteed loss figures and at Unity power factor 0.8 Power factor
- a At full load [%]
- b At ¾ load [%]
- c At ½ load [%]
- 21 i Maximum efficiency [%]
- ii Load at which maximum efficiency occurs[% of full load]
- 22 Time in minutes for which the transformer can be run at full load without exceeding the maximum permissible temperature at reference ambient temperature when supply to:-
- i Fans are cut off
23. Short time thermal rating of
- i HV winding in KA and duration in seconds
- ii LV winding in KA and duration in seconds
- 24 Permissible over loading:-
- a HV winding
- b LV winding
- 25 Terminal arrangement
- a High voltage [HV]
- b Low voltage (LV)
- c Neutral
- 26 Insulating and cooling medium
- 27 [A] Test voltage HV LV
- i Lightning impulse withstand test voltage [KVP]
- ii Power frequency withstand test voltage [dry and wet][for 1 minute] [KV-rms.]
- 28 Partial discharge level as per relevant upto date IEC
- 29 Noise level when energized at normal voltage, frequency without load and with all cooling fans in running condition.
30. External short circuit withstand capacity [MVA] and duration [seconds]
- 31 Over-fluxing withstand capability of the Transformer
- 32 DETAILS OF CORE
- a Type of core construction
- b Type of corner joints of the core
- c. Maximum flux density at
- i Rated voltage [220/33 KV] & rated frequency 50 Hz][in Tesla]
- ii Highest system voltage [245/36 KV] and lowest system frequency [48.5Hz.][in Tesla]
- d No load current, no load loss and no load power factor at normal ratio and frequency [Amp/KW/p.f.]
- i 10 percent of rated voltage
- ii 25percent of rated voltage

- iii 50 percent of rated voltage
- iv 85 percent of rated voltage
- v 100 percent of rated voltage
- vi 105percent of rated voltage
- vii 110 percent of rated voltage
- viii 112.5 percent of rated voltage
- ix 115 percent of rated voltage
- x 120 percent of rated voltage
- xi 121 percent of rated voltage
- xii 125 percent of rated voltage
- e Core laminations:-
 - i Material of core lamination [HIB/Laser grade]
 - ii Grade of core laminations
 - iii Thickness of core lamination [mm]
 - iv Specific loss [watt/Kg.] at rated voltage and rated frequency
 - v Specific loss [watt/Kg.] at highest system voltage and lowest system frequency
 - vi Whether specific core loss graph [flux density vs. watt/Kg.submitted
 - vii VA/Kg at rated voltage and rated frequency
 - viii VA/Kg. at highest system voltage and lowest system frequency
 - ix Whether VA/Kg. Vs. flux density graph submitted.
 - x Insulation of core laminations
- f CORE ASSEMBLY:-
 - i Core diameter [mm]
 - ii Core window height [mm]
 - iii Core leg centre [mm]
 - iv Gross core cross-sectional area [m²]
 - v. Whether details of core widths, stacks and calculation furnished as per enclosed annexure
 - vi Distance between centres [mm]
 - vii Total height of core [mm]
 - viii
 - 1) Details of core belting.
 - 2) Material, grade & type.
 - 3) Width.
 - 4) Thickness.
 - 5) Fixing method.
 - ix. Details of top end frame.
 - x Details of Bottom end frame.
 - xi Details of clamp plate [Material, thickness, Insulation]
 - xii Details of clamp plate [material, thickness, Insulation]
 - xiii Total core weight [kg]
 - xiv Core loss basing on core loss graph at operating flux density [rated voltage and rated frequency] [kw] factor
 - xv Core stacking
 - xvi Net core area Sq. m.
 - xvii Margin towards corner joints, cross fluxing etc [kw]
 - xviii Total core loss at rated voltage and rated

	frequency	[xv+xviii]		[kw]
xix	Dielectric loss at rated voltage and rated frequency		[KW]	
xx	No load loss at rated voltage and rated frequency [xix+xx] [KW]			
g	Describe location/method of core in grounding			
h	Details of oil ducts			core
i	Peak value of magnetising Inrush current (% of HV rated current).			
33	<u>DETAILS OF WINDINGS.</u>	HV	LV	
a	Type of winding			
b	Material of the winding conductor.			
c.	Maximum current density of windings [at rated current] [Normal Tap] and Conductor area	Conductor / density [A/cm ²]	Current area [cm ²]	
i	HV			
ii	Regulating			
iii	L.V			
d	Whether HV windings are interleaved.			
e	Whether windings are pre-shrunk?			
f	Whether adjustable coil clamps are provided for H.V. and L.V. windings?			
g	Whether steel rings are used for the windings? If so, whether these are split?			
h	Whether electrostatic shields are provided to obtain uniform voltage distribution in the windings?			
i	Winding Insulation		Type & class. Graded or ungraded	
i	H.V. & Regulating			
ii	LV			
j	Insulating material used for			
i	H.V. & Regulating winding.			
ii	L.V Winding			
iii	For core bolts washers and end plates.			
iv	Tapping connection.			
k	Insulating material used between			
i	H.V. and L.V. winding			
ii	H.V. and Regulating winding.			
iii	Core and L.V winding.			
iv	H.V. to H.V.winding [between phases]			
l	Type of axial coil supports.			
i	H.V. winding			
ii	LV winding			
iii	Regulating winding			
m	Type of radial coil supports			
i	HV winding			
ii	Regulating winding			
iii	LV winding			
n	Maximum allowable torque on coil clamping bolts	<u>HV</u>	<u>Regulating</u>	<u>LV</u>
o	Bare conductor size (mm).			

- p** Insulated conductor size (mm).
- q** No. of conductors in parallel (Nos.).
- r** No. of turns/phase
- s** No. of discs/phase
- t** No. of turns/disc
- u** Gap between discs. (mm).
- v** Inside diameter (mm).
- w** Outside diameter (mm).
- x** Axial height after shrinkage (mm).
- y** D.C.RESISTANCE
- i** L.V winding at 75 ° C (Ohms).
- ii** HV winding and Regulating winding at normal tap at 75° C (Ohms).
- iii** HV winding and Regulating winding at highest tap at 75° C (Ohms).
- iv** HV winding and regulating winding at lowest tap. (Ohms).
- v** Total I²R losses at 75 ° C. for normal tap. (KW).
- vi** Total I²R losses at 75 ° C. for highest tap. (KW)
- vii** Total I²R losses at 75 ° C for lowest tap.(KW).
- viii** Stray losses including eddy current losses in winding at 75°C (KW).
- a** Normal tap position
- b** Highest tap position
- c** Lowest tap position.
- d** Any special measures taken to reduce eddy current losses and stray losses, mention in details.
- z** Load losses at 75°C [I²R + stray].
- a** Normal tap position [KW].
- b** Highest tap position [KW].
- c** Lowest tap position [KW].
- aa** Details of special arrangement provided to improve surge voltage distribution in the windings
- bb** Tan delta(power factor) of Windings(Max.)

34	<u>BUSHINGS.</u>	<u>HV</u>	<u>LV</u>	<u>HVN</u>	<u>LVN</u>
	a				
	i				
	ii				
	b.				
	c				
	d				
	i				
	ii				
	e.				
	f				
	g				
	h				
	i				
	j				

- k Weight of assembled bushing [Kg.]
- l Minimum clearance height for removal of bushing [mm]
- m Under oil flashover or puncture impulse voltage [KVP]
- n. Under oil flashover or puncture power frequency voltage (KV-rms).
- o. Phase to earth clearance in air of live parts at the top of bushings.
- p. Maximum tan delta value at 20 deg.C
- 35 **Minimum clearance [mm]** **Between Windings** **Phase to ground**
- (A) **Out of Oil**
- HV
- LV
- (B) **In Oil**
- (i) LV to Core
- (ii) LV to top yoke
- (iii) LV to bottom yoke
- (iv) LV to HV(radially)
- (v) HV to Regulating(radially)
- (vi) HV to top yoke
- (vii) HV to bottom yoke
- (viii) Regulating to top yoke
- (xii) Regulating to bottom yoke
- (xiii) Reg. winding to Reg. winding
- (xiv) Regulating winding to tank wise
- (a) Length wise
- (b) Breadth wise
- (c) Width wise

N:B- Winding Arrangement-CORE-LV-HV-REGULATING

- 36 **Weight [Tolerance + 5%]**
 [Approximate value is not allowed]
- a Core [Kg.]
- b Core with clamping [Kg.]
- c H.V. winding insulated conductor [Kg.]
- d L.V. winding insulated conductor [Kg.]
- e Regulating winding insulated conductor [Kg.]
- f Coils with insulation [Kg.]
- g Core and winding [Kg]
- i Oil required for first filling [Liter/Kg.]
- j Tank and fittings with accessories [Kg.]
- k Untanking weight [Kg.]
- l Total weight with oil and fittings along with accessories [Kg.]

37 **DETAILS OF TANK**

- a Material for Transformer tank
- b Type of tank
- c Thickness of sheet
 [No approximate value to be mentioned]
- i Sides [mm]

- ii Bottom [mm]
 - iii Cover [mm]
 - iv Radiators [mm]
 - d Inside dimensions of main tank
[No approximation in dimensions to be used]
 - i Length [mm]
 - ii Breadth [mm]
 - iii Height [mm]
 - e Outside dimensions of main tank
[No approximation in dimensions to be used]
 - i Length [mm]
 - ii Breadth [mm]
 - iii Height [mm]
 - f. Thickness of spray galvanisation of tank bottom.
 - g. Vacuum recommended for hot oil circulation [torr]
 - h. Vacuum to be maintained during oil filling in Transformer tank [torr]
 - i. Vacuum to which the tank can be subjected without distortion [torr]
 - j. No. of bi-directional wheels provided
 - k. Track gauge required for the wheels
 - i Transverse axis
 - ii Longitudinal axis
 - l Type and make of pressure relief device and
minimum pressure at which it operates [Kpa]
- 38** **CONSERVATOR**
- a Total volume [Liters]
 - b Volume between the highest and lowest visible
oil levels [Litres]
 - c Power required by heaters
[if provided][KW]
 - d Conservator sheet thickness (mm.)
- 39** **OIL QUALITY**
- a Governing standard
 - b Density in gms/cu-cm
 - c Kinematics viscosity in CST
 - d Inter facial tension at 27°C in N/m
 - e Flash point in °C
 - f Pour point in °C
 - g Acidity [neutralization value] in mg of
KOH/gm
 - h Corrosive sulfur in %
 - i Electric strength
[breakdown voltage]
 - i As received [KV-rms.]
 - ii After treatment [KV-rms.]
 - j Dielectric dissipation factor [tan delta] at 90°C
 - k Saponification value in mg of KOH/gm
 - l Water content in ppm
 - m Specific resistance
 - i At 90°C [ohm-cm]
 - ii At 27 °C [ohm-cm]
 - n N- dm analysis CA%
CM%
CP%

	o	Oxidation stability	
	i	Neutralization value after oxidation	
	ii	Total sludge after oxidation	
	p	Characteristic of oil after ageing test as per ASTMD-1934	
	i	Specific resistance at 27°C [ohm-cms] 90°C [ohm-cms]	
	ii	Tan delta	
	iii	Sludge content	
	iv	Neutralization number	
	v	Percentage of Napthenic content	
	vi	Percentage of paraffinic content	
	vii	Details of oil preserving equipment offered	
40		<u>RADIATORS</u>	
	a	Overall dimensions lxbxh [mm]	
	b	Total weight with oil [Kg.]	
	c	Total weight without oil [Kg.]	
	d	Thickness of radiator tube [mm]	
	e	Types of mounting	
	f	Vacuum withstand capability	
	g	Total radiating surface in sq.m	
	h	Type and make of material used for the radiators	
	i	Total number of radiators/Banks for Transformer and dimensions of tubes.	
	j	Thickness of hot dip galvanization of radiators.	
41		<u>COOLING EQUIPMENT</u>	Fan motor
	a	Make and type	
	b	No. of connected units	
	c	No. of stand -by units	
	d	Rated power input	
	e	Capacity [cu-m/min. or] [liters/min]	
	f	Rated voltage [volts]	
	g	Locked rotor current [Amps.]	
	h	Efficiency of motor at full load [%]	
	i	Temperature rise of motor at full load [°C]	
	j	BHP of driven equipment	
	k	Temperature range over which control is adjustable [°C]	
	l	Whether the fans are suitable for continuous operation at 85 % of their rated voltage.	
	m	Estimated time constant in hours for	
	i	Natural cooling	
	ii	Forced air cooling	
42		<u>GAS AND OIL OPERATED RELAY</u>	
	a	Make	
	b	Type	
	c	Size	
	d	Whether supervisory alarm and trip contacts	

provided and their sizes and Nos.

- | | | | | |
|----|------|--|------------------------|--|
| 43 | [I] | <u>TEMPERATURE INDICATORS</u> | Oil Temp.
Indicator | Winding Temp.
Indicator |
| | | a | | Make and type |
| | | b | | Permissible setting ranges for alarm and trip |
| | | c | | Number of contacts |
| | | d | | Current rating of each contact |
| | | e | | Whether supervisory alarm contacts provided? |
| | | f | | Size [lxbxd] |
| | | g | | Nos. |
| | | h | | Ratio and type of CT used for winding temperature indicators. |
| | [II] | <u>OPTIC FIBER TEMPERATURE SYSTEM</u> | | |
| | | a. | | MAKE & TYPE |
| | | b. | | Whether the offered Optic Fiber Temperature System fulfills the stipulations for the same as per this Specification |
| | | c. | | Whether the end-user's certificate for offered Optic Fiber Temperature System, from Indian Utilities furnished |
| | | d. | | Whether, the Bidder has got past experience of supply of Transformers with Optic Fiber Temperature System [YES/NO] |
| | | e. | | If 'YES', please state the No. of such Transformers, supplied along with the name(s) of Organisation(s), to whom supplied with Make of the Optic Fiber Temperature System, supplied and performance of the same. |
| | | f. | | Address of FO system supplier |
| | | g. | | Nos. of channels |
| | | h. | | Sensors per channel |
| | | i. | | Channel switching frequency |
| | | j. | | Sampling sensor rate |
| | | k. | | Switching reliability |
| | | l. | | Wave length operational length |
| | | m. | | PC output interface |
| | | n. | | Data display |
| | | o. | | Self Diagnostic |
| | | p. | | Temp range & resolution |
| | | q. | | Accuracy |
| | | r. | | Response time |
| | | s. | | Front panel display |
| | | t. | | Probe signal strength readout |
| | | u. | | Input power |
| | | v. | | Serial Output |
| | | w. | | Fiber type |
| | | x. | | Nos. of relays |
| | | y. | | Temperature Data storage |
| | | z. | | LED alarm indicators |
| | | aa. | | System fault relay |

- bb. System fault status indicator
- cc. Surge protection
- dd. Connectors
- ee. Operating temperature range
- ff. Storage temperature
- gg. Probes material & dimensions
- hh. Analog output
- ii. SCADA compatibility
- jj. Nos. of probes
- kk. Tank wall adaptor plate with cover
- ll. EMI/RMI susceptibility
- mm. Signal conditioner compatibility
- nn. Connector for tank wall feed through

44 APPROXIMATE OVERALL DIMENSIONS OF TRANSFORMER INCLUDING COOLING SYSTEM, TAP CHANGING GEAR ETC.

- a Length [mm]
- b Breadth [mm]
- c Height [mm]

45

- a Minimum clearance height for lifting core and winding from tank [mm]
- b Minimum clearance height for lifting tank cover [mm]

46

SHIPPING DETAILS

- a Approximate weight of heaviest package [Kg.]
- b Approximate dimensions of largest Package [Kg.]

47

Transformers will be transported with oil/gas.

48

Size of rail recommended for the track.

49

Details of Neutral Current Transformers

- a Quantity
- b Type and voltage class
- c No. of cores
- d Ratio
- e VA burden
- f Accuracy class
- g Minimum knee point voltage [volts]
- h Maximum magnetization current at minimum knee point voltage [mA]
- i Maximum secondary winding resistance at 75°C[ohms]

50

MARSHALLING KIOSK

- a Make and type
- b Details of apparatus proposed to be housed in the kiosk

51

Details of anti-earthquake device provided, if any

52

Separate conservator and Buchholz relay provided

53

TAP CHANGING EQUIPMENT

[These details refer to the basic rating of O.L. T.C. as guaranteed by OLTC manufacturers]

- a Make
 - b Type
 - c Power flow [Uni.-directional/bi – directional/restricted bi-directional]
 - d Rated voltage to earth [KV]
 - e Rated current [Amps.]
 - f Step voltage [volts]
 - g Number of steps
 - h Control - manual/local-electrical/remote-electrical
 - i Voltage control [Automatic/Non -automatic]
 - j Line drop compensation provided/not provided
 - k Parallel operation
 - l protective devices
 - m Auxiliary supply details
 - n Time for complete tap change [one step][Sec.]
 - o Diverter selector switch transient time [cycles]
 - p Value of maximum short circuit current [Amps] [minimum]alongwith duration
 - q Maximum impulse withstand test voltage with 1.2/50 micro seconds full wave between switch assembly and ground [KVP]
 - r Maximum power frequency test voltage between switch assembly and earth [KV-rms]
 - s Maximum impulse withstand test voltage with 1.2/50 micro-seconds across the tapping range [KVP]
 - t Approximate overall dimensions of tap changer [WxBxD] in mm.
 - u Approximate overall weight [Kg.]
 - v Approximate mass of oil [Kg.]
 - w Particulars of the OLTC control panel for installation in control room
- 54** **DRIVING MECHANISM BOX**
- a Make and type
 - b Details of apparatus proposed to be housed in the box
- 55** Types of terminal connectors and drawing No
- a HV
 - b LV
- 56** Details of painting, galvanization conforms to this Specification [Yes/No]
- 57** Type of oil level indicator and whether Supervisory alarm contact for low oil level provided [Yes/No]
- 58** Type and size of thermostat to be used
- 59** No. of breathers provided [Nos.]
- 60** Type of dehydrating agent used for breathers
- 61** **Valve sizes and numbers**
- a Drain valves- mm-Nos.
 - b Filter valves- mm-Nos.
 - c Sampling valves- mm-Nos.
 - d Radiator valves- mm-Nos.

- e Other valves- mm-Nos.
- 62 a) Type and make of PRV.
b) No. of each type of devices per transformer
c) Min. pressure at which device operates.
- 63 Please enclose the list of accessories and fittings, being provided on transformer. Please confirm, these are as stipulated in the tender.
- 64 Whether the transformer, covered is fully type tested and if so, whether copies of type test certificates, enclosed with the tender.
- 65 Whether tenderer can supply transformer, wound on vertical coil winding machine. Preference shall be given to the tenderer who will ensure supply of transformer wound on vertical winding machines.
- 66 In case Sl.No.65 is not confirmed, what are the additional pre-cautions which shall be taken by the tenderer to justify that the coil, wound on horizontal machine shall be equivalent in all respects to that which are wound on vertical winding machine.
- 67 What are the arrangements, available for jointing the winding. Preference shall be given to the tenderer using high-frequency brazing machines. In case other jointing techniques are used, adequacy of the same is to be recorded. Please note that bolted joints in the winding are not acceptable. This should be confirmed here
- 68 Please confirm that you will guarantee maximum Impedance variation between phases within the limit of 2% only.
- 69 a) Please confirm that the transformer shall be dried by vapour-phase drying method. Please specify level of dryness.
b) In case, other methods of drying are used, the level of dryness, so achieved should be identical to that by VPD. Adequacy of such system should be justified.
- 70 Please confirm whether the In-House facilities for all routine tests as per this Tender Specification are available with the tenderer and the tenderer shall agree to conduct these tests on the transformer in the event of order.
- 71 **Whether the Tenderer has got In-House core-cutting facility for cutting core materials for the transformer ratings as offered. (YES/NO)**
- 72 **If 'YES', following informations/confirmations are required: -**
- a. Name of the manufacturer of HIB Grade core material from whom core materials will be directly imported or through their accredited marketing organization of repute. If to be imported through the accredited Marketing Organisation, Please state the name of such Marketing Organisation and please enclose the relevant documents with the Tender Offer regarding accreditation of the said Marketing Organisation by the manufacturer of the HIB core material.
- b. Grade, Trade Name and Thickness of the core material, to be imported
- c. Whether agreed for witnessing of core materials by OPTCL's representative(s)

- d. Whether, the Bidder has past experience towards direct import of core materials. If 'YES', the copies of recent past Import documents to be furnished with the Tender Offer (Please state, whether the said import documents are enclosed with the Tender Offer)
- e. Whether, the Bidder has got In-House CNC Machine facility for cutting of core materials
- f. Whether the Bidder is agreed to follow the procedures, as stipulated at Cl.No.5.4.8 (o), (p) &(q) of this Technical Specification, as applicable for those, who have got In-House core-cutting facility

73 If the Bidder has no In-House core-cutting facility, the following informations/confirmations are required: -

- a. Name of the core manufacturer of core materials from whom core materials will be directly imported or through their accredited marketing organization of repute. If to be imported through the accredited Marketing Organisation, Please state the name of such Marketing Organisation and please enclose the relevant documents with the Tender Offer regarding accreditation of the said Marketing Organisation by the manufacturer of the HIB core material.
- b. Grade, Trade Name and Thickness of the core material, to be imported
- c. Name of the core-cutting vendor and whether the said vendor has got In-House CNC Machine facility for cutting of core materials and whether the said vendor has been accredited by ISO
- d. Whether, the Bidder has past experience towards direct import of core materials. If 'YES', the copies of recent past Import documents to be furnished with the Tender Offer (Please state, whether the said import documents are enclosed with the Tender Offer)
- e. Whether the Bidder is agreed to follow the procedures, as stipulated at Cl.No.5.4.8 (o), (p) &(q)(1), (2), (3), (4), (5),(6) & (7) of this Technical Specification, as applicable for those, who have got no In-House core-cutting facility.

74. Please confirm that the facility for partial discharge test Is available with the tenderer and the tenderer shall agree to conduct This test on transformer in the event of order.

Place
Date

Bidder's name:
Signature, Designation, Seal

N.B.

The bidder must fill up all the points of GTP for offered item(s). Instead of indicating “refer drawing” or “as per IS/IEC”, the exact value(s) must be filled in.

GUARANTEED TECHNICAL PARTICULARS NITROGEN INJECTION SYSTEM FOR PREVENTION OF FIRE/ EXPLOSION FOR TRANSFORMERS/REACTORS.

Sr. No.	Description	Guaranteed Particulars
1	Name of Manufacture and country of origin	
2	Reference standards	
3	Details of system equipments	
4	FEC (Fire Extinguishing Cubicle)	
4.1	Dimensions (LXBXH) mm	
4.2	Weight	
4.3	Capacity of Nitrogen cylinder	
4.4	Number of cylinders	
4.5	Pressure of Nitrogen filing	
4.6	Minimum distance of FE cubicle from the transformer	
4.7	Method of mounting	
4.8	Whether the following items are provided in FE cubicle. If so furnish make, type & other details	
4.9	Contact Manometer	
4.10	Pressure Regulator	
4.11	Oil Release Unit	
4.12	Gas release unit	
4.13	Oil drain assembly	
4.14	Pressure / limit switches	
4.15	No. of contacts & spare contacts (NO & NC)	
4.16	Oil drain Valve (ABOVE FEC)	
4.17	Make	
4.18	Type	
4.19	Size	
4.20	Type of metal	
4.21	Nitrogen Injection Valve (Above FEC)	
4.22	Make	
4.23	Type	
4.24	Size	
4.25	Oil drain pipe	
4.26	Size	
4.27	Length	
4.28	Number of openings in the transformer tank	
4.29	Material	
5	Control Box	
5.1	Dimensions (LXBXH) mm	

5.2	mm	
5.3	Type & Thickness of sheet steel	
5.4	Details of components provided in the control box	
5.5	Control voltage	
5.6	Method of mounting	
5.7	Whether audio and visual alarm provided?	
6.	Transformer Conservator Isolation Valve	
6.1	Make	
6.2	Type	
6.3	Location	
6.4	Whether suitable for pipe of size 80 mm dia	
6.5	No. of contacts & spare contacts (NO & NC)	
6.6	Padlocking provision	
7	Detectors	
7.1	Make	
7.2	Type	
7.3	Quantity required	
7.4	Method of fixing	
7.5	Effective heat sensing area	
7.6	Temperature recommended for effective heat sensing	
7.7	Number of contacts NO / NC	
7.8	Necessity and condition of Refilling	
8	Whether approved by Tariff Advisory Committee of India	
9	TECHNICAL PARTICULARS FOR NITROGEN INJECTION SYSTEM FOR PREVENTION OF TRANSFORMER EXPLOSION	
10	Power Supply	
10.1	Control box	
10.2	FEC (lighting)	
10.3	Extinction period	
10.4	On system activation	
10.5	On commencement of Nitrogen injection	
11	FEC Suitable for capacity	
11.1	Dimensions (LXBXH) mm	
11.2	Weight	
11.3	Nitrogen cylinder capacity	
12	Control Box	
12.1	Dimensions (LXBXH) mm	
12.2	Weight	
13	Detectors	
13.1	Heat sensing temperature	
13.2	Time of operation	Transformer Tank Explosion Prevention
	For system activation	Fire Extinction
	For reduction of pressure in	

tank by Nitrogen Release		
--------------------------	--	--

13.3 Any other technical details not covered above.

N.B. The bidder must fill up all the points of GTP for offered item(s). Instead of indicating “refer drawing” or “as per IS/IEC”, the exact value(s) must be filled in.

ANNEXURE - V.

ADDITIONAL SCHEDULE OF INFORMATIONS.

(To be furnished by the bidder along with the Tender Offer)

<u>Sl. No.</u>	<u>Item.</u>	<u>Remarks.</u>
----------------	--------------	-----------------

SIGNATURE OF THE TENDERER
WITH SEAL AND DATE

ANNEXURE - VI.

CHECK-LIST TOWARDS TYPE TEST REPORTS.

[To be filled in by the Bidder]

Name of the Type Test.	Date of Test	Name of the Laboratory where the test has been conducted.	Whether Laboratory is Govt. Approved.	Name of the Govt. Organisation Which has witnessed the type test.	Whether the test report is valid as per Clause No.6.4.1 of TS	Whether the copy of test report in complete shape along with the drawings etc. furnished or not?	Whether the type tested 40 MVA,220/33KV transformers fulfills the technical requirements as per TS	Remarks
1	2	3	4	5	6	7	8	9

Place

Dated:

SINGATURE OF THE TENDERER
WITH SEAL AND DATE:

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

ANNEXURE

-

VII

CALIBRATION STATUS OF TESTING EQUIPMENTS AND INSTRUMENTS / METERS.

[To be filled in by the Bidder]

Name of the Test.	Meters & Equipment required for the corresponding test with range accuracy, make and Sl.No.	Date of calibration	Due date of calibration	Name of the Calibrating Agency.	Whether calibrating agency is Govt. Approved.
1	2	3	4	5	6

Whether documents related to Govt. approval of the Calibrating Agency furnished.	Whether the meters/equipments fulfill the accuracy class as per calibration report.	Whether calibrating Agency has put any limitation towards the use of the particular meters/equipments. If yes, state the limitations.	In spite of imposed limitations, whether the particular meter/equipments can still be used. Justify its use for corresponding test(s)	Remarks.
7	8	9	10	11

Place

Dated:

SINGATURE OF THE TENDERER
WITH SEAL AND DATE:

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

CHECK - LIST FOR DELIVERY SCHEDULE

[To be filled in by the Bidder]

<u>Sl. No.</u>	<u>Description of the equipment.</u>	<u>Quantity.</u>	<u>Delivery Schedule</u>
----------------	--------------------------------------	------------------	--------------------------

Place:

SIGNATURE OF THE TENDERER

Dated:

WITH SEAL AND DATE:

N: B:-Period of delivery is to be quoted from the date of issue of the purchase order only. Any other form of quotation such as delivery from the date of approval of drawings or any other form will not be accepted.

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

**ABSTRACT OF TERMS AND CONDITIONS.
[TECHNICAL]****[To be filled in by the Bidder]**

- | | | |
|-----|--|--------|
| 1 | Whether accepted Clause 1.0 “Scope” and its Sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 2 | Whether accepted Clause 2.0 “Standards” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 3 | Whether accepted Clause 3.0 “Auxiliary Power Supply”. If ‘no’ then indicate your terms. | Yes/No |
| 4 | Whether accepted Clause 4.0 “Principal Parameters”. If ‘no’ then indicate your terms. | Yes/No |
| 5 | Whether accepted Clause 5.0 “General Technical Requirements” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 6 | Whether accepted Clause 6.0 “Inspection and Testing” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 7 | Whether accepted Clause 7.0 “Test Reports”. If ‘no’ then indicate your terms. | Yes/No |
| 8 | Whether accepted Clause 8.0 “List of Transformer Accessories and Test Certificates required for them”. If ‘no’ then indicate your terms. | Yes/No |
| 9 | Whether accepted Clause 9.0 “Inspection” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 10 | Whether accepted Clause 10.0 “Quality Assurance Plan” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 11 | Whether accepted Clause 11.0 “Documentation” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 12 | Whether accepted Clause 12.0 “Packing and Forwarding” and its sub-clauses. If ‘no’ then indicate your terms. | Yes/No |
| 13. | Whether accepted Clause 13.0 “Supervision of Erection, Testing and Commissioning”. If ‘no’ then indicate your terms. | Yes/No |
| 14 | Whether accepted Clause 14.0 “Quantity and Delivery requirements”. If ‘no’ then indicate your terms. | Yes/No |

15	Whether accepted Clause 15.0. If 'no' then indicate your terms.	Yes/No
16	Whether accepted Clause 16.0. "Method of Technical Evaluation". If 'no' then indicate your terms.	Yes/No
17	Whether furnished 'ANNEXURE-II' in full shape.	Yes/No
18	Whether furnished 'ANNEXURE-III' (Loss calculations) in full shape.	Yes/No
19	Whether furnished 'ANNEXURE-IV' (G.T.P.) in full shape.	Yes/No
20	Whether furnished 'ANNEXURE-V' (Additional Schedule of Informations).	Yes/No
21	Whether furnished 'ANNEXURE-VI' (Check List towards type test reports). in full shape.	Yes/No
22	Whether furnished 'ANNEXURE-VII' (Calibration Status). in full shape.	Yes/No
23	Whether furnished 'ANNEXURE-VIII' in full shape (Check list for Delivery Schedule).	Yes/No
24	Whether furnished B.H. and Sp. Loss Curve for the core material?	Yes/No
25	Whether furnished "Knee Point Voltage" Graph?	Yes/No
26	Whether furnished 'Short Circuit Temperature rise' and 'force calculation' as per clause No.5.1.2 of T.S.?	Yes/No
27	Whether furnished calculation towards H.V.Air-core reactance and 'Magnetising Inrush current.?	Yes/No
28.	Whether all other documents/calculations relating to different clauses as per the Technical Specification furnished?	Yes/No

PLACE:

DATE:

SIGNATURE OF THE TENDERER
WITH SEAL AND DATE

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

Annexure-X.

[Manufacturer's Authorization for Optic Fiber Temperature System (OFTS) being offered]

Ref: _____

Date: _____

To,

The SG.M, CPC, OPTCL,1ST FLOOR, MULTI STORIED BUILDING, ODISHA POWER TRANSMISSION CORPORATION LIMITED,BHUBANESWAR.

We, _____ who are established and reputed manufacturer, meeting the Qualifying requirement of Supply of **Optic Fiber Temperature System (OFTS)** equipment as per your tender specification, having factories in _____ do hereby authorize M/s _____ to offer our equipment for tender against NIT No. _____ & Tender Specification -----

We hereby undertake that **Optic Fiber Temperature System (OFTS)** equipment being offered will meet the relevant technical specification of _____. The supervision of erection, testing and commissioning of the offered equipment at site which will be carried out by our Service Engineer. We hereby confirm that the necessary spares for the above item(s) shall be available for the period for 10 years from the date of commissioning of transformer.

(Signature of Authorized Representative)

Name:

Designation:

Common Seal of the Company:

WITNESS SIGNATURE WITH ADDRESS

1.

2.

Notes:-

- 4) The manufacturer authorization shall be submitted from the Optic Fiber Temperature System (OFTS) equipment manufacturer(s), which should be filled in non-judicial stamp paper of worth Rs.100/- and duly Notarized.
- 5) The bidder shall furnish the copy of the Power of Attorney of the Optic Fiber Temperature System (OFTS) equipment manufacturer(s) in the name of their above authorized signatory, along with the bid.
- 6) The bidder shall submit the manufacturer authorization from such manufacturer(s) who meets the requirements as stated for the equipment.

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format.

Annexure-XI.

[Manufacturer's Authorization for Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES) being offered]

Ref:_____

Date:_____

To,
The SG.M, CPC, OPTCL,1ST FLOOR, MULTI STORIED BUILDING, ODISHA POWER TRANSMISSION CORPORATION LIMITED,BHUBANESWAR.

We,_____who are established and reputed manufacturer, meeting the Qualifying requirement of Supply of **Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES)** equipment as per your tender specification, having factories in_____do hereby authorize M/s_____to offer our equipment for tender against NIT No._____ & Tender Specification -----

We hereby undertake that **Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES)** equipment being offered will meet the relevant technical specification of_____. The supervision of erection, testing and commissioning of the offered equipment at site which will be carried out by our Service Engineer. We hereby confirm that the necessary spares for the above item(s) shall be available for the period for 10 years from the date of commissioning of transformer.

(Signature of Authorized Representative)

Name:

Designation:

Common Seal of the Company:

WITNESS SIGNATURE WITH ADDRESS

1.

2.

Notes:-

4. The manufacturer authorization shall be submitted from the Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES) equipment manufacturer(s), which should be filled in non-judicial stamp paper of worth Rs.100/- and duly Notarized.
5. The bidder have furnish the copy of the Power of Attorney of the Nitrogen Injection Type Fire Prevention & Extinguishing System(NIFPES) equipment manufacturer(s) in the name of their above authorized signatory, along with the bid.
6. The bidder shall submit the manufacturer authorization from such manufacturer(s) who meets the requirements as stated for the equipment.

NB- The Bidders are required to up load this sheet duly filling the required data, in PDF format